



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# RS-232 DATA ACQUISITION MODULE

232SDA12



## PRODUCT FEATURES

- Automatic Baud Rate Detection
- 11 Channels of 12-bit A/D
- 0.610mV A/D Resolution (with 2.5VDC Reference)
- 3 Digital Inputs (-30 to +30 VDC)
- 3 Digital Outputs (0 to 5 VDC)

The 232SDA12 provides a low-cost, easy to use solution for serial port data acquisition. It offers 11 channels of 12-bit A/D inputs, 3 digital outputs, and 3 digital inputs. With these features, the module can be used to sense a variety of external conditions and to control a variety of devices. The module comes with a demo program in QuickBasic. A data logging utility is included to provide a simple way to import data into other programs (such as Excel). These programs are Windows compatible (95, 98, NT, 2K, XP, and Vista). RS-485 and 10-bit A/D versions are available (232SDA10, 485SDA10, and 485SDA12).

### Operation

- A manual is contained on the CD ROM which ships with the module.
- There are only three commands required to control the 232SDA12: Read A/D, Read Digital I/O, and Set Output State. Bit error detection is also possible. Refer to the manual for information concerning these commands.
- A/D Converter: The module has 11 channels of 12-bit A/D inputs. The full-scale voltage can be set anywhere from 2.5 VDC to 5.0 VDC. A 5 VDC reference is available to provide a 0 to 5 VDC range without any external components. The A/D converter has a conversion time of approximately 10 microseconds. However, the sampling rate is limited by the serial communications. The actual sampling rate for a single channel is approximately 120 samples per second at 9600 baud. This rate drops to 25 samples per second when sampling all of the channels. The A/D inputs are made via a DB-25 female connector.
- Digital I/O Lines: The 232SDA12 has 3 digital inputs and 3 digital outputs. The digital outputs are CMOS/TTL compatible. The digital inputs are CMOS/TTL compatible and can handle voltages from -30 to +30 VDC. A DB-25 female connector is used.
- Digital I/O Lines: The 232SDA12 has 3 digital inputs and 3 digital outputs. The digital outputs are CMOS/TTL compatible. The digital inputs are CMOS/TTL compatible and can handle voltages from -30 to +30 VDC. A DB-25 female connector is used.
- Communications: Connect the unit to your PC. The baud rates between 1200 and 9600 are automatically detected. Format is 8 data bits, 1 stop bit, and no parity. The 232SDA12 is a DCE device. Refer to the product manual for more information.

## ORDERING INFORMATION

MODEL NUMBER	PC PORTS
232SDA12	RS-232 Data Acquisition Module

## ACCESSORIES

- 232PS - 12VDC@100mA Power Supply, Wall transformer
- 232CAM - 6 ft PC-AT Computer to Modem Cable

USA, Canada: check with your local distributor for product availability and options. Certified for major North American carriers. Contact B+B SmartWorx for latest approvals.

# RS-232 DATA ACQUISITION MODULE

232SDA12



## SPECIFICATIONS

### ANALOG TO DIGITAL CONVERTER

Resolution:	12 Bit
Channels:	11
Reference Range:	5.0 VDC Max (1.221 mV per Bit)
	2.5 VDC Min (0.610 mV per Bit)
A/D Ref Input (negative):	0 to 2.5 VDC
A/D Ref Input (positive):	2.5 to 5.0 VDC
Input Voltage Range:	Negative 0.3 to Positive 5.3 VDC
Total Adjusted Error:	Plus or minus 1.0 LSB Max.
Note: A/D input must be driven from a source impedance less than 1 k ohm	

### DIGITAL OUTPUTS

Channels:	3
Low Voltage:	0.6 VDC @ 8.7 milliamps
High Voltage:	4.3 VDC @ -5.4 milliamps

### COMMUNICATIONS

Standard:	RS-232 (unit is DCE)
Data Rate:	1200 to 9600 baud (automatic detection)
Format:	8 data bits, 1 stop bit, no parity
Connector:	DB-25 Female

### 5 VOLT REFERENCE

Output Voltage:	4.975 VDC to 5.025 VDC (5.0 VDC typical)
Accuracy:	Plus or minus 0.5%
Max Output Level:	5 mA

### DIGITAL INPUTS

Channels:	3
Voltage:	Minus 30 to Positive 30 VDC
Low Voltage:	Minus 30 to Positive 1 VDC
High Voltage:	Positive 2 to Positive 30 VDC
Leakage Current:	1 micro amp maximum

### POWER SUPPLY

Input Voltage:	7 to 18 VDC
Current:	5 milliamps (does not include external devices)

## I/O CONNECTOR PIN-OUT

PIN	FUNCTION
1	Ground
2	+ 12 VDC Output (see note)
3	Digital Input Number 0
4	Digital Input Number 1
5	Digital Input Number 2
6	Digital Ground
7	Analog Ground
8	A/D Input Number 0
9	A/D Input Number 1
10	A/D Input Number 2
11	A/D Input Number 3
12	A/D Input Number 4
13	A/D Input Number 5
14	Digital Output Number 0
15	Digital Output Number 1
16	Digital Output Number 2
17	+5 VDC Output
18	A/D Reference Input (+)
19	A/D Reference Input (-)
20	No Connection
21	A/D Input Number 6
22	A/D Input Number 7
23	A/D Input Number 8
24	A/D Input Number 9
25	A/D Input Number 10

Note: Actual output is equal to power supply input minus 0.7 VDC

## RS-232 CONNECTOR PIN-OUT

PIN	SIGNAL	DIRECTION	NOTES
2	Transmit Data (TD)	Input	Connection is required
3	Receive Data (RD)	Output	Connection is required
4	Request to Send (RTS)	Input	May be used to power unit if kept high
5	Clear to Send (CTS)		Internally looped back to RTS
6	Data Set Ready (DSR)		Internally looped back to DTR
7	Signal Ground (SG)		Connection is required
8	Data Carrier Detect (DCD)		Internally looped back to DTR
20	Data Terminal Ready (DTR)		May be used to power unit if kept high