



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# PSR-SCP- 24DC/SSM/2X1

# PSR-SPP- 24DC/SSM/2X1

## Safety Relay With Downtime Monitoring



### INTERFACE

Data Sheet

© PHOENIX CONTACT - 05/2006

### Description

The **PSR-...- 24DC/SSM/2X1** safety relay can be used in safety circuits according to DIN EN 60204-1/VDE 0113-1. Depending on the external wiring, up to safety category 4 according to EN 954-1 can be achieved. The relay meets the requirements of SIL 3 according to EN 61508. Control is implemented via two PNP or 2-wire proximity switches that switch with a 180° overlap (see "Connection Example" on page 6).

The requirements of the following standards are met once the safety equipment has been in use for the relevant period of time or a function test is carried out (experiment test).

Standard	Level	Period of Use
IEC 61508	SIL 3	48 months
EN 954-1	Cat. 4	12 months

The relay has two positively-driven N/O contacts that meet stop category 0 according to DIN EN 60204-1/VDE 0113-1.



Observe the safety instructions on page 3.



Make sure you always use the latest documentation. It can be downloaded at [www.download.phoenixcontact.com](http://www.download.phoenixcontact.com).

A conversion table is available on the Internet at [www.download.phoenixcontact.com/general/7000\\_en\\_00.pdf](http://www.download.phoenixcontact.com/general/7000_en_00.pdf).



This data sheet is valid for all products listed on the following page:

## Ordering Data

### Safety Relays

Description	Type	Order No.	Pcs./Pkt.
Safety relay with downtime monitoring, with screw connection	PSR-SCP- 24DC/SSM/2X1	2981567	1
Safety relay with downtime monitoring, with spring-cage connection	PSR-SPP- 24DC/SSM/2X1	2981570	1

### Documentation

Description	Type	Order No.	Pcs./Pkt.
Application manual for PSR safety relays	UM EN SAFETY RELAY APPLICATION	2888712	1

## Technical Data

### Input Data

Nominal input voltage $U_N$	24 V DC
Permissible range	0.85 - 1.1 x $U_N$
Typical current consumption at $U_N$ (without proximity switch)	60 mA
Voltage at +S1, +S2	24 V DC
Typical response time (K1, K2) at $U_N$	12 ms
Typical release time (K1, K2) at $U_N$	8 ms
Surge protection	Suppressor diode
Status indicators (K1, K2)	Green LED
Switching range	
Downtime at	< 2 Hz
Operation at	> 2.5 Hz
Cut-off frequency	2 kHz

### Output Data

Contact type	2 enable current paths, 2 signaling current paths		
Contact material	Silver nickel 15 (AgNi15), hard gold-plated (5 $\mu$ m Au)		
Maximum switching voltage	250 V AC/DC		
Minimum switching voltage	10 V AC/DC		
Limiting continuous current	5 A		
Total current	On request		
Maximum inrush current	5 A		
Minimum inrush current	10 mA		
Maximum shutdown power	Ohmic load $\tau = 0$ ms	Inductive load $\tau = 40$ ms	
	24 V DC	192 W	48 W
	48 V DC	144 W	24 W
	110 V DC	88 W	33 W
	220 V DC	66 W	22 W
	250 V AC	2000 VA	
Minimum switching power	0.25 W		
Mechanical service life	50 x 10 <sup>6</sup> cycles, approximately		
Switching capacity	<b>Cycles</b>	<b>DC13</b>	<b>AC15</b>
	<b>360/h:</b>	24 V:	2 A
		230 V:	–
			3 A
Short-circuit protection of the output circuits, external	6 A gL (automatic device C8)		

**General Data**

Permissible ambient operating temperature	-20°C ... +55°C
Nominal operating mode	100% operating factor
Degree of protection according to VDE 0470-1	
Housing	IP40
Connection terminal blocks	IP20
Installation location	IP54, minimum
Mounting position	Any
Air and creepage distances between circuits	According to EN 60664/VDE 0110
Basic insulation <sup>1</sup>	
Impulse voltage withstand level	4 kV <sup>1</sup>
Pollution degree	2
Surge voltage category	III
Dimensions (W x H x D):	
PSR-SCP- 24DC/SSM/2X1	22.5 mm x 99 mm x 114.5 mm
PSR-SPP- 24DC/SSM/2X1	22.5 mm x 112 mm x 114.5 mm
Conductor cross section	0.2 mm <sup>2</sup> ... 2.5 mm <sup>2</sup>
Housing material	Polyamide PA, not reinforced

<sup>1</sup> Safe isolation, increased insulation, and 6 kV between input circuit and output contact current paths.

**Tests/Approvals**

TÜV (German Technical Inspectorate)



UL

applied for

**Safety Instructions**

- During operation, parts of electrical switching devices carry hazardous voltages.
- Before working on the device, disconnect the power.
- Please observe the safety regulations of electrical engineering and industrial safety and liability associations. Disregarding these safety regulations may result in death, serious personal injury or damage to equipment.
- Startup, assembly, modifications, and upgrades may only be carried out by a skilled electrical engineer.



- For emergency stop applications, the machine must be prevented from restarting automatically by a higher-level control system.
- Protective covers must not be removed when operating electrical switching devices.



- In the event of an error, replace the device immediately.
- Repairs, especially if the housing must be opened, may only be carried out by the manufacturer or authorized persons. Otherwise the warranty is invalidated.




The device must be operated in a closed control cabinet (according to EN 61508-6:2001, Table 01).



When operating relay modules the operator must meet the requirements for noise emission for electrical and electronic equipment (EN 61000-6-4) on the contact side and, if required, take appropriate measures.



## Structure



PSR-SCP- 24DC/SSM/2X1

PSR-SPP- 24DC/SSM/2X1

Figure 1 Structure

- 1 Metal lock for fixing on the DIN rail
- 2 COMBICON plug-in screw terminal blocks
- 3 COMBICON plug-in spring-cage terminal blocks
- 4 13-14, 23-24: N/O contact
- 5 31-32, 41-42: N/C contact
- 6 "Output" LED: Lights up in the event of a downtime, OFF in the event of movement, flashes in the event of a device error
- 7 "Mode" LED: Lights up when "Device OK", flashes in the event of a sensor error
- 8 "Power" LED: Lights up in the event of voltage at A1/A2
- 9 +S1, +S2: Supply voltage for proximity switches IN1, IN2
- 10 A1, A2: Supply voltage connection
- 11 MO: Downtime alarm output
- 12 FO: Error output (+24 V = device OK)
- 13 IN1, IN2: Proximity switch connection

## Block Diagram




Figure 2 Block diagram

## Function

If the 24 V DC operating voltage is applied at terminal blocks A1 and A2, the electronics checks (in the stop state) whether at least one of the proximity switches provides a signal at input IN1 or IN2.

The FO diagnostic output indicates the ready state with +24 V. The "Power" and "Mode" LEDs light up. If this is the case (one or both proximity switches provide a signal), the internal output relays switch to the operated condition. N/O contacts 13-14 and 23-24 are closed, N/C contacts 31-32 and 41-42 are open, and the "Output" lights up. Alarm output MO indicates +24 V.

The outputs remain active in their switch position as long as no signal change is generated at inputs IN1 and IN2 by a movement.

N/O contacts 13-14 and 23-24 open and N/C contacts 31-32 and 41-42 close if a signal change with a frequency > 2.5 Hz is detected at inputs IN1 and IN2. Alarm output MO is a high-resistance output.

If the input circuit frequency is less than 2 Hz (stop state entered or movement not hazardous), relays K1 and K2 switch. N/O contacts 13-14 and 23-24 are closed and N/C contacts 31-32 and 41-42 are open. Alarm output MO indicates +24 V.

In the event of an error (sensor error), the "Mode" LED flashes and FO is a high-resistance output.

For a connection example, please refer to page 6.

## Assembly and Startup



**Before working on the device, disconnect the power.**

In order to comply with UL approval, use copper cables that are designed for operating temperatures > 75°C. For reliable and safe-to-touch contacts, strip the cable ends as follows:




Figure 3 PSR-SCP- 24DC/SSM/2X1




Figure 4 PSR-SPP- 24DC/SSM/2X1

### Mounting the Proximity Switches



**Prevent cross circuits between IN1 and IN2 by using a suitable cable installation.**

#### Requirements for a Gearwheel or Gear Rack:

The design of the gearwheel or gear rack is of particular importance for safe operation:

The surface of the gearwheel must always be greater than the gap between the teeth. This ensures that at least one proximity switch is actuated.

#### Arrangement of the Proximity Switches:

- Tooth > gap
- Tooth > switch diameter
- Depth of gap > switching interval of the switch
- $a \leq (\text{switching interval of the switch}/2)$




Figure 6 Mounting the proximity switches

### Connection Example




Figure 5 Two-channel downtime monitoring using two PNP or 2-wire proximity switches, suitable up to safety category 3\*, SIL 3

© PHOENIX CONTACT 05/2006

\* Safety category 4 is possible if a test is performed within 24 hours of machine downtime to detect the internal sensor errors.