



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com


Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Adafruit Feather M0 RFM69 Packet Radio – 433MHz

PRODUCT ID: 3177



Description

Feather is the new development board from Adafruit, and like its namesake it is thin, light, and lets you fly! We designed Feather to be a new standard for portable microcontroller cores. This is the Adafruit Feather M0 RFM69 Packet Radio (433 MHz) – our take on an microcontroller with a RFM69 HCW packet radio transceiver plus built in USB and battery charging. Its an Adafruit Feather M0 with a 433MHz radio module cooked in! We have other boards in the Feather family, check'em out here.

This is the 433 MHz radio version. We also sell a 900 MHz version of the same radio chipset!

At the Feather M0's heart is an ATSAM21G18 ARM Cortex M0 processor, clocked at 48 MHz and at 3.3V logic, the same one used in the new Arduino Zero. This chip has a whopping 256K of FLASH (8x more than the Atmega328 or 32u4) and 32K of RAM (16x as much)! This chip comes with built in USB so it has USB-to-Serial program & debug capability built in with no need for an FTDI-like chip.

To make it easy to use for portable projects, we added a connector for any of our 3.7V Lithium polymer batteries and built in battery charging. You don't need a battery, it will run just fine straight from the micro USB connector. But, if you do have a battery, you can take it on the go, then plug in the USB to recharge. The Feather will automatically switch over to USB power when its available. We also tied the battery thru a divider to an analog pin, so you can measure and monitor the battery voltage to detect when you need a recharge.

Here's some handy specs! Like all Feather M0's you get:

Measures 2.0" x 0.9" x 0.3" (51mm x 23mm x 8mm) without headers soldered in

Light as a (large?) feather – 5.8 grams

ATSAMD21G18 @ 48MHz with 3.3V logic/power

No EEPROM

3.3V regulator with 500mA peak current output

USB native support, comes with USB bootloader and serial port debugging

You also get tons of pins – 20 GPIO pins

Hardware Serial, hardware I2C, hardware SPI support

8 x PWM pins

10 x analog inputs

1 x analog output

Built in 100mA lipoly charger with charging status indicator LED

Pin #13 red LED for general purpose blinking

Power/enable pin

4 mounting holes

Reset button

The **Feather M0 Radio** uses the extra space left over to add an RFM69HCW 433 or 900MHz radio module. These radios are not good for transmitting audio or video, but they do work quite well for small data packet transmission when you need more range than 2.4 GHz (BT, BLE, WiFi, ZigBee)

SX1231 based module with SPI interface

Packet radio with ready-to-go Arduino libraries

Uses the license-free ISM band ("European ISM" @ 868MHz or "American ISM" @ 915MHz)

+13 to +20 dBm up to 100 mW Power Output Capability (power output selectable in software)

50mA (+13 dBm) to 150mA (+20dBm) current draw for transmissions

Range of approx. 350 meters, depending on obstructions, frequency, antenna and power output

Create multipoint networks with individual node addresses

Encrypted packet engine with AES-128

Simple wire antenna or spot for uFL connector

Comes fully assembled and tested, with a USB bootloader that lets you quickly use it with the Arduino IDE. We also toss in some headers so you can solder it in and plug into a solderless breadboard. You will need to cut and solder on a small piece of wire (any solid or stranded core is fine) in order to create your antenna. **Lipoly battery and USB cable not included but we do have lots of options in the shop if you'd like!**

Technical Details

51mm x 23mm x 8mm / 2.0" x 0.9" x 0.28"

Weight: 5.6g

[FCC Test Report](#)

[RoHS Test Report](#)

[RoHS Test Report](#)

[REACH Test Report](#)

[RFM69HCW Datasheet](#)

[SX1231 Transceiver Datasheet](#)

Engineered in NYC Adafruit®