



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!




Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





E-Series 12V DC Transformer

40W (SKU #3577), 60W (SKU# 3578)

12V DC Class 2 Voltage LED Drivers Installation Guide



BEFORE YOU BEGIN

This driver is to be installed in accordance with Article 450 of the National Electric Code. The driver must be installed in a well-ventilated area free from explosive gases and vapors. Proper operation requires for free flow of air. As the driver is hardwired, it should only be installed by a qualified electrician.

Precautions Before Installing

Check the label and ensure the driver has the proper input voltage and wattage for the job. Check the wire markings to ensure they match the wiring diagram on this installation guide.

Mounting

Select a suitable location capable of supporting the weight of the driver. Use the two keyholes in the driver case to mount using suitable screws. It is recommended that the driver be mounted vertically with the wiring compartment pointing down.

Input Connections/Grounding

Remove the wiring compartment knockouts and install the clamp connectors provided with the driver. With power turned off, route 12-14 AWG Class 2 in-wall rated cable through the clamp connector and connect one wire to black and one wire to white. For all wire connections use only UL listed wire nuts and connectors of suitable size and style. Connect the ground wire to the driver green wire, *the driver case MUST be grounded in accordance with N.E.C.*

QUICK SPECS

Input Voltage	120V AC
Output Voltage	12V DC
Operating Temperature	-20°C to 70°C (-4°F to 158°F)
Enclosure	IP67 – Dry and damp location rated
Dimensions (inch)	6.77" x 2.67" x 1.26"
Weight	17 oz

Output Connections

Bring 16-22 AWG (18 AWG preferred) thermostat or speaker wire from light fixture through the other clamp connector and connect them to the driver wire- positive to the **red (+)** wire and negative to the **blue (-)** wire.

Dimming

This series of drivers is compatible with most standard TRIAC dimmers. Not compatible with digital fade dimmers.

Please Note- *Low-level flickering may be present with certain switch models, CFL/LED switches are recommended to allow for manual adjustment of dimmer settings. For a complete list of compatible dimmers, please view the product information page.*

To Calculate Voltage Drop

Visit www.magniguage.magnitudeinc.com

