



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




PmodAD2™ Reference Manual

Revised May 24, 2016

This manual applies to the PmodAD2 rev. A

Overview

The PmodAD2 is an analog-to-digital converter powered by the [Analog Devices AD7991](#). Users may communicate with the board through I²C to configure up to 4 conversion channels at 12 bits of resolution.



The PmodAD2.

Features include:

- Up to four 12-bit analog to digital converter channels
- On-board 2.048 V voltage reference
- Jumper selectable reference input
- Small PCB size for flexible designs (1.0 in × 0.8 in)(2.5 cm × 2.0 cm)
- Follows [Diligent Interface Specification](#)
- Library and example code available in [resource center](#)

1 Functional Description

The PmodAD2 utilizes Analog Devices[®] AD7991 to provide up to four channels of 12-bit analog-to-digital conversion.

2 Interfacing with the Pmod

The PmodAD2 communicates with the host board via the I²C protocol. System boards are able to call the Pmod by sending out the device address of 0b0101000 followed by the appropriate read or write bit. If a write bit is chosen, users may then configure the on-board chip to only use certain channels or may immediately start reading the 12 bits of data from the 16-bit data register if the read bit is sent.

Unlike other devices that use I²C, no addresses are associated with these two registers; only the read/write bit at the end of the slave address distinguishes between the two registers. By default, all four channels have analog-to-

digital conversions performed on them sequentially with the supply voltage VCC acting as the voltage reference for the ADC.

After each conversion is performed, the device places itself into power-down mode. Upon a read command, the device will wake itself up and prepare for a conversion, which takes approximately 0.6 μ s. The actual conversion process takes approximately 1.0 μ s.

Pin	Signal	Description
1 & 5	SCL	Serial Clock
2 & 6	SDA	Serial Data
3 & 7	GND	Power Supply Ground
4 & 8	VCC	Power Supply (3.3V/5V)

Table 1. Pinout description table.

Any external power applied to the PmodAD2 must be within 2.7V and 5.5V; however, it is recommended that the Pmod is operated at 3.3V.

3 Physical Dimensions

The pins on the pin header are spaced 100 mil apart. The PCB is 1 inch long on the sides parallel to the pins on the pin header and 0.8 inches long on the sides perpendicular to the pin header.