



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!




## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





### FEATURES

- 3.3V/0.5A, 5V/0.5A or 12V/0.4A outputs; Pin and size-compatible with LM7805 & LM7812 regulators
- Up to 95% efficiency – no heat sinks or thermal derating required
- Two SIP-packages fit existing TO-220 footprints:
  - Vertical-pin models occupy less than 0.1 square in.
  - Optional horizontal pins provide 0.350 in. installed height
- +7.5-36Vdc operating input range; Low 3mA quiescent current
- Built-in filter capacitors – no external components required
- -40 to +70°C operation at full load; Short-circuit protection
- Excellent load ( $\pm 0.2\%$ ) and line ( $\pm 0.3\%$ ) regulation
- Ideal for powering instrumentation from 9V/12V/24V/28V supplies or batteries
- Can be used with unregulated dc supplies protection

Murata Power Solutions' 7805SR-C (5V output), 7812SR-C (12V output) and 7803SR-C (3.3V output) step-down switching regulators are modern drop-in replacements for older, inefficient, LM7805 and LM7812 linear regulators. The 78XXSR's are pin- and size-compatible with industry-standard TO-220 SIP packages. A 260kHz switching frequency provides for efficiencies as high as 95%. Full-load (up to 0.5A) operation from 9V, 12V, 24V, or 36V supplies at ambient temperatures up to +70°C requires no heat sinks, no temperature derating, no forced-air cooling, and no external capacitors.

78SR switching regulators provide many significant improvements over their linear counterparts: lower quiescent current (3mA vs. 5 mA), higher input voltage (40V vs. 32V), and better output accuracy ( $\pm 2\%$  vs.  $\pm 5\%$ ). All these features combine to make 78SR regulators ideal for new or existing LM7805 & LM7812 applications requiring full-load operation at elevated voltages.

### TECHNICAL NOTES

1. **Input/Output (I/O) Filtering:** As shown in the noise and ripple graphs, 78SR switching regulators exhibit excellent low-noise performance with no external I/O capacitors. However, if additional noise reduction is required, be sure to use low-ESR capacitors that are rated for continuous operation (with an additional 20% safety margin) at the highest system voltages and temperatures. Adding external output capacitors will also improve the unit's load-transient response. Applications in which 78SR regulators are located more than 24 inches (61cm) from the input power supply should include an external 47 $\mu$ F/50V (or greater) aluminum electrolytic capacitor, connected as close as possible to the regulator's +Vin and GND terminals (pins 1 and 2). An external input capacitor is particularly important if the input voltage is applied to the regulator via a mechanical switch or relay. Contact bounce at turn-on can produce large inductive current-spikes, and these current spikes can generate damaging voltage transients at the regulator's input terminals.
2. **Input Fusing:** 78SR switching regulators are not internally fused. If fusing their input and/or output terminals is required, use the data shown in the Efficiency Curves as a guide to selecting an appropriate slow-blow fuse.
3. **Input-Output Isolation:** 78SR regulators' internal input and output circuits share a common connection (GND, pin 2); there is no electrical isolation between the INPUT (pin 1) and OUTPUT (pin 3) terminals.
4. **Overvoltage Protection:** 78SR switching regulators do not provide input or output overvoltage protection. In the extremely rare situation in which a catastrophic failure occurs, the output voltage may rise to excessively high levels. If your load must be protected against all possible overvoltage situations, external voltage-limiting circuitry must be provided.
5. **Operation at 40Vdc:** Operating with inputs up to 40Vdc is permissible if, for inputs between 36 and 40Vdc, the maximum load current is reduced to 0.35A for 7805SR-C and 7803SR-C, and to 0.3A for 7812SR-C. Under no circumstances should the input voltage be allowed to exceed 45Vdc.

### Ordering Information

| MPS Part No.                  | Output Voltage | Output Current | Input Voltage |
|-------------------------------|----------------|----------------|---------------|
| <b>Standard Pin Package</b>   |                |                |               |
| 7803SR-C                      | +3.3Vdc        | 0.5A           | +7.5-36Vdc    |
| 7805SR-C                      | +5.0Vdc        | 0.5A           | +7.5-36Vdc    |
| 7812SR-C                      | +12.0Vdc       | 0.4A           | +15-36Vdc     |
| <b>Horizontal Pin Package</b> |                |                |               |
| 7803SRH-C                     | +3.3Vdc        | 0.5A           | +7.5-36Vdc    |
| 7805SRH-C                     | +5.0Vdc        | 0.5A           | +7.5-36Vdc    |
| 7812SRH-C                     | +12.0Vdc       | 0.4A           | +15-36Vdc     |



For full details go to  
[www.murata-ps.com/rohs](http://www.murata-ps.com/rohs)

### TECHNICAL NOTES (continued)

- 6. Soldering & Handling Precautions:** All units are designed to be hand soldered to pc-boards using no-clean solders (+260°C, 5 seconds max.). Water-soluble solders can also be used, but the units must be washed and dried using processes appropriate to the type of solder employed. See the Mechanical Specifications section for pin 1 orientation and recommended plated-through hole dimensions.
- While 78SR regulators easily withstand a 2kV ESD discharge to any terminal (using human body model), they should always be treated as ESD sensitive devices.
- 7. Horizontal-Pin Models (78XXSRH-C):** 78XXSRH-C switching regulators are pin-compatible replacements for TO-220 style LM78XX linear regulators that are installed with their metal tabs lying flat on the surface of the pc-board. However, because the surface of inductor L1 on 78XXSRH-C models is electrically conductive, it must not be allowed to come in contact with any exposed pc-board traces, other than power ground (GND). While the 2-mil-thick (0.05mm) polyester label attached to L1 provides some degree of electrical insulation (only if L1 sits perfectly flat on the pc-board), it is recommended that a 0.020" (0.5mm) clearance be maintained between L1 and all exposed pc-board traces.
- 8. Dropout Voltage:** 78SR series regulators described in this data sheet specify a minimum input voltage at which full-load accuracy and output regulation are guaranteed (7.5V for 7803SR-C and 7805SR-C, and 15.0V for 7812SR-C). However, these devices will stay in regulation at lower input voltages if they are operated at less than their rated loads. The following dropout-voltage data, derived from sample testing performed at an ambient temperature of +25°C with resistive loads, should be used for information purposes only. For these tests, a unit was considered to be out of regulation when its output changed by more +/–0.005Vdc from its nominal value. All voltages were measured directly at the regulator's I/O pins.

| Typical Dropout Voltage |         |          |          |           |
|-------------------------|---------|----------|----------|-----------|
|                         | 0% Load | 25% Load | 50% Load | 100% Load |
| 7803SR-C                | 6.0V    | 6.2V     | 6.2V     | 6.3V      |
| 7805SR-C                | 6.3V    | 6.2V     | 6.2V     | 6.8V      |
| 7812SR-C                | 12.8V   | 13.0V    | 12.8V    | 13.0V     |

### Performance/Functional Specifications

Typical at T<sub>A</sub> = +25°C

| Input/Output                  |                        |            |           |
|-------------------------------|------------------------|------------|-----------|
| Models                        | 7803SR-C               | 7805SR-C   | 7812SR-C  |
| Output Voltage                | +3.3Vdc                | +5.0Vdc    | +12.0Vdc  |
| Rated Output Current          | 0.5A                   | 0.5A       | 0.4A      |
| Output Voltage Accuracy       | ±2%                    | ±2%        | ±2%       |
| Input Voltage Range ①         | +7.5-36Vdc             | +7.5-36Vdc | +15-36Vdc |
| Line Regulation (100% load)   | ±0.3%                  | ±0.3%      | ±0.3%     |
| Load Regulation (0-100% load) | ±0.2%                  | ±0.2%      | ±0.2%     |
| Quiescent Current             | 3mA typ., 5mA max.     |            |           |
| Input Current                 | See Performance Curves |            |           |
| Efficiency                    | See Performance Curves |            |           |
| Transient Response            | See Performance Curves |            |           |
| Input & Output Noise          | See Performance Curves |            |           |
| Short Circuit Protection ②    | Continuous             |            |           |
| Isolation                     | None                   |            |           |
| Oversvoltage Protection       | None                   |            |           |
| Undersvoltage Protection      | None                   |            |           |

| Environmental             |                     |          |          |
|---------------------------|---------------------|----------|----------|
| Models                    | 7803SR-C            | 7805SR-C | 7812SR-C |
| Operating Temperature     | –40 to +70°C        |          |          |
| Storage Temperature       | –40 to +85°C        |          |          |
| Cooling                   | Free Air Convection |          |          |
| Humidity (Non-condensing) | 0 to 85%            |          |          |

| Physical      |   |
|---------------|---|
| Mechanical    | See Mechanical Specifications             |
| Package       | Open-frame SIP                            |
| Pins          | 0.025" (0.64mm) square, tin-plated bronze |
| Weight        | 0.08 ounces (2.2g)                        |
| Pin Soldering | +260°C for 5 seconds                      |


① See Technical Note 5.

② While these regulators can withstand a continuous short-circuit across their output terminals, they will experience a significant temperature rise. Extended short-circuit operation will adversely affect the unit's reliability.


Typical Performance Curves  $T_A = +25^\circ\text{C}$ ,  $V_{IN}$  as indicated

**Noise and Ripple - 10% and 100% Load, 20MHz Bandwidth**


7803SR-C  $V_{in} = 12\text{V}$ ,  $I_{LOAD} = 50\text{mA}$




7805SR-C  $V_{in} = 12\text{V}$ ,  $I_{LOAD} = 50\text{mA}$




7812SR-C  $V_{in} = 24\text{V}$ ,  $I_{LOAD} = 40\text{mA}$




7803SR-C  $V_{in} = 12\text{V}$ ,  $I_{LOAD} = 500\text{mA}$



7805SR-C  $V_{in} = 12\text{V}$ ,  $I_{LOAD} = 500\text{mA}$




7812SR-C  $V_{in} = 24\text{V}$ ,  $I_{LOAD} = 400\text{mA}$




### Transient Response - 90% Load Step


7803SR-C 10% to 100% Load Step




7805SR-C 10% to 100% Load Step




7812SR-C 10% to 100% Load Step




7803SR-C 100% to 10% Load Step









7805SR-C 100% to 10% Load Step




7812SR-C 100% to 10% Load Step



## Efficiency Curves




SHIPPING TRAYS AND BOXES




EACH FOAM TRAY (2300276) CONTAINS 50 UNITS IN FULL MPQ  
QUANTITIES, TWO TRAYS EQUAL TO A TOTAL OF 100(2x50) UNITS PER  
CARTON.

MECHANICAL DIMENSIONS: Inches (mm)  
TOLERANCES: 2 PL DEC  $\pm 0.02$  ( $\pm 0.51$ )  
3 PL DEC  $\pm 0.010$  ( $\pm 0.254$ )

Standard Package



**low-profile package**



Murata Power Solutions, Inc.  
11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A.  
ISO 9001 and 14001 REGISTERED



**This product is subject to the following operating requirements and the Life and Safety Critical Application Sales Policy:**  
Refer to: <http://www.murata-ps.com/requirements/>

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice. © 2015 Murata Power Solutions, Inc.