



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



WWW.CROUZET-MOTORS.COM


TNi21 DCMIND BRUSHLESS MOTORS

USER AND SAFETY MANUAL



TNi21 DCmind brushless motors

User and safety manual



Important notes

- This manual is part of the product.
- Read and follow the instructions in this manual.
- Keep this manual in a safe place.
- Give this manual and any documents relating to the product to anyone using the product.
- Read and follow closely all the safety instructions in the "Before you start - Safety information" section.
- Please see the current catalogue for the product's technical specification.
- We reserve the right to make modifications without prior notice.
- Unless otherwise stated in writing by Crouzet Automatismes, any use of the products described herein automatically signifies unconditional acceptance by the user of our general conditions of sale and the waiver of any stipulations which might be printed on its orders or correspondence. Crouzet Automatismes accepts no liability for any malfunction or damage caused by the user, due to the use of this manual or the instructions herein.

Table of contents

1.	Introduction	5
1.1.	Motor family.....	5
1.2.	Features	5
1.3.	Options	5
1.4.	Identification label	5
1.5.	Product coding	6
2.	Before you start - Safety information	7
2.1.	Qualification of personnel.....	7
2.2.	Use for intended purpose.....	7
2.3.	Basic information.....	8
2.4.	Standards and concepts	9
3.	Precautions for use at a mechanical level	10
3.1.	Data specific to the motor shaft	10
3.1.1.	Force applied when pushing items on to the shaft.....	10
3.1.2.	Radial load on the shaft.....	10
3.2.	Options	11
3.2.1.	Holding brake	11
3.2.2.	Gearboxes	11
3.2.3.	Others.....	11
4.	Installation.....	12
4.1.	Snapshot of the installation procedure.....	14
4.2.	Electromagnetic compatibility, EMC	14
4.3.	Before fitting	15
4.4.	Fitting the motor	16
4.5.	Electrical installation.....	17
4.5.1.	Connecting the holding brake (option)	19
4.6.	Production connector	20
5.	Switching on.....	21
5.1.	Preparations for switching on.....	21
6.	Product presentation.....	23
6.1.	Description of the product	23
6.2.	TNi21 control electronics	23
7.	Technical characteristics	24
7.1.	Electrical data.....	24
7.2.	Generic data.....	24
7.3.	Control logic bundle	25
7.4.	Power supply cable	26
8.	Motor electrical connection	27

- 8.1. Power connection.....27
 - 8.1.1. Ballast circuit27
 - 8.1.2. Protection for EMC29
- 8.2. Protective devices30
 - 8.2.1. Voltage protection.....30
 - 8.2.2. Temperature protection30
 - 8.2.3. Current limiting31
- 8.3. Connecting inputs/outputs.....31
 - 8.3.1. Equivalent inputs diagram31
 - 8.3.2. Equivalent outputs diagram32
- 9. Operating mode33
 - 9.1. Preliminaries33
 - 9.2. Functions associated with inputs33
 - 9.2.1. Function E1 - On / Off33
 - 9.2.2. Function E2 - Direction of rotation.....33
 - 9.2.3. Function E3 - Speed set-point.....33
 - 9.2.4. Function E4 - Torque limiter set-point34
 - 9.3. Functions associated with outputs34
 - 9.3.1. Function S1 - Encoder output.....34
 - 9.3.2. Function S2 - Torque limiter output.....34
 - 9.3.3. Function S3 - Actual direction of rotation output34
 - 9.4. SAFE mode35
- 10. Diagnostics and troubleshooting35
 - 10.1. Mechanical faults35
 - 10.2. Electrical problems.....35
- 11. Service, maintenance and problem solving36
 - 11.1. Addresses of after-sales service points36
 - 11.2. Storage.....36
 - 11.3. Maintenance.....36
 - 11.4. Replacing the motor37
 - 11.5. Shipping, storage, disposal37
 - 11.6. Terms and abbreviations.....38

About this manual

This manual applies to TNi21 DCmind brushless products:

- 801400TNi21, 801495TNi21, 801496TNi21, 801410TNi21,
- 801800TNi21, 801896TNi21, 801897TNi21, 801810TNi21,
- 802800TNi21, 802896TNi21, 802897TNi21, 802810TNi21,

Reference source for manuals

Manuals are available to download from the Internet at the following address

<http://www.crouzet.com/>

Units

By default, units rotate anti-clockwise.

Risk categories

In this manual, safety instructions are identified by warning symbols.

Safety instructions are divided into three risk categories, depending on the gravity of the situation.

 **DANGER**

DANGER indicates an immediately dangerous situation, which, if instructions are not followed, would **inevitably** result in a serious or fatal accident.

 **WARNING**

WARNING indicates a potentially dangerous situation which, if instructions are not followed, could **in certain cases** result in a serious or fatal accident or cause damage to equipment.

 **CAUTION**

CAUTION indicates a potentially dangerous situation which, if instructions are not followed, could **in certain cases** result in an accident or cause damage to equipment.

1. INTRODUCTION

1.1. Motor family

TNi21 DCmind brushless motors are direct current brushless motors with a built-in electronic control board.

1.2. Features

TNi21 DCmind brushless motors are intelligent servomotors for speed and torque control applications. They are fitted with two unscreened cables as standard, one for power and one for control.

1.3. Options

Motors may be supplied with options such as:

- a range of gearboxes
- a holding brake in the event of loss of current
- various motor output shaft versions

1.4. Identification label

The label carries the following information:




Figure 1

1. Product family code
2. Product reference
3. Reserved area
4. Area reserved for special customer markings
5. Date manufactured: week/year
6. Operating voltage
7. The motor's rated speed at 24V
8. The motor's rated current
9. Gear ratio (for versions with gearboxes)
10. Maximum nominal torque applicable to gearboxes (for versions with gearboxes).
11. Motor approvals.
12. Insulation system temperature class.
13. Degree of protection (sealing) of the product during operation (apart from the output shaft).
14. Country of manufacture

1.5. Product coding

80 XX XX TNi21: Product family based on TNi21 electronics

PRODUCT REFERENCE	8 0	X X	X X	X X
Motor				
Type of stator:				
14: 30 mm brushless stator				
18: 50mm brushless stator				
28: 50mm brushless stator high torque				
Gearboxes fitted:				
00: no gearbox				
10: RAD10 gearbox				
95: P52 gearbox				
96: P62 gearbox				
97: P81 gearbox				
Incrementing numbers				

2. BEFORE YOU START - SAFETY INFORMATION

2.1. Qualification of personnel

Only qualified personnel, familiar with and understanding the contents of this manual, are authorised to work on and with this product.

Qualified personnel should have a sound knowledge of current standards, regulations and requirements with regard to accident prevention, when carrying out work on or with the product.

Those personnel must have undergone safety training, so that they are able to detect and prevent any associated danger.

By virtue of their professional training, knowledge and experience, these qualified personnel should be able to provide warning or recognise potential dangers, that could be caused by use of the product, modifying its settings or those of mechanical, electrical and electronic equipment in the installation in general.

2.2. Use for intended purpose

As stated in these instructions, this product is a component intended for use in an industrial environment. The safety instructions in force, specified conditions and technical characteristics must be respected at all times.

Before using the product for the first time, a risk analysis should be carried out on its use in practice. Depending on the result, any necessary safety measures should be taken.

Since the product is used as a component in an overall system, it is the user's responsibility to ensure the safety of persons through the design of the overall system, e.g. machine design.

Use only original spare parts and accessories.

The product must not be used in an explosive atmosphere (Ex zone).

Any other use is considered as non-compliant and could cause danger.

Only duly qualified personnel are authorised to install, operate, maintain and repair electrical devices and equipment.

2.3. Basic information



DANGER

DANGER DUE TO ELECTRIC SHOCK, EXPLOSION OR EXPLOSION DUE TO AN ELECTRICAL ARC

- Only qualified personnel, familiar with and understanding the contents of this manual, are authorised to work on and with this product. Only qualified personnel are authorised to install, adjust, repair and maintain it.
- The person/entity constructing the installation is responsible for compliance with all applicable requirements and regulations concerning the earthing of the drive system.
- It is the user's responsibility to determine whether it is necessary to earth the motor, depending on its use.
- Do not touch unprotected live parts.
- Use only electrically insulated tools.
- AC voltages may flow along unused conductors in the motor cable. Isolate unused conductors at both ends of the motor cable.
- The motor produces a voltage when the shaft rotates. Isolate the motor shaft from any external power supply, before carrying out any work on the drive system.
 - Switch off all connections
 - Attach a "DO NOT SWITCH ON" sign on all switches.
 - Prevent all switches from being re-engaged.
 - Wait for the motor's internal capacitors to discharge.. Measure the voltage in the power cable and check that it is less than 12V DC.
- Fit and close all protective covers before re-applying power..

Failure to take these precautions could result in death or serious injury.

 **WARNING****LOSS OF CONTROL**

• When designing the control of the installation, the manufacturer should keep in mind the implications of a potential failure in control paths and, for certain critical functions, provide a method for returning to a safe state during and after the failure of a control path.

Examples of critical control functions are:

EMERGENCY STOP, restricting the final position, network interruption and re-starting.

- Separate or redundant control paths must be available for critical functions.
- Follow accident prevention instructions and all applicable safety directives.
- Any installation in which the product described in this manual is used must be carefully and minutely checked to ensure that it is operating correctly, before it is switched on.

If these precautions are not taken, the result could be death or serious injury.

 **WARNING****UNBRAKED MOVEMENT**

In the event of a loss of power to the power stage, the motor is no longer braked in a controlled way and could cause damage.

- Prevent access to the risk area..
- If necessary, use a damped mechanical stop or a service brake.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

2.4. Standards and concepts


This product complies with European ROHS Directive 2011/65/EC and is CE marked.

The product's electrical design complies with standards IEC 60335-1 and IEC 60950-1.

3. PRECAUTIONS FOR USE AT A MECHANICAL LEVEL

3.1. Data specific to the motor shaft

3.1.1. Force applied when pushing items on to the shaft

 WARNING
<p>MECHANICAL CHARACTERISTICS OF THE MOTOR Exceeding the maximum permitted force on the shaft will result in rapid wearing of the bearings, a broken shaft or the deterioration of any accessories (encoder, brake, etc.)</p> <ul style="list-style-type: none"> • Never exceed the max. permissible radial or axial forces on the motor. • Protect the shaft against impacts. • When pushing items in to the shaft, do not exceed the maximum permitted axial force. <p>If these precautions are not taken, the result could be death, serious injury or damage to equipment.</p>

The maximum force when pushing items on to the shaft is limited by the maximum permitted axial force acting on the ball bearings.

This maximum axial force is given in the motor's data sheet.

Alternatively, the item to be attached can be secured by clamping, bonding or binding.

3.1.2. Radial load on the shaft




Figure 2

The point of application **X** of the radial force **F** depends on the size of the motor. This information is shown in the motor's data sheet.

The maximum radial and axial loads should not be applied simultaneously, so as to maximise the motor's service life.

3.2. Options

3.2.1. *Holding brake*

TNi21 DCmind brushless motors can be fitted with a fail safe electromechanical brake. The holding brake is designed to prevent the shaft from rotating when there is no power to the motor. The holding brake has no safety function. The "Connecting a holding brake" section describes how it should be controlled.

3.2.2. *Gearboxes*

TNi21 DCmind brushless motors may be fitted with various types of gearbox. The gearboxes offered in the standard catalogue are planetary gearboxes, combining compactness with strength, and worm gearboxes that provide output from the shaft at right angles to the motor shaft.

3.2.3. *Others*

Other types of adaptation are possible upon request. Please contact our sales department.

4. INSTALLATION

In a general sense, motors should be installed in line with good industrial practice.

 **WARNING****CONSIDERABLE WEIGHT AND FALLING PARTS**

The motor can weigh a lot.

- Take the motor's weight into consideration when fitting it.
- Fit the motor (tightening torque of screws) in such a way that it cannot come adrift, even in the event of high levels of acceleration or permanent vibration.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **WARNING****STRONG ELECTROMAGNETIC FIELDS**

Motors can generate powerful local electrical and magnetic fields. They can cause sensitive equipment to fail.

- Keep persons wearing implants such as heart pacemakers away from the motor.
- Do not position sensitive equipment in the immediate proximity of the motor.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **WARNING****UNEXPECTED BEHAVIOUR AS A RESULT OF DETERIORATION OR FOREIGN BODIES**

As a result of deterioration of the product, the presence of foreign bodies or deposits or penetration by fluids, unexpected behaviour can occur.

- Do not use damaged products..
- Do not allow any foreign body to enter the product.
- Check that seals and power cable glands are correctly fitted.
- Check that the plug protecting the motor's internal connector is fitted correctly.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **WARNING****HOT SURFACES**

The metal surface of the product can reach more than 70°C during use.

Avoid all contact with the metal surface.

- Do not position inflammable or heat-sensitive components in immediate proximity.
- Try to achieve an assembly that allows heat to dissipate efficiently.

If these precautions are not taken, the result could be injury or damage to equipment.

 **WARNING****DETERIORATION OR DESTRUCTION OF THE MOTOR DUE TO OVER-STRESSING**

The motor is not designed to withstand loads. If the motor is stressed, it could be damaged or even fall.

- Do not stand on the motor.
- Prevent the motor being used in any other way than its intended purpose by taking protective measures and following the safety instructions.

If these precautions are not taken, the result could be injury or damage to equipment.

 **CAUTION****OVER-VOLTAGES**

During braking phases, the motor generates over-voltages.

- Check that these over-voltages are acceptable to other equipment connected to the same power supply.
- Preferably, use an external circuit, to limit over-volting

In cases where braking is used intensively.

If these precautions are not taken, the result could be injury or damage to equipment.


4.1. Snapshot of the installation procedure

The installation procedure is described in the follow sections:

- Electromagnetic compatibility, EMC
- Before fitting
- Fitting the motor
- Electrical installation

Check that these sections have been read and understood and that, subsequently, the motor has been installed correctly.

4.2. Electromagnetic compatibility, EMC

 **DANGER**

INTERFERENCE AFFECTING SIGNALS AND EQUIPMENT
 Interference with signals can cause equipment to behave unpredictably

- Wiring should be done in accordance with the EMC recommendations specific to each device.
- Ensure that these EMC recommendations are followed correctly.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

Recommendations with regard to EMC: installing the motor's power supply wiring.

At the wiring planning stage, consider that the motor's power supply wiring must be installed isolated from network or signal transmission cables.

Take the following measures with regard to EMC.

EMC measures	Effect
Keep cables as short as possible. Do not install loops of unused cable.	Reduce interference, capacitive and inductive couplings.
Earth the product.	Reduce emissions; increase immunity to interference,
Where shielded cables are used, the cable shielding should be fitted to the widest possible surface area. Use cable clamps and earth bands.	Reduce emissions.
Position the motor's power supply wires separate from cables that carry signals or use screening plates.	Reduce mutual interference
If screened cables are used, fit them without an isolation point. ¹⁾	Reduce radiating interference.

1) Where the installation requires a cable to be cut, cables must be connected at the isolation point via a shielded cable inside a metal enclosure.

Equipotential link conductors

Where screened cables are used, differences in voltage can cause currents not permitted in screened cables. Fit equipotential link conductors to reduce current in screened cables.

4.3. Before fitting

Look for damage

Damaged drive systems should not be fitted or used.

⇒ Check the drive system before fitting and look for visible signs of damage.

Cleaning the shaft

On leaving the factory, the ends of the motor shafts are coated with film of oil.

Where transmission devices are to be fitted by bonding, it may be necessary to remove that oil film and clean the shaft. Where necessary, use degreasing products recommended by the manufacturer of the bonding adhesive.

⇒ Avoid all contact between the skin and sealing materials and the cleaning product used.

Fitting surface for the flange

The fitting surface must be stable, flat and clean.

⇒ On the installation side, ensure compliance with all dimensions and tolerances.

Specification for power supply wires.

The power supply wires for the motor and its accessories must be selected with care according to their length, the motor's supply voltage, the ambient temperature, the current passing through them and their environment.



WARNING

DETERIORATION AND FIRE FOLLOWING INCORRECT INSTALLATION

Forces and movement in cable glands can damage cables.

- Comply with the stated bend radius
- Avoid subjecting cable glands to forces or movement.
- Secure supply cable close to cable glands using a strain relief clamp.

If these precautions are not taken, the result could be injury or damage to equipment.

4.4. Fitting the motor

 **DANGER****HOT SURFACES**

The surface of the motor can reach more than 70°C during use.

- Avoid contact with hot surfaces.
- Do not position inflammable or heat-sensitive components in immediate proximity.
- Try to achieve an assembly that allows heat to dissipate efficiently.
- Run a test to check the temperature.

If these precautions are not taken, the result could be injury or damage to equipment.

 **WARNING****UNEXPECTED MOVEMENT DUE TO ELECTROSTATIC DISCHARGES**

In rare cases, electrostatic discharges (ESD) on the shaft can cause faults in the encoding system and unexpected movements of the motor.

- Use conductive components, e.g. anti-static belts or other appropriate measures to prevent any static charge due to movement.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **WARNING****UNINTENDED BEHAVIOUR DUE TO MECHANICAL DETERIORATION OF THE MOTOR**

Exceeding the maximum permissible forces on the shaft will result in rapid wear of the bearings, a broken shaft or damage to the internal encoder.

- Never exceed the max. permissible radial or axial forces on the motor.
- Protect the shaft against impacts.
- When pushing items on to the shaft, do not exceed the maximum permitted axial force.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

Installation position

The motor can be installed in any position.

Installation

When fitting the motor on the flange, it must be aligned precisely, both axially and radially. All securing screws must be tightened to the torque prescribed by the application, taking care not to cause any warping.

Fitting transmission devices

Fitting transmission devices incorrectly could damage the motor.

Transmission devices such as pulleys and gears must be fitted with reference to the maximum axial and radial forces specified in the data sheet for each motor.

Follow the manufacturer's fitting instructions for each transmission device.

The motor and transmission device must be aligned accurately, both radially and axially. Any failure to do so will result in erratic operation, damage to bearings and a high level of wear.

4.5. Electrical installation

These motors are not designed to be connected directly to the electrical system.

It is the installer's responsibility to specify the electrical protection to be deployed with regard to the regulations applicable to the field of use of the final product.

For the supply to the power part, we recommend the use of a stabilised double-insulated power supply unit.

The motor's power stage is not protected against reversed polarity.

The motor is said to be regenerative, i.e. it can feed back energy to the power supply during braking phases.

Voltage surges created in this way can reach levels that risk damaging the motor itself or to devices connected to the same power supply.

DANGER

ELECTRIC SHOCK

High voltages can occur unexpectedly at the motor connection.

- The motor produces a voltage when the shaft rotates. Isolate the motor shaft from any external driving force before doing any work on the drive system.
- The system's manufacturer is responsible for complying with all the rules applicable to the earthing of the drive system.

Failure to take these precautions could result in death or serious injury.

WARNING

UNEXPECTED MOVEMENT

Drives may move unexpectedly, due to an incorrect connection or some other error.

- Only start the installation if there is no person or obstacle inside the danger zone.
- Make initial test movements with no load connected.
- Do not touch the motor shaft or connected drive components.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **WARNING****OVER-VOLTAGES**

During braking phases, the motor generates over-voltages.

- Check that these over-voltages are acceptable to other equipment connected to the same power supply.
- Preferably use an external circuit, to limit over-volting

In cases where braking is used intensively.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **CAUTION****FIRE DUE TO POOR CONTACT**

The connection terminals to the motor could heat up and the contacts melt due to electrical arcing, if the connector is not properly plugged in.

- Poor connections can cause heating due to electrical arcing.

If these precautions are not taken, the result could be injury or damage to equipment.

 **CAUTION****REVERSED POLARITY COULD DESTROY THE PRODUCT**

Incorrectly connecting the power can result in reversed polarity and the destruction of the electronic board inside the motor.

- Check that the power connection is correct.

If these precautions are not taken, the result could be injury or damage to equipment.


Connecting the protective conductor


It is the installer's responsibility to determine the necessity to earth the motor.


This must be done via the mounting flange.

Under no circumstances connect or disconnect the product's power supply wires while they are live.

4.5.1. Connecting the holding brake (option)

 WARNING
<p>LOSS OF BRAKING FORCE DUE TO WEAR OR HIGH TEMPERATURE Application of the holding brake while the motor is rotating can cause rapid wear and loss of braking force.</p> <ul style="list-style-type: none">• Do not use the brake as a service brake.• Note that an "emergency stop" can also cause wear. <p>If these precautions are not taken, the result could be death, serious injury or damage to equipment.</p>

 WARNING
<p>UNEXPECTED MOVEMENT Releasing the holding brake can cause unexpected movement in the installation.</p> <ul style="list-style-type: none">• Take care that this does not cause any damage.• Only run tests if there is no person or obstacle inside the danger zone. <p>If these precautions are not taken, the result could be death, serious injury or damage to equipment.</p>

 CAUTION
<p>MALFUNCTION OF THE HOLDING BRAKE DUE TO AN INAPPROPRIATE VOLTAGE</p> <ul style="list-style-type: none">• If the voltage is too low, the holding brake cannot release itself and that will cause wear.• If voltages are higher than specified, the holding brake will suffer excessive heating. <p>If these precautions are not taken, the result could be injury or damage to equipment.</p>

A motor with a holding brake requires a suitable control logic which releases the brake when rotational movement starts and which grips the motor shaft in time when the motor stops.

4.6. Production connector

The motor is fitted with a silicone plug, as shown in the image below. It protects the connector used during the motor's manufacture. This connector is not intended to be accessed by users of the product. If the plug is removed, the motor will no longer be sealed, allowing fluids and particles to enter the motor, potentially destroying it or causing it to malfunction.




Figure 3

The plug should never be removed by the user.

 **CAUTION**

LOSS OF SEALING

The plug keeps the motor sealed.

- Do not remove the plug.

If these precautions are not taken, the result could be injury or damage to equipment.

5. SWITCHING ON

5.1. Preparations for switching on

Before switching on:

- ⇒ Check that the mechanical installation is correct.
- ⇒ Check that the electrical installation has been done professionally: in particular, check the connections on protective conductors and earth connections. Ensure that all connections are correct and sound and that screws are properly tight.
- ⇒ Check the ambient conditions and conditions for use: ensure that the prescribed ambient conditions are met and that the drive solution complies with the intended conditions for use.
- ⇒ Check that any transmission devices already fitted are balanced and accurately aligned.
- ⇒ Check that the conditions of use do not cause any abnormal over-voltages for the product or the application.
- ⇒ Check that the holding brake can support the maximum load. Check that after the braking voltage is applied, the holding brake releases correctly. Ensure that the holding brake is properly released prior to movement starting.
- ⇒ Check that the connector protection plug is in place.

 **WARNING****UNEXPECTED MOVEMENT**

Drives may move unexpectedly, due to an incorrect connection or some other error.

- Check the wiring.
- Only start the installation if there is no person or obstacle inside the danger zone.
- Make initial test movements with no load coupled.
- Do not touch the motor shaft or associated drive components.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **WARNING****ROTATING PARTS**

Rotating parts can cause injury or catch clothing or hair. Loose parts or unbalanced parts can be thrown off.

- Check that all rotating parts are secure.
- Fit a guard over rotating parts.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **WARNING****FALLING PARTS**

Reactive torque could cause the motor to move, tip or fall.

- Secure the motor firmly, so that it cannot come loose due to severe acceleration.

If these precautions are not taken, the result could be death, serious injury or damage to equipment.

 **CAUTION****HOT SURFACES**

The surface of the motor can reach more than 70°C during use.

- Avoid contact with hot surfaces.
- Do not position inflammable or heat-sensitive components in immediate proximity.
- Try to achieve an assembly that allows heat to dissipate efficiently.
- Run a test to check the temperature.

If these precautions are not taken, the result could be injury or damage to equipment.

 **CAUTION****OVER-VOLTAGES**

During braking phases, the motor generates over-voltages.

- Check that these over-voltages are acceptable to other equipment connected to the same power supply.
- Preferably use an external circuit, to limit over-volting

In cases where braking is used intensively.

If these precautions are not taken, the result could be injury or damage to equipment.

6. PRODUCT PRESENTATION

6.1. Description of the product




Figure 4

6.2. TNi21 control electronics

The TNi21 electronic board contains control electronics for brushless motors and is built into the body of the motor.

These electronics provide:

- Motor power control in trapeze mode ("6 steps").
- A speed control
- Torque limiting control
- Management of the four inputs and three outputs that control the motor:
 - Two 10-bit or PWM analogue control inputs
 - Speed set-point
 - Torque limiting
 - Two switching inputs
 - On/off
 - Direction of rotation
 - One encoder output
 - 12 points per revolution for 80140 and 80180 motors
 - 24 points per revolution for 80280 motors
 - One 'torque limit reached' switching output
 - One actual direction of rotation switching output

7. TECHNICAL CHARACTERISTICS

7.1. Electrical data

Maximum product characteristics				
Parameters	Value			Unit
Supply voltage V_{DC_MAX}	56 ^(*)			V
Maximum current I_{DC_MAX}	20			A
Maximum voltage at the inputs V_{IN_MAX}	50 ^(*)			V
Maximum voltage at the outputs V_{OUT_MAX}	56 ^(*)			V
Maximum current at the outputs I_{OUT_MAX}	50			mA
Operating characteristics				
Parameters	Min.	Typical	Max.	Unit
Power supply voltage V_{DC}	10	12 / 24 / 32	36	V
Peak current I_{DC}	-	-	17	A
Motor consumption at rest without holding I_0	-	75	-	mA
Input characteristics				
Parameters	Min.	Typical	Max.	Unit
Input impedance between E1 and E2 R_{IN_TOR}	-	57	-	k Ω
Input impedance between E3 and E4 $R_{IN_ANA/PWM}$	-	69	-	k Ω
Low logic level on inputs E1 to E2 V_{IL_TOR}	0	-	2	V
High logic level on inputs E1 to E2 V_{IH_TOR}	4	-	50 ^(*)	V
Low logic level on inputs E3 to E4 V_{IL_PWM}	0	-	2	V
High logic level on inputs E3 to E4 V_{IH_PWM}	7.5	-	50 ^(*)	V
Frequency of PWMs on input	100	-	2000	Hz
Resolution of proportional inputs		10		bits
Output characteristics				
Parameters	Min.	Typical	Max.	Unit
Low logic level on outputs S1 to S3 V_{OL} $R_L = 4K7\Omega$, $V_{DC} = 24V$	0	-	0.2	V
High logic level on outputs S1 to S3 V_{OL} $R_L = 4K7\Omega$, $V_{CC} = 24V$	$V_{DC} - 0.5V$	-	V_{DC}	V
Type PNP open slip-ring				

^(*) 36V prior to 15 October 2015

7.2. Generic data

General characteristics		
Parameters	Value	Unit
Motor ambient temperature	-30 to +70	°C
Insulation class (complies with directive IEC 60085)	E	/
Protection index (other than shaft axis)	IP65M	/