



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China

FEATURES

- Adjustable input threshold voltage options: 0.4 V and 1.23 V
- Pre-trimmed V_{CC} threshold options ([ADM6306](#))
 - Increments between 2.5 V and 5 V
- Manual reset input ([ADM6306](#))
- 4 factory programmed reset timeout delays
 - 1 ms, 20 ms, 140 ms, and 1.12 sec (minimum)
- Reset output stage: active low, open drain
- Low power consumption: 5 μ A typical
- Power supply glitch immunity
- 5-lead SOT-23 package
- Temperature range: -40°C to $+125^{\circ}\text{C}$

APPLICATIONS

- Portable/battery-operated equipment
- Microprocessor systems
- Multivoltage applications

GENERAL DESCRIPTION

The [ADM6305/ADM6306](#) are dual voltage supervisors designed to monitor two supplies and provide a reset signal to DSP- and microprocessor-based systems. Low supply current and a small form factor make these devices suitable for portable and battery-operated applications.

If a monitored power supply voltage falls below the minimum voltage threshold, a single active low output asserts triggering a system reset. Once all voltages rise above the selected threshold level, the reset signal remains low for the reset timeout period. Four reset timeout options are available.

The [ADM6305](#) monitors two supplies via two adjustable resistor-programmable undervoltage reset inputs. Both RST IN1 and RST IN2 have a reset threshold of either 0.4 V or 1.23 V depending on the particular model; that is, the RST IN1 and RST IN2 threshold of the [ADM6305DxARJZ](#) model is

FUNCTIONAL BLOCK DIAGRAMS




Figure 1.

09345-001




Figure 2.

09345-002

1.23 V, while in the case of [ADM6305DxARJZ1](#) model, it is 0.4 V. The V_{CC} input of the [ADM6305](#) is not a monitored input.

The [ADM6306](#) has one adjustable undervoltage reset input, RST IN, which features a choice of reset threshold, 0.4 V or 1.23 V (see the Ordering Guide for more information). The [ADM6306](#) incorporates a variety of internally pretrimmed V_{CC} undervoltage threshold options for monitoring supply voltages in increments between 2.5 V and 5 V. The [ADM6306](#) also includes a manual reset input.

The [ADM6305/ADM6306](#) RESET output remains valid as long as V_{CC} exceeds 0.9 V.

The [ADM6305/ADM6306](#) are available in a 5-lead SOT-23 package. These devices are specified over the temperature range of -40°C to $+125^{\circ}\text{C}$.

TABLE OF CONTENTS

Features	1	Pin Configurations and Function Descriptions	5
Applications	1	Typical Performance Characteristics	6
Functional Block Diagrams	1	Theory of Operation	8
General Description	1	Input Configuration	8
Revision History	2	Reset Output Configuration	8
Specifications	3	Manual Reset	8
Absolute Maximum Ratings	4	Options	9
Thermal Resistance	4	Outline Dimensions	11
ESD Caution	4	Ordering Guide	11

REVISION HISTORY

6/14—Rev. A to Rev. B

Changes to Figure 3 and Figure 4 5

4/12—Rev. 0 to Rev. A

Changes to Figure 1 and Figure 2 1
Change to V_{CC} Pin Description, Table 5 5
Changes to Table 9 10
Updated Outline Dimensions 11
Changes to Ordering Guide 11

10/10—Revision 0: Initial Version

SPECIFICATIONS

V_{CC} = 2.5 V to 5 V for the ADM6305, V_{CC} = (V_{TH} + 2.5%) to 5.5 V for the ADM6306. T_A = −40°C to +125°C, unless otherwise noted. Typical values are at T_A = 25°C.

Table 1.

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
OPERATING VOLTAGE RANGE, V_{CC} ¹	0.9 0.9		5.5	V V	V_{CC} that guarantees valid output
INPUT CURRENT, I_{CC}		5 5	16 20	μA μA	$V_{CC} = 5.5$ V, T_A = −40°C to +85°C $V_{CC} = 5.5$ V, T_A = −40°C to +125°C
V_{CC} THRESHOLD VOLTAGE (ADM6306) ²	$V_{TH} - 1\%$ $V_{TH} - 1.5\%$ $V_{TH} - 2.5\%$	V_{TH} V_{TH} V_{TH}	$V_{TH} + 1\%$ $V_{TH} + 1.5\%$ $V_{TH} + 2.5\%$	V V V	$T_A = 25$ °C $T_A = -40$ °C to +85°C $T_A = -40$ °C to +125°C
RESET THRESHOLD TEMPERATURE COEFFICIENT		25		ppm/°C	
RESET THRESHOLD HYSTERESIS (V_{HYST})		2 × V_{TH}		mV	
RESET TIMEOUT PERIOD (t_{RP})					
ADM630xD1	1.0	1.4	2.0	ms	
ADM630xD2	20	28	40	ms	
ADM630xD3	140	200	280	ms	
ADM630xD4	1120	1570	2240	ms	
RESET OUTPUT VOLTAGE (V_{OL})			0.4 0.3 0.3 0.3 0.3	V V V V V	$V_{CC} > 4.25$ V, $I_{SINK} = 3.2$ mA $V_{CC} > 2.5$ V, $I_{SINK} = 1.2$ mA $V_{CC} > 1.2$ V, $I_{SINK} = 500$ μA $V_{CC} > 1$ V, $I_{SINK} = 50$ μA $V_{CC} > 0.9$ V, $I_{SINK} = 25$ μA
MR INPUT (ADM6306)					
V_{IL}			0.8 0.3 × V_{CC}	V V	$V_{TH} > 4.0$ V $V_{TH} < 4.0$ V
V_{IH}		2.4 0.7 × V_{CC}		V V	$V_{TH} > 4.0$ V $V_{TH} < 4.0$ V
MR Minimum Input Pulse Width		1 1.5		μs μs	$T_A = 0$ °C to +70°C $T_A = -40$ °C to +125°C
MR Glitch Rejection		0.1		μs	
MR To Reset Delay		500		ns	
MR Pull-Up Resistance	32	63.5	100	kΩ	
1.23 V ADJUSTABLE RESET COMPARATOR INPUT					
RST INx Input Threshold, V_{RSTH}	1.22 1.211 1.20	1.23 1.23 1.26	1.24 1.249	V	$T_A = 25$ °C $T_A = -40$ °C to +85°C $T_A = -40$ °C to +125°C
RST INx Input Current, I_{RSTINx}	−25 −25		+25 +25	nA nA	$0 \text{ V} < V_{RSTIN} < V_{CC} - 0.3 \text{ V}^3$, $T_A = -40$ °C to +85°C $V_{RSTIN} = V_{RSTH}$
RST INx Hysteresis			2.5	mV	
0.4 V ADJUSTABLE RESET COMPARATOR INPUT					
RST INx Input Threshold, V_{RSTH}	0.396 0.394 0.39	0.40 0.40 0.40	0.404 0.406 0.41	V V V	$T_A = 25$ °C $T_A = -40$ °C to +85°C $T_A = -40$ °C to +125°C
RST INx Input Current, I_{RSTINx}	−25 −25		+25 +25	nA nA	$0 \text{ V} < V_{RSTIN} < V_{CC} - 0.3 \text{ V}^3$, $T_A = -40$ °C to +85°C $V_{RSTIN} = V_{RSTH}$

¹ The ADM6305 switches from undervoltage reset to normal operation when $1.5 \text{ V} > V_{CC} < 2.5 \text{ V}$.

² The ADM6306 monitors V_{CC} through an internal factory trimmed voltage divider, which programs the nominal reset threshold. Factory-trimmed reset thresholds are available in approximately 100 mV increments from 2.5 V to 5 V.

³ Guaranteed by design.

ABSOLUTE MAXIMUM RATINGS

Table 2.

Parameter	Rating
V _{CC}	-0.3 V to +6 V
All Pins (Except V _{CC})	-0.3 V to (V _{CC} + 0.3 V)
Input/Output Current	20 mA
Rate of Rise, V _{CC}	100 V/μs
Storage Temperature Range	-65°C to +160°C
Operating Temperature Range	-40°C to +125°C
Lead Temperature (10 sec)	300°C
Junction Temperature	150°C

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

THERMAL RESISTANCE

Table 3.

Package Type	θ _{JA}	Unit
5-Lead SOT-23	240	°C/W

ESD CAUTION



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

PIN CONFIGURATIONS AND FUNCTION DESCRIPTIONS




Figure 3. ADM6305 Pin Configuration

Table 4. ADM6305 Pin Function Descriptions

Pin No.	Mnemonic	Description
1	RESET	Active Low, Open-Drain RESET Output.
2	GND	Ground.
3	RST IN1	Adjustable Reset Comparator Input. This pin asserts <u>RESET</u> if the input voltage is below threshold. Its high input impedance allows the use of an external resistor divider to program the monitoring threshold. Connect this pin to V _{CC} if it is not used.
4	RST IN2	Adjustable Reset Comparator Input. This pin asserts <u>RESET</u> if the input voltage is below threshold. Its high input impedance allows the use of an external resistor divider to program the monitoring threshold. Connect this pin to V _{CC} if it is not used.
5	V _{CC}	Power Supply Input. V _{CC} is not monitored on the ADM6305.




Figure 4. ADM6306 Pin Configuration

Table 5. ADM6306 Pin Function Descriptions

Pin No.	Mnemonic	Description
1	RESET	Active Low, Open-Drain RESET Output.
2	GND	Ground.
3	MR	Manual Reset Input.
4	RST IN	Adjustable Reset Comparator Input. This pin asserts <u>RESET</u> if the input voltage is below threshold. Its high input impedance allows the use of an external resistor divider to program the monitoring threshold. Connect this pin to V _{CC} if it is not used.
5	V _{CC}	Power Supply Input. V _{CC} is monitored on the ADM6306.

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 5. Supply Current vs. Temperature




Figure 6. Reset Timeout vs. Temperature









Figure 7. Reset Threshold vs. Temperature


Figure 8. V_{CC} Falling Propagation Delay vs. TemperatureFigure 9. Maximum Transient Duration vs. V_{CC} Reset Threshold OverdriveFigure 10. RST IN ($V_{TH} = 1.23$ V) Falling Propagation Delay vs. Temperature



09345-011



09345-013



09345-012

THEORY OF OPERATION

The **ADM6305/ADM6306** are compact, low power supervisory circuits capable of monitoring two voltage rails. If a monitored voltage drops below its associated threshold, the active low reset output asserts low.

The **ADM6305** monitors two supplies via two adjustable resistor-programmable undervoltage reset inputs. Both RST IN1 and RST IN2 have a reset threshold of either 0.4 V or 1.23 V depending on the particular model; that is, the RST IN1 and RST IN2 threshold of the **ADM6305DxARJZ** model is 1.23 V, while in the case of **ADM6305DxARJZ1** model, it is 0.4 V. The V_{CC} input of the **ADM6305** is not a monitored input.

The **ADM6306** has one adjustable undervoltage reset input, RST IN, which features a choice of reset threshold, 0.4 V or 1.23 V (see the Ordering Guide for more information). The **ADM6306** incorporates a variety of internally pretrimmed V_{CC} undervoltage threshold options for monitoring supply voltages in increments between 2.5 V to 5 V. The **ADM6306** also includes a manual reset input.

INPUT CONFIGURATION

The threshold voltage at an adjustable input is either 0.4 V or 1.23 V. To monitor a voltage greater than the typical adjustable threshold, V_{RSTH} , connect a resistor divider network to the circuit as depicted in Figure 14, where




Figure 14. Setting the Adjustable Monitor

The high input impedance (leakage of ± 25 nA) of the adjustable inputs minimizes the offset error caused by the leakage current and external resistor divider. This allows the user to apply a divider with large resistance to minimize the loss. The offset voltage caused by the leakage current is calculated by $R1 \times \pm 25$ nA.

The RST INx inputs are designed to ignore fast voltage transients (see Figure 11 and Figure 12). Increase the noise immunity by connecting a 0.1 μ F bypass capacitor between RST INx and ground. Note that adding capacitance to RST INx slows the overall response time of the device.

There is no hysteresis associated with the 0.4 V adjustable inputs; instead, a time-based glitch filter to prevent false triggering is used. The glitch filter avoids the need to use a portion of the operating supply range to provide hysteresis

on this input. The **ADM6305/ADM6306** are powered via V_{CC} . Figure 9 shows the maximum transient duration vs. V_{CC} reset threshold overdrive, for which reset pulses are not generated. Figure 9 depicts the maximum pulse width that a negative going V_{CC} transient may typically have without causing RESET to be asserted. As the amplitude of the transient increases, the maximum allowable pulse width decreases. The addition of a bypass capacitor on V_{CC} provides additional transient immunity.

RESET OUTPUT CONFIGURATION

The **ADM6305/ADM6306** are available in a choice of four reset timeouts. Once the monitored supplies rise above their associated threshold level, the RESET signal remains low for the reset timeout period before deasserting. Subsequently, if a monitored supply falls below its associated threshold, the RESET output reasserts. The open-drain RESET output of the **ADM6305/ADM6306** remains valid as long as V_{CC} exceeds 0.9 V.

The **ADM6305** remains in UVLO when V_{CC} is below 1.5 V. The RESET output is controlled by RTS INx if V_{CC} exceeds 2.5 V.

The open-drain RESET output allows the **ADM6305** and **ADM6306** to interface easily with microprocessors and devices with bidirectional reset pins. Connecting the supervisory devices RESET output directly to the microcontrollers RESET pin with a single pull-up resistor allows either device to issue a system reset (see Figure 15).




Figure 15. Interfacing to Microprocessors with Bidirectional RESET Output

MANUAL RESET

The **ADM6306** features a manual reset input (\overline{MR}) which, when driven low, asserts the reset output. When \overline{MR} transitions from low to high, reset remains asserted for the duration of the reset active timeout period before deasserting. The \overline{MR} input has a 63.5 k Ω internal pull-up resistor so that the input is always high when unconnected. An external push-button switch can be connected between \overline{MR} and ground so that the user can generate a reset. Debounce circuitry is integrated on-chip for this purpose. Noise immunity is provided on the \overline{MR} input, and fast, negative-going transients of up to 0.1 μ s (typical) are ignored. If required, a 0.1 μ F capacitor between \overline{MR} and ground provides additional noise immunity.

OPTIONS

Table 6. ADM6306 V_{CC} Reset Voltage Threshold Options

Reset Threshold Number	T _A = 25°C			T _A = -40°C to +125°C		Unit
	Min	Typ	Max	Min	Max	
25	2.463	2.5	2.538	2.438	2.563	V
26	2.591	2.63	2.669	2.564	2.696	V
27	2.66	2.7	2.741	2.633	2.768	V
28	2.758	2.8	2.842	2.73	2.87	V
29	2.886	2.93	2.974	2.857	3	V
30	2.955	3	3.045	2.925	3.075	V
31	3.034	3.08	3.126	3.003	3.157	V
32	3.152	3.2	3.248	3.12	3.28	V
33	3.251	3.3	3.35	3.218	3.383	V
34	3.349	3.4	3.451	3.315	3.485	V
35	3.448	3.5	3.553	3.413	3.588	V
36	3.546	3.6	3.654	3.51	3.69	V
37	3.645	3.7	3.756	3.608	3.793	V
38	3.743	3.8	3.857	3.705	3.895	V
39	3.842	3.9	3.959	3.803	3.998	V
40	3.94	4	4.06	3.9	4.1	V
41	4.039	4.1	4.162	3.998	4.203	V
42	4.137	4.2	4.263	4.095	4.305	V
43	4.236	4.3	4.365	4.193	4.408	V
44	4.314	4.38	4.446	4.27	4.49	V
45	4.433	4.5	4.568	4.388	4.613	V
46	4.561	4.63	4.699	4.514	4.746	V
47	4.63	4.7	4.771	4.583	4.818	V
48	4.728	4.8	4.872	4.68	4.92	V
49	4.827	4.9	4.974	4.778	5.023	V
50	4.925	5.0	5.075	4.875	5.125	V

Table 7. Reset Timeout Options

Reset Timeout Period Code	T _A = -40°C to +125°C			Unit
	Min	Typ	Max	
ADM630xD1	1.0	1.4	2.0	ms
ADM630xD2	20	28	40	ms
ADM630xD3	140	200	280	ms
ADM630xD4	1120	1570	2240	ms

Table 8. Adjustable Input Threshold Options

Model	Monitored Input Threshold		
	RST IN1	RST IN2	RST IN
ADM6305_Z-RL7	1.23 V	1.23 V	N/A
ADM6305_Z1-RL7	0.4 V	0.4 V	N/A
ADM6306_Z-R7	N/A	N/A	1.23 V
ADM6306_Z1-R7	N/A	N/A	0.4 V




Figure 16. ADM6305 Ordering Code Structure




Figure 17. ADM6306 Ordering Code Structure

Table 9. Standard Models

Model	Monitored Input Threshold				Minimum Reset Timeout
	RST IN1	RST IN2	V _{cc} Reset	RST IN	
ADM6305D3ARJZ-RL7	1.23 V	1.23 V	N/A	N/A	140 ms
ADM6305D3ARJZ1-RL7	0.4 V	0.4 V	N/A	N/A	140 ms
ADM6306D131ARJZ-R7	N/A	N/A	3.08 V	1.23 V	1 ms
ADM6306D131ARJZ1R7	N/A	N/A	3.08 V	0.4 V	1 ms
ADM6306D329ARJZ-R7	N/A	N/A	2.93 V	1.23 V	140 ms
ADM6306D330ARJZ-R7	N/A	N/A	3 V	1.23 V	140 ms
ADM6306D331ARJZ-R7	N/A	N/A	3.08 V	1.23 V	140 ms
ADM6306D344ARJZ-R7	N/A	N/A	4.38V	1.23 V	140 ms
ADM6306D346ARJZ-R7	N/A	N/A	4.63 V	1.23 V	140 ms

OUTLINE DIMENSIONS




Figure 18. 5-Lead Small Outline Transistor Package [SOT-23]
(RJ-5)
Dimensions shown in millimeters




Figure 19. ADM6305/ADM6306 Reel Orientation

ORDERING GUIDE

Model ^{1, 2, 3}	Temperature Range	Ordering Quantity ⁴	Package Description	Package Option	Branding
ADM6305D3ARJZ-RL7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LG9
ADM6305D3ARJZ1-RL7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LG8
ADM6306D131ARJZ-R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LGA
ADM6306D131ARJZ1R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LGC
ADM6306D329ARJZ-R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LLY
ADM6306D330ARJZ-R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LM0
ADM6306D331ARJZ-R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LG6
ADM6306D331ARJZ1R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LQC
ADM6306D344ARJZ-R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LM1
ADM6306D346ARJZ-R7	-40°C to +125°C	3,000	5-Lead SOT-23	RJ-5	LLZ

¹ ADM6305 and ADM6306 follow the C2 Pin 1 orientation standard for tape and reel packaging (see Figure 19).

² If ordering nonstandard models, complete the ordering code shown in Figure 16 and Figure 17 by inserting the reset threshold, reset timeout, and adjustable threshold suffixes. Contact Sales for availability of nonstandard models, quoting ADM6305-NTSD or ADM6306-NTSD first, and then the complete ordering code.

³ Z = RoHS Compliant Part.

⁴ A minimum of 10,000 must be ordered for nonstandard models.

NOTES