



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



## FEATURES

An eco-friendly switch-replacing a mercury switch with steel ball inside  
High corrosive gas resistance-sealed construction by O ring assures high contact reliability



## TYPICAL APPLICATIONS

- For detection of tip
  - Gas heaters
  - Electric air conditioners
  - Electric fans
- For criminal detection
  - Vending machines
  - Public phones
  - Amusement equipments

## ORDERING INFORMATION

Vertical mounting type	Part number	Horizontal mounting type	Part number
	AHF11		AHF12

## SPECIFICATIONS

### 1. Contact rating

0.1A 30VDC

Applicable range: 1mA 5VDC to 0.1A 30VDC

### 2. Characteristics


Expected electrical life (Min. operations)	0.1A 30VDC resistive	Min. $5 \times 10^3$
	1mA 5VDC resistive	Min. $10^6$
Insulation resistance		Min. 100 m at 500 VDC
Dielectric strength		100 Vrms for 1 min.
Vibration resistance		2.9 m/s <sup>2</sup> {0.3G} 40 to 400 Hz for 7 days 5 to 10 Hz at double amplitude of 10 mm, $5 \times 10^5$ cycles
Shock resistance		588 mm/s <sup>2</sup> {60G}, 6 directions, 3 times/each direction
Ambient temperature		-25°C to +85°C, -13°F to +185°F (not freezing below 0°C 32°F)
Ambient humidity		Max. 85%RH
Initial contact resistance		Max. 100 m (by voltage drop, 0.1A 6 to 8 VDC)

### 3. Operating characteristics


Operating angle (angle of turning off the circuit)	Goes off at more than 25 and less than 60 degrees in relation to the reference line (with an operation angle of 6 degrees/second in the X and Y directions)
Release angle (angle of turning on the circuit)	Goes on at 20 degrees or more (in the X and Y directions)

**DIMENSIONS**

**VERTICAL MOUNTING TYPE**




PC board pattern




Schematic




**HORIZONTAL MOUNTING TYPE**



PC board pattern



Schematic



**NOTES**

**1. Soldering operations**

1) for manual soldering  
Soldering should be accomplished in less than 8 seconds with a 60 watt iron max. (iron tip temperature: Max. 350°C 662°F)  
2) For automatic soldering  
Soldering should be done less than 10 seconds in 260°C 500°F solder bath or less than 3 seconds in 350°C 662°F solder bath.

**2. Environment**

Avoid using and keeping switches in the following conditions.

- In corrosive gases
- In a dusty environment
- Where silicon atmosphere prevails

**3. Quality check under actual loading conditions**

To assure reliability, check the switch under actual loading conditions.


**4. Recommended circuit for tip**

Contact chattering may happen when vibration or shock is applied to the switch because of a leaf spring and steel ball inside. Please detect a signal by following procedure.

- 1) Read access by a microcomputer should be done every 30 msec. at 1 mA 5VDC.
- 2) Two reading 'open' in succession should be judged as 'open' condition.
- 3) After the judgement, if the 'open' condition continues for more than 0.5 sec., the condition should be confirmed lastly.

<Example>

Microcomputer read access



**5. Others**

- Switch cover is set to the body through O-ring for sealing purpose. Do not disassemble the switch or the characteristics may change.
- For switching of inductive loads (relay, solenoids, buzzers, etc.), in order to prevent damage to contacts due to the occurrence of arcing, an arc absorbing circuit should be applied.