



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





AM-510 Commercial / Residential Digital Multimeter

AM-500 Digital Multimeter Series

The Amprobe AM-510 Commercial/Residential Multimeter is designed for light commercial and advanced residential applications. Re-wire electrical panels, install heated floors or new light fixtures, troubleshoot and repair home appliances, electrical sockets and automotive electrical problems with this easy-to-use multimeter. The AM-510 features a built-in flashlight to see wires and fuses in the dark, a rubber tilt stand and probe holder to give you the "third-hand" you need while taking measurements. Also offering safety features including Voltect non-contact voltage detection for quick go/no-go checks without the need for an additional tool. Compact yet tough, this multimeter is built to last through all your electrical projects.

- Voltage up to 600V ac/dc, ac/dc current and resistance
- Frequency, capacitance, duty cycle for troubleshooting applications
- Voltect™ Non-contact voltage detection
- Audible continuity
- Diode test
- Backlit LCD display
- Data hold
- Relative zero mode
- Auto and manual-ranging
- Built-in flashlight
- Built-in test leads storage and "third hand" probe holder
- Auto and manual-ranging
- Auto power off
- Low battery warning
- Safety rated: CAT III 600V

AM-510 DETAILED SPECIFICATIONS

Specifications	Range	Best Accuracy
AC Voltage	400 mV 4.000 / 40.00 / 400.0 / 600 V	±(1.0% Rdg + 3 LSD) @ 45 Hz to 400 Hz, 4 V to 400V ranges
DC Voltage	400 mV 4.000 / 40.00 / 400.0 / 600 V	±(0.8% Rdg + 1 LSD) @ 4 V to 400 V ranges
Resistance	400.0 Ohms 4.000 / 40.00 / 400.0 kOhms 4.000 / 40.00 MOhms	±(1.0% Rdg + 2 LSD) @ 4 kOhms to 400 kOhms ranges
AC Current	400.0 / 4000 µA 40.00 / 400.0 mA 4.000 / 10.00 A	±(1.2% Rdg + 3 LSD)
DC Current	400.0 / 4000 µA 40.00 / 400.0 mA 4.000 / 10.00 A	±(1.0% Rdg + 2 LSD)
Frequency	10Hz to 10MHz	±(0.1% Rdg + 4 LSD)
Capacitance	40.00 / 400.0 nF 4.000 / 40.00 / 100.0 µF	±(3.0% Rdg + 5 LSD) @ 400 nF to 40 µF ranges
Battery Test	1.5 V, 9 V	±(1.0% Rdg + 3 LSD)
Duty Cycle		0.1% to 99.9%

For more detailed specifications see instruction manual.

AM-500 SERIES SELECTION GUIDE

		AM-500	AM-510	AM-520	AM-530	AM-540	AM-550		
MULTIMETER TYPE		Autoranging	Com / Res	HVAC	Electrical	Adv. HVAC	Industrial		
Application:									
Functions	Safety Rating	Safety		CAT III 600V	CAT III 600V	CAT III 600V CAT II 1000V	CAT III 600V CAT II 1000V	CAT IV 600V CAT III 1000V	CAT IV 600V CAT III 1000V
	Measure voltage in noisy environments	True-rms							
	Electrical panels, AC outlets	AC Voltage (V)		600	600	750	750	1000	1000
	DC systems, auto/marine batteries	DC Voltage (V)		600	600	1000	1000	1000	1000
	AC Current - electrical panels, appliances	AC Current (A)		10	10	10	10	10	10
	DC Current - electronics, DC motors	DC Current (A)		10	10	10	10	10	10
	Specified resistance and continuity	Resistance (MOhms)		20	40	40	40	60	60
	Flame sensors	Micro Amps		■	■	■	■	■	■
	Diodes in ac to dc converters	Diode test		■	■	■	■	■	■
	Fuses, light bulbs, wire connections	Continuity		■	■	■	■	■	■
	Household batteries	Battery test		■	■				
	Motor startup or run capacitors	Capacitance			■	■	■	■	■
	Frequency verification	Frequency			■	■	■	■	■
	VolTect™ Non-contact voltage detection	Non-contact voltage			■	■	■	■	■
	Electrical load-time on vs. time off	Duty cycle			■			■	■
Temp of air vents, fuses, transformers	Temperature inputs				1	1	2	2	
Features	Automatically selects measurement range	Autoranging		■	■	■	■	■	■
	Manually select measurement range	Manual ranging			■	■	■	■	■
	Voltage on variable frequency drives	Low pass filter					■	■	■
	Detect stray voltages	Low Z						■	■
	Dimly lit areas	Built-in flashlight			■	■	■	■	■
Display	Meter resolution	LCD Counts		2,000	4,000	4,000	4,000	6,000	6,000
	Dimly lit areas	Backlight			■	■	■	■	■
	Monitoring fast changing signals	Bar graph				■	■	■	■
	Two relative measurements on one screen	Dual display						■	■
Events	Data memory	Data hold		■	■	■	■	■	■
	Difference between two measurements	Relative reading			■	■	■	■	■
	Max/min peak measurement	Max/min hold				■	■	■	■
	Specialized signal measurements	Peak hold (crest)					■	■	■

INCLUDED ACCESSORIES

Model	Batteries (Installed)	Test Leads	Temperature Probe	Temperature Adaptor	Velcro Strap	Carrying Case	User's Manual
AM-500	AAA x2	■					■
AM-510	9V (6F22) x1	■					■
AM-520	9V (6F22) x1	■	K-type probe x1		■	■	■
AM-530	9V (6F22) x1	■	K-type probe x1		■	■	■
AM-540	9V (6F22) x1	■	K-type probe x2	■	■	■	■
AM-550	9V (6F22) x1	■	K-type probe x2	■	■	■	■

Amprobe®

info@amprobe.com
 Everett, WA 98203
 Tel: 877-AMPROBE (267-7623)

Amprobe® Europe

In den Engematten 14,
 79286 Glottertal, Germany
 Tel.: +49 (0) 7684 8009 - 0