



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832


Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



## Key Features of AXO®-EVB3

- Printed Circuit Board for evaluation of AXO® products
- Includes 1 accelerometer and external passive components
- Plug and Play SPI interface, compatible with Arduino M0
- RS422 and USB interfaces for Arduino boards
- 5V single power supply
- 5V, 3.3V and 1.8V compatibility for communication interface



## 1. General Description

AXO®-EVB3 evaluation board is intended to easily and quickly perform characterizations of AXO215 accelerometers. AXO®-EVB3 was specially designed to be interfaced with an Arduino M0 board. The combination of AXO®-EVB3 with the Arduino platform is ideally suited for tests with rate table over the temperature range [-40°C to +85°C].

The 1.8V, 3.3V and 5V compatibility for SPI communication also enables connecting the AXO®-EVB3 with most of the acquisition systems and microcontrollers in the market.

This document describes the mechanical and electrical features of the AXO®-EVB3 board as well as the SPI protocol used for the digital communication. This document is applicable to the whole AXO product line, including AXO215 accelerometers.

For more information about performances of each product, please refer to the dedicated datasheet, available on our [website](#).

## 2. Mechanical features

The evaluation board has the following dimensions:




Figure 1: AXO-EVB3 board (unpopulated) dimensions in millimeters with 3D top view

The main AXO®-EVB3 components are described in the table 1:

Name	Description	Information
J1	I/O connector	AXO® I/O signals <ul style="list-style-type: none"> <li>• Enable pin: EN</li> <li>• Self-Test pin: ST</li> <li>• SPI Slave select: SSB</li> <li>• Data Ready pin: DRDY</li> </ul>
J2	I/O connector	Arduino UART signals (RX and TX)
J3	I/O connector	Tronics reserved
J4	I/O connector	Not used
J5	I/O connector	Power supply: 5V, VDDIO, GND
J6	I/O connector	Power supply lines: 5V, GND SPI lines: MOSI, MISO, SCLK
J7	AXO® Product	Linear acceleration sensor
J8	I/O connector	RS422 connector (RX+, RX-, TX+, TX-, GND)
J9	I/O connector	SPI level voltage reference: <ul style="list-style-type: none"> <li>• With jumper on +5V : SPI level = +5V</li> <li>• With jumper on 3V3/EXT : SPI level = VDDIO</li> </ul>
J10	I/O connector	Sensor reset: <ul style="list-style-type: none"> <li>• Without jumper: no reset</li> <li>• With jumper: reset</li> </ul>

Table 1: Main components description

Please note that the PCB has a flat backside and thickness of 1.6 mm. The board has been designed for a direct mounting onto the surface of your test equipment (rate table, vibration shaker...) in order to avoid parasitic mechanical resonance of the PCB.

### 3. Pins configuration and description

To enable compatibility with the Arduino M0 platform, some signals are redundant, such as 5V and GND signals. If you don't intend to use the Arduino platform, redundancy is not necessary. However the pins marked with bold characters in the tables below must absolutely be connected.

J1 gives access to the following signals:

Pin #	Name	Type	Function
#1	-	-	Not Connected
#2	-	-	Not Connected
#3	-	-	Not Connected
#4	GND	Power	Ground Power Supply
#5	-	-	Not Connected
#6	DRDY	Output	Data Ready pin
#7	<b>SSB</b>	<b>Input</b>	<b>SPI Slave Select pin</b>
#8	-	-	Not Connected
#9	ST	Output	Self-test pin
#10	<b>EN</b>	<b>Input</b>	<b>Enable pin</b>

J2 gives access to the following signals:

Pin #	Name	Type	Function
#1	RX	Input	Arduino UART RX
#2	TX	Output	Arduino UART TX
#3	-	-	Not Connected
#4	-	-	Not Connected
#5	-	-	Not Connected
#6	-	-	Not Connected
#7	-	-	Not Connected
#8	-	-	Not Connected

J3 gives access to the following signals:

Pin #	Name	Type	Function
#1	T0	Output	Tronics Reserved
#2	T1	Output	Tronics Reserved
#3	T2	Output	Tronics Reserved
#4	T3	Output	Tronics Reserved

J4 gives access to the following signals:

Pin #	Name	Type	Function
#1	-	-	Not Connected
#2	-	-	Not Connected
#3	-	-	Not Connected
#4	-	-	Not Connected
#5	-	-	Not Connected
#6	-	-	Not Connected

J5 gives access to the following signals:

Pin #	Name	Type	Function
#1	-	-	Not Connected
#2	-	-	Not Connected
#3	-	-	Not Connected
#4	<b>3V3 / EXT</b>	<b>Power</b>	<b>VDDIO Power Supply</b>
#5	<b>5V</b>	<b>Power</b>	<b>5V Power Supply</b>
#6	<b>GND</b>	<b>Power</b>	<b>Ground Power Supply</b>
#7	GND	Power	Ground Power Supply
#8	-	-	Not Connected

J6 gives access to the following signals:

Pin #	Name	Type	Function
#1	5V	Power	5V Power Supply
#2	<b>MOSI</b>	<b>Input</b>	<b>SPI data input</b>
#3	GND	Power	Ground Power Supply
#4	<b>MISO</b>	<b>Output</b>	<b>SPI data output</b>
#5	<b>SCLK</b>	<b>Input</b>	<b>SPI serial clock</b>
#6	-	-	Not Connected

J8 gives access to the following signals:

Pin #	Name	Type	Function
#1	TX+	Output	Arduino RS422 TX+
#2	TX-	Output	Arduino RS422 TX-
#3	RX-	Input	Arduino RS422 RX-
#4	RX+	Input	Arduino RS422 RX+
#5	GND	Power	Ground Power Supply
#6	5V	Power	Ground Power Supply

For more information about the RS422 interface and its use, please refer to the dedicated technical notes, available on our [website](#)

## 4. Electrical circuit

The following figure presents the electrical schematic of the board with its passive components (resistors & capacitances).




Figure 2: Electrical schematic

## 5. Electrical Characteristics

Parameter	Min	Typical	Max	Units
5V Power Supply (VDD)	4.75	5	5.25	V
Reference Voltage (VDDIO)	1.8	-	5	V
Current consumption <sup>1)</sup>		25		mA
Output		Digital 24 bits		-
Digital interface		SPI		-

1) The specified value represents the typical current consumption of AXO® products.

**Table 2: Electrical characteristics**

For more information about advanced use of AXO® product, please refer to the dedicated AXO® datasheet, available on our [website](#)

### Caution!



The product may be damaged by ESD, which can cause performance degradation or device failure! We recommend handling the device only on a static safe work station. Precaution for the storage should also be taken.

The sensor **MUST** be powered-on *before* any SPI operation. Having the SPI pads at a high level while VDD is at 0V could damage the sensor, due to ESD protection diodes and buffers.

## 6. Environment












Environmental specifications for AXO® accelerometers and AXO®-EVB3 are the following:

Parameter	Condition	Min	Typ	Max	Units
Operating temperature range		-40		+85	°C
Humidity	At 45°C			98	%

**Table 3: Environmental specifications**

## 7. Available Tools and Resources

The following tools and resources are available on [AXO®](#) webpage of Tronics website.

Item	Description
<b>Documentation &amp; technical notes</b>	
	<b>AXO215 - Flyer</b>
	<b>AXO215 - Datasheet</b>
<b>Mechanical tool</b>	
	<b>AXO215 - 3D model</b>
<b>Evaluation kit</b>	
	<b>AXO®-EVB3 – Evaluation board</b> <i>Evaluation board for AXO215, compatible with Arduino M0</i>
	<b>Tronics Evaluation Tool – Software</b>
	<b>AXO®-EVB3 – User manual</b>
	<b>Tronics Evaluation Kit – Quick Start Guide</b>
	<b>Tronics Evaluation Tool – Software User Manual</b>
	<b>Tronics Evaluation Tool – Installation Tutorial</b>
	<b>Tronics Evaluation Tool – Software Tutorial</b>
	<b>Tronics Evaluation Tool – Arduino Firmware</b>