

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









High Pass Filter 50Ω BNC 45 MHz 7th Order



Part Number: CHPFL-0045-BNC

New BNC

New Britters

Filters

High Pass

High Pass

CHPFL-0045-BNC

CHPFL-0045-BNC

Schematic
In/Out

In/Out

(65.79)

1.480

(37.59)

Features:

- 7th Order Chebyshev Response
- 50Ω BNC Connectors

Applications:

- Test Equipment
- Lab Use

Maximum Ratings:

- +36dBm (4 Watts)
- Operating Temperature: -40°C to 85°C
- Storage Temperature: -45°C to 90°C

Crystek's new line of BNC High Pass Filters are designed in a rugged BNC housing. This filter line has excellent out-of-band rejection.

BNC

Male

Designed for Test Equipment and General Lab Use.

Rev A
Page 1 of 3

0.550

(13.97)

 \bigcirc

BNC


Female




12730 Commonwealth Drive • Fort Myers, Florida 33913 Phone: 239-561-3311 • 800-237-3061 Fax: 239-561-1025 • www.crystek.com



High Pass Filter CHPFL-0045-BNC





Rev A

Page 2 of 3





High Pass Filter CHPFL-0045-BNC

FREQ (MHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)
0.300	74.72	0.05
1.799	100.11	0.02
3.297	100.34	0.01
4.796	112.09	0.01
6.294	109.07	0.02
7.793	101.67	0.03
9.291	106.44	0.04
10.790	89.65	0.06
12.288	81.67	0.08
13.787	73.61	0.11
15.285	67.14	0.14
16.784	61.01	0.18
18.282	55.27	0.23
19.781	49.92	0.28
21.279	44.91	0.35
22.778	40.15	0.43
24.276	35.63	0.53
25.775	31.31	0.65
27.273	27.16	0.80
28.772	23.17	0.99
30.270	19.36	1.24
31.769	15.75	1.59
33.267	12.39	2.08
36.264	6.88	3.90
37.763	4.93	5.37
39.261	3.55	7.19
42.258	2.06	11.19
43.757	1.69	13.03
57.243	0.73	22.91
69.231	0.51	32.25
78.222	0.43	25.89
105.195	0.35	18.19
120.180	0.32	17.09
168.132	0.27	16.60
195.105	0.24	17.00
225.075	0.20	17.79
273.027	0.16	19.78
300.000	0.15	20.99

_			
Proc	duict.	Con	rol

i roduct control.			
Crystek Part Number:	CHPFL-0045-BNC	Release Date:	09-Jul-2015
Revision Level:	Α	Responsible:	K. Piotrowicz

Rev A Page 3 of 3

