# mail

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





### DRF1400

500V, 30A, 30MHz

## MOSFET Half Bridge Hybrid

The DRF1400 is a half bridge hybrid containing two high power gate drivers and two power MOSFETs. It was designed to provide the system designer increased flexibility, higher performance and lowered cost over a non-integrated solution. This low parasitic approach, coupled with the Schmitt trigger input, Kelvin signal ground, anti-Ring function Invert and Non-invert select pin provide improved stability and control in Kilowatt to Multi-Kilowatt, High Frequency ISM applications.



#### **FEATURES**

Switching Frequency: DC TO 30MHz

• Inverting Non-Inverting Select

- B... = 5
- Low Pulse Width Distortion
- Single Power Supply (Per Section)
- 1V CMOS Schmitt Trigger Input 1V Hysteresis
- Switching Speed 3-4ns
- B<sub>Vds</sub> = 500V
- I<sub>ds</sub> = 30A avg. Per-section
- R<sub>ds(on)</sub> ≤ .24 Ohm
- P<sub>D</sub> = 550W Per-section
- RoHS Compliant

#### **TYPICAL APPLICATIONS**

- Class D Half Bridge RF Generetors
- Switch Mode Power Amplifiers
- HV Pulse Generators
- Ultrasound Transducer Drivers
- Acoustic Optical Modulators

#### **Driver Absolute Maximum Ratings**

Symbol	Parameter	Ratings	Unit
V <sub>DD</sub>	Supply Voltage	15	V
IN, FN	Input Single Voltages	7 to +5.5	v
I <sub>о РК</sub>	Output Current Peak	8	А
T <sub>JMAX</sub>	Operating Temperature	175	°C

#### **Driver Specifications**

Symbol	Parameter	Min	Тур	Мах	Unit
V <sub>DD</sub>	Supply Voltage	8	12	15	N
IN	Input Voltage	3		5	V
IN <sub>(R)</sub>	Input Voltage Rising Edge		3		20
IN <sub>(F)</sub>	Input Voltage Falling Edge		3		ns
I <sub>DDQ</sub>	Quiescent Current		2		mA
Ι <sub>ο</sub>	Output Current		8		А
C <sub>oss</sub>	Output Capacitance		2500		~ [
C <sub>iss</sub>	Input Capacitance		3		рг
R <sub>IN</sub>	Input Parallel Resistance		1		mΩ
V <sub>T(ON)</sub>	Input, Low to High Out	0.8		1.1	V
V <sub>T(OFF)</sub>	Input, High to Low Out	1.9		2.2	v
T <sub>DLY</sub>	Time Delay (throughput)		38		ns
t,	Rise Time		5		
t <sub>r</sub>	Fall Time		5		ns
T <sub>D</sub>	Prop. Delay		35		

#### **MOSFET Absolute Maximum Ratings (Per-Section)**

Symbol	Parameter	Min	Тур	Max	Unit
BV <sub>DSS</sub>	Drain Source Voltage	500			V
I <sub>D</sub>	Continuous Drain Current T <sub>HS</sub> = 25°C			30	А
R <sub>DS(on)</sub>	Drain-Source On State Resistance		0.24		Ω

#### **Dynamic Characteristics (Per-Section)**

Symbol	Parameter	Min	Тур	Max	Unit
C <sub>ISS</sub>	Input Capacitance		1800		
C <sub>oss</sub>	Output Capacitance		335		pF
C <sub>rss</sub>	Reverse Transfer Capacitance		75		

#### **Thermal Characteristics (Total Package)**

Symbol	Parameter	Ratings	Unit
R <sub>θJC</sub>	Junction to Case Thermal Resistance	.06	°C/M
R <sub>ØJHS</sub>	Junction to Heat Sink Thermal Resistance	.134	C/W
T <sub>JSTG</sub>	Storage Junction Temperature	-55 to 150	°C
P <sub>D</sub>	Maximum Power Dissipation @ T <sub>SINK</sub> = 25°C	1.1	KM
P <sub>DC</sub>	Total Power Dissipation @ $T_c = 25^{\circ}C$	2.5	r.vv

Section A and B Output Switching Performance					
Symbol	Characteristic	Min	Тур	Max	Тур
T <sub>on</sub>	Leading Edge 10% to 90%	2	3	4	
T <sub>OFF</sub>	Trailing Edge 10% to 90%	45	TBD	49	
T <sub>DLY(ON)</sub>	Total Throughput Delay Time, ON	47	TBD	45	
T <sub>DLY(OFF)</sub>	Total Throughput Delay Time, OFF	49	50	51	ns
$\Delta T_{DLY(ON)}$	Delta $T_{oN}$ Delay between Section A and B	-0.5	0	1.5	
$\Delta T_{\text{DLY(OFF)}}$	Delta T <sub>OFF</sub> Delay between Section A and B	0	0.6	1.3	

Microsemi reserves the right to change, without notice, the specifications and information contained herein.



#### Figure 1, DRF1400 Test Circuit Diagram

The DRF1400 is configured as a Half Bridge Hybrid incorporating two independent channels consisting of a driver, a high voltage MOSFET and by-pass capacitors. The function of the by-pass capacitors C1 and C2 is to reduce the internal parasitic loop inductance. This coupled with the tight geometry of the hybrid allows optimal gate drive to the MOSFET. This low parasitic approach coupled with the Schmitt trigger input (IN), Kelvin signal ground (SG) and the Anti-Ring function; provide improved stability and control in Kilowatt to Multi-Kilowatt high frequency applications. The IN pin should be referenced to the Kelvin Ground (SG) and is applied to a Schmitt Trigger. The SG pin is a Kelvin return for the IN pin only. The signal is then applied to the intermediate drivers and level shifters; this section contains proprietary circuitry designed specifically for ring abatement. To further increase the utility of the device the driver die and the MOSFET die are adjacent die selected. This provides a very close match in the turn on and propagation delays.

**DRF1400** 

None of the inputs to U1 or U2 of the DRF1400 are isolated for direct connection to a ground referenced power supply or control circuitry. **Isolation appropriate to the application is the responsibility of the end user.** It is imperative that high output currents be restricted to the Drain (17), Source (15) Output (16) and the C3 Bypass (18, 19) connection pins by design. See DRF100 for more information on Driver IC used in the device.

The Function (FN, pin 3 or pin 9) is the invert or non-invert select Pin, it is Internally held high.

Truth Table * Referenced to SG				
FN (pin 3)	IN (pin 4)	MOSFET		
HIGH	HIGH	ON		
HIGH	LOW	OFF		
LOW	HIGH	OFF		
LOW	LOW	ON		

Truth Table * Referenced to SG				
FN (pin 9)	IN (pin 10)	MOSFET		
HIGH	HIGH	ON		
HIGH	LOW	OFF		
LOW	HIGH	OFF		
LOW	LOW	ON		



#### Figure 2, DRF1400 Test Circuit

The test circuit illustrated in Figure 2 was used to evaluate the DRF1400. The input control signal is applied via IN and SG pins using RG188. This provides excellent noise immunity and control of the signal ground currents. The  $+V_{DD}$  inputs (pins 2, 6, 8 and 12) should be heavily by-passed by 1uF capacitors as close to the pins as possible. The capacitors used for this function must be capable of supporting the RMS currents and frequency of the gate load. A 50 Ohm (RL) load is used to evaluate the output performance.

DRF1400

Pin Assignments			
Pin 1	High Side GND		
Pin 2	U1 +Vdd		
Pin 3	U1 FN		
Pin 4	U1 IN		
Pin 5	U1 SG		
Pin 6	U1 +Vdd		
Pin 7	High Side GND		
Pin 8	Low Side GND		
Pin 9	U2 +Vdd		
Pin 10	U2 FN		
Pin 11	U2 IN		
Pin 12	U2 SG		
Pin 13	U2 +Vdd		
Pin 14	Low Side GND		
Pin 15	Source		
Pin 16	Output		
Pin 17	Drain		



