



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China

DATA SHEET

For a complete data sheet, please also download:

- The IC04 LOC莫斯 HE4000B Logic Family Specifications HEF, HEC
- The IC04 LOC莫斯 HE4000B Logic Package Outlines/Information HEF, HEC

HEF4514B MSI

**1-of-16 decoder/demultiplexer with
input latches**

Product specification
File under Integrated Circuits, IC04

January 1995

1-of-16 decoder/demultiplexer with input latches**HEF4514B
MSI****DESCRIPTION**

The HEF4514B is a 1-of-16 decoder/demultiplexer, having four binary weighted address inputs (A_0 to A_3), a latch enable input (EL), and an active LOW enable input (\bar{E}). The 16 outputs (O_0 to O_{15}) are mutually exclusive active HIGH. When EL is HIGH, the selected output is determined by the data on A_n . When EL goes LOW, the

last data present at A_n are stored in the latches and the outputs remain stable. When \bar{E} is LOW, the selected output, determined by the contents of the latch, is HIGH. At \bar{E} HIGH, all outputs are LOW. The enable input (\bar{E}) does not affect the state of the latch. When the HEF4514B is used as a demultiplexer, \bar{E} is the data input and A_0 to A_3 are the address inputs.




Fig.1 Functional diagram.




Fig.2 Pinning diagram.

PINNING

A_0 to A_3	address inputs
\bar{E}	enable input (active LOW)
EL	latch enable input
O_0 to O_{15}	outputs (active HIGH)

- HEF4514BP(N): 24-lead DIL; plastic (SOT101-1)
 HEF4514BD(F): 24-lead DIL; ceramic (cerdip) (SOT94)
 HEF4514BT(D): 24-lead SO; plastic (SOT137-1)

(): Package Designator North America

APPLICATION INFORMATION

Some examples of applications for the HEF4514B are:

- Digital multiplexing.
- Address decoding.
- Hexadecimal/BCD decoding.

FAMILY DATA, I_{DD} LIMITS category MSI

See Family Specifications

1-of-16 decoder/demultiplexer with input latches


HEF4514B
MSI

Fig.3 Logic diagram.




Fig.4 Logic diagram (one latch).

1-of-16 decoder/demultiplexer with input latches

HEF4514B
MSI

TRUTH TABLE

INPUTS					OUTPUTS															
\bar{E}	A_0	A_1	A_2	A_3	O_0	O_1	O_2	O_3	O_4	O_5	O_6	O_7	O_8	O_9	O_{10}	O_{11}	O_{12}	O_{13}	O_{14}	O_{15}
H	X	X	X	X	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L
L	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L	L	L	L	L	L
L	H	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L	L	L	L	L
L	L	H	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L	L	L	L
L	H	H	L	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L	L	L
L	L	L	H	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L	L	L
L	H	L	H	L	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L	L
L	L	H	H	L	L	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L
L	H	H	H	L	L	L	L	L	L	H	L	L	L	L	L	L	L	L	L	L
L	L	L	L	H	L	L	L	L	L	L	H	L	L	L	L	L	L	L	L	L
L	H	L	L	H	L	L	L	L	L	L	L	H	L	L	L	L	L	L	L	L
L	L	H	L	H	L	L	L	L	L	L	L	L	H	L	L	L	L	L	L	L
L	H	H	L	H	L	L	L	L	L	L	L	L	L	H	L	L	L	L	L	L
L	L	L	H	H	L	L	L	L	L	L	L	L	L	L	H	L	L	L	L	L
L	H	L	H	H	L	L	L	L	L	L	L	L	L	L	L	H	L	L	L	L
L	L	H	H	H	L	L	L	L	L	L	L	L	L	L	L	L	H	L	L	L
L	H	H	H	H	L	L	L	L	L	L	L	L	L	L	L	L	L	L	H	L

Notes

- EL = HIGH; H = HIGH state (the more positive voltage);
L = LOW state (the less positive voltage); X = state is immaterial

AC CHARACTERISTICS

 $V_{SS} = 0 \text{ V}$; $T_{amb} = 25^\circ\text{C}$; $C_L = 50 \text{ pF}$; input transition times $\leq 20 \text{ ns}$

	V_{DD} V	SYMBOL	TYP.	MAX.		TYPICAL EXTRAPOLATION FORMULA
Propagation delays A_n , EL \rightarrow O_n HIGH to LOW	5	t_{PHL}	260	520	ns	233 ns + (0,55 ns/pF) C_L
	10		95	190	ns	84 ns + (0,23 ns/pF) C_L
	15		65	130	ns	57 ns + (0,16 ns/pF) C_L
	5	t_{PLH}	270	550	ns	243 ns + (0,55 ns/pF) C_L
	10		95	190	ns	84 ns + (0,23 ns/pF) C_L
	15		65	130	ns	57 ns + (0,16 ns/pF) C_L
	5	t_{PHL}	175	350	ns	148 ns + (0,55 ns/pF) C_L
	10		65	130	ns	54 ns + (0,23 ns/pF) C_L
	15		45	90	ns	37 ns + (0,16 ns/pF) C_L
	5	t_{PLH}	200	400	ns	173 ns + (0,55 ns/pF) C_L
	10		70	140	ns	59 ns + (0,23 ns/pF) C_L
	15		50	100	ns	42 ns + (0,16 ns/pF) C_L

1-of-16 decoder/demultiplexer with input latches

HEF4514B
MSI**AC CHARACTERISTICS** $V_{SS} = 0 \text{ V}$; $T_{amb} = 25 \text{ }^{\circ}\text{C}$; $C_L = 50 \text{ pF}$; input transition times $\leq 20 \text{ ns}$

	V_{DD} V	SYMBOL	MIN.	TYP.	MAX.	TYPICAL EXTRAPOLATION FORMULA
Output transition times HIGH to LOW	5	t_{THL}	90	180	ns	40 ns + (1,0 ns/pF) C_L
	10		35	65	ns	14 ns + (0,42 ns/pF) C_L
	15		25	50	ns	11 ns + (0,28 ns/pF) C_L
	5 LOW to HIGH	t_{TLH}	85	170	ns	35 ns + (1,0 ns/pF) C_L
			35	70	ns	14 ns + (0,42 ns/pF) C_L
			25	50	ns	11 ns + (0,28 ns/pF) C_L
Set-up time $A_n \rightarrow EL$	5	t_{SU}	120	60	ns	see also waveforms Fig.5
	10		40	20	ns	
	15		30	15	ns	
Hold time $A_n \rightarrow EL$	5	t_{hold}	0	60	ns	
	10		0	20	ns	
	15		0	15	ns	
Minimum EL pulse width; HIGH	5	t_{WELH}	120	60	ns	
	10		40	20	ns	
	15		30	15	ns	

	V_{DD} V	TYPICAL FORMULA FOR P (μW)	
Dynamic power dissipation per package (P)	5 10 15	$1100 f_i + \sum (f_o C_L) \times V_{DD}^2$ $5500 f_i + \sum (f_o C_L) \times V_{DD}^2$ $16\,000 f_i + \sum (f_o C_L) \times V_{DD}^2$	where f_i = input freq. (MHz) f_o = output freq. (MHz) C_L = load capacitance (pF) $\sum (f_o C_L)$ = sum of outputs V_{DD} = supply voltage (V)

1-of-16 decoder/demultiplexer with input latches


HEF4514B
MSI

Fig.5 Waveforms showing minimum pulse width for EL, set-up and hold times for A_n to EL. Set-up and hold times are shown as positive values but may be specified as negative values.