



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China

# 10-CHANNEL HIGH DEFINITION AUDIO CODEC

STAC9271/9274

## Description

The STAC9271/74 are Theater Quality 10-channel audio CODECs that enable systems with 7.1 audio playing simultaneously with VoIP or another stereo audio stream. IDT's proprietary  $\Sigma\Delta$  technology provides high fidelity with an estimated DAC SNR up to 105dB. Up to four digital microphones are supported enabling high quality voice input for increased usability of voice applications.

## Features

- **High performance HD Audio CODEC provides Theater Quality Audio**
- **High performance  $\Sigma\Delta$  technology**
  - 105dB DAC SNR
  - 90dB ADC SNR
- **Five Stereo DACs and three stereo ADCs**
  - Supports 7.1 Audio with simultaneous Real Time Communication (RTC) channel such as VoIP or separate stereo audio stream
- **24-bit resolution with up to 192 KHz sample rates**
- **Digital Microphone Interface (STAC9274)**
  - Direct interface up to four Digital Microphones
- **Analog Stereo Microphone**
  - Microphone Boost 0, 10, 20, 30, 40dB
  - Six adjustable Vref outputs for microphone bias
- **Integrated Headphone Amps (3)**
- **S/PDIF In and Out**
- **ADAT® Optical "Lightpipe" Output Support (STAC9274)**
- **Volume Up/Down Control**
- **Jack Insertion Detect and Impedance Sensing supports Jack Retasking and Universal Jacks**



- **Digital PC Beep to all outputs**
- **+5 V analog power supply options**
- **Environmental 48-pin LQFP package**

## Software Support

- **SKPI (Kernel Processing Interface)**
  - Enables plug-ins that can operate globally on all audio streams of the system
- **12 band parametric equalizer SKPI plug-in**
  - Constant, system-level effects tuned to optimize a particular platform can be combined with user-mode "presets" tailored for specific acoustical environments and applications
  - System-level effects automatically disabled when external connections made
- **Dynamics Processing SKPI plug-in**
  - Enables improved voice articulation
  - Compressor/limiter allows higher average noise level without resonances
- **Dolby PC Entertainment Experience Logo Program**
  - Dolby Master Studio™ (STAC9274D)
  - Dolby Home Theater™ (STAC9271D, STAC9274D)
  - Dolby Sound Room™(STAC9271D, STAC9274D)
- **Dolby Technologies**
  - Dolby Headphone™, Dolby Virtual Speaker™
  - Dolby ProLogic II™, Dolby ProLogic IIx™
  - Dolby Digital Live™
- **Intel Audio Studio™ from Sonic Focus**
- **Maxx Player™ from Waves**
- **Microphone Beam Forming, Acoustic Echo Cancellation, & Noise Suppression from Knowles™**

## Table of Contents

<b>1. DESCRIPTION .....</b>	<b>14</b>
<b>2. CHARACTERISTICS .....</b>	<b>15</b>
2.1. Audio Fidelity .....	15
2.2. Electrical Specifications .....	15
2.2.1. Absolute Maximum Ratings .....	15
2.2.2. Recommended Operation Conditions .....	15
2.3. STAC9271/74 5 V, 4.5 V, 4.0 V and 3.3 V Analog Performance Characteristics .....	17
<b>3. DETAILED DESCRIPTION .....</b>	<b>21</b>
3.1. Universal Jacks™ .....	21
3.1.1. Audio Jack Presence Detect .....	21
3.2. SPDIF Input .....	22
3.3. SPDIF Output .....	23
3.4. ADAT® Output (STAC9274) .....	23
3.5. Digital Microphone Support (STAC9274) .....	23
3.6. Analog PC-Beep .....	27
3.7. Headphone Drivers (Restrictions) .....	27
3.8. Device IDs .....	27
<b>4. FUNCTIONAL BLOCK DIAGRAMS .....</b>	<b>28</b>
4.1. STAC9274 .....	28
4.2. STAC9271 .....	29
<b>5. WIDGET DIAGRAM .....</b>	<b>30</b>
5.1. Pin Configuration Default Register Settings .....	31
<b>6. WIDGET INFORMATION .....</b>	<b>32</b>
6.1. Root Node (NID = 0x00) .....	34
6.1.1. Root ID .....	34
6.1.2. Root RevID .....	34
6.1.3. Root NodeInfo .....	35
6.2. AFG Node (NID = 0x01) .....	35
6.2.1. AFG Reset .....	35
6.2.2. AFG NodeInfo .....	36
6.2.3. AFG Type .....	36
6.2.4. AFG Type .....	36
6.2.5. AFG PCMCap .....	37
6.2.6. AFG Stream .....	38
6.2.7. AFG InAmpCap .....	39
6.2.8. AFG SupPwrState .....	39
6.2.9. AFG GPIOCnt .....	40
6.2.10. AFG OutAmpCap .....	41
6.2.11. AFG PwrState .....	41
6.2.12. AFG UnsolResp .....	42
6.2.13. AFG GPIO .....	42
6.2.14. AFG GPIOEn .....	43
6.2.15. AFG GPIODir .....	44
6.2.16. AFG GPIOWakeEn .....	45
6.2.17. AFG GPIOUnsol .....	46
6.2.18. AFG GPIOSticky .....	47
6.2.19. AFG SubID .....	48
6.2.20. AFG TCKT .....	49
6.2.21. AFG Sply .....	49
6.2.22. AFG DACMode .....	50
6.2.23. AFG GPIOPlrty .....	51
6.2.24. AFG GPIODrive .....	52
6.2.25. AFG DMic .....	53

6.3. DAC0 Node (NID = 0x02) .....	54
6.3.1. DAC0 Cnvtr .....	54
6.3.2. DAC0 OutAmpRight .....	55
6.3.3. DAC0 OutAmpLeft .....	55
6.3.4. DAC0 WCap .....	56
6.3.5. DAC0 PwrState .....	57
6.3.6. DAC0 CnvtrID .....	57
6.3.7. DAC0 LR .....	58
6.4. DAC1 Node (NID = 0x03) .....	58
6.4.1. DAC1 Cnvtr .....	58
6.4.2. DAC1 OutAmpRight .....	60
6.4.3. DAC1 OutAmpLeft .....	60
6.4.4. DAC1 WCap .....	60
6.4.5. DAC1 PwrState .....	61
6.4.6. DAC1 CnvtrID .....	62
6.4.7. DAC1 LR .....	63
6.5. DAC2 Node (NID = 0x04) .....	63
6.5.1. DAC2 Cnvtr .....	63
6.5.2. DAC2 OutAmpRight .....	64
6.5.3. DAC2 OutAmpLeft .....	65
6.5.4. DAC2 WCap .....	65
6.5.5. DAC2 PwrState .....	66
6.5.6. DAC2 CnvtrID .....	67
6.5.7. DAC2 LR .....	67
6.6. DAC3 Node (NID = 0x05) .....	68
6.6.1. DAC3 Cnvtr .....	68
6.6.2. DAC3 OutAmpRight .....	69
6.6.3. DAC3 OutAmpLeft .....	70
6.6.4. DAC3 WCap .....	70
6.6.5. DAC3 PwrState .....	71
6.6.6. DAC3 CnvtrID .....	72
6.6.7. DAC3 LR .....	72
6.7. DAC4 Node (NID = 0x06) .....	73
6.7.1. DAC4 Cnvtr .....	73
6.7.2. DAC4 OutAmpRight .....	74
6.7.3. DAC4 OutAmpLeft .....	74
6.7.4. DAC4 WCap .....	75
6.7.5. DAC4 PwrState .....	76
6.7.6. DAC4 CnvtrID .....	76
6.7.7. DAC4 LR .....	77
6.8. ADC0 Node (NID = 0x07) .....	77
6.8.1. ADC0 Cnvtr .....	77
6.8.2. ADC0 WCap .....	79
6.8.3. ADC0 ConLst .....	80
6.8.4. ADC0 ConLstEntry .....	80
6.8.5. ADC0 ProcState .....	80
6.8.6. ADC0 PwrState .....	81
6.8.7. ADC0 CnvtrID .....	82
6.9. ADC1 Node (NID = 0x08) .....	82
6.9.1. ADC1 Cnvtr .....	82
6.9.2. ADC1 WCap .....	83
6.9.3. ADC1 ConLst .....	84
6.9.4. ADC1 ConLstEntry .....	85
6.9.5. ADC1 ProcState .....	85
6.9.6. ADC1 PwrState .....	86

6.9.7. ADC1 CnvtrID .....	87
6.10. ADC2 Node (NID = 0x09) .....	87
6.10.1. ADC2 Cnvtr .....	87
6.10.2. ADC2 WCap .....	88
6.10.3. ADC2 ConLst .....	89
6.10.4. ADC2 ConLstEntry .....	90
6.10.5. ADC2 ProcState .....	90
6.10.6. ADC2 PwrState .....	91
6.10.7. ADC2 CnvtrID .....	92
6.11. SPDIFOut Node (NID = 0x1E) .....	92
6.11.1. SPDIFOut Cnvtr .....	92
6.11.2. SPDIFOut WCap .....	93
6.11.3. SPDIFOut PCM .....	94
6.11.4. SPDIFOut Stream .....	96
6.11.5. SPDIFOut CnvtrID .....	96
6.11.6. SPDIFOut DigCnvtr .....	97
6.12. SPDIFIn Node (NID = 0x20) .....	97
6.12.1. SPDIFIn Cnvtr .....	97
6.12.2. SPDIFIn WCap .....	99
6.12.3. SPDIFIn PCMCap .....	100
6.12.4. SPDIFIn Stream .....	101
6.12.5. SPDIFIn ConLst .....	101
6.12.6. SPDIFIn ConLstEntry .....	101
6.12.7. SPDIFIn CnvtrID .....	102
6.12.8. SPDIFIn DigCnvtr .....	102
6.12.9. SPDIFIn VCSR0 .....	103
6.13. PortA Node (NID = 0x0A) .....	105
6.13.1. PortA WCap .....	105
6.13.2. PortA PinCap .....	106
6.13.3. PortA ConLst .....	107
6.13.4. PortA ConLstEntry .....	108
6.13.5. PortA ConSelectCtrl .....	108
6.13.6. PortA PinWCntrl .....	109
6.13.7. PortA UnsolResp .....	109
6.13.8. PortA ChSense .....	110
6.13.9. PortA ConfigDefault .....	111
6.14. PortB Node (NID = 0x0B) .....	111
6.14.1. PortB WCap .....	111
6.14.2. PortB PinCap .....	112
6.14.3. PortB ConLst .....	113
6.14.4. PortB ConLstEntry .....	114
6.14.5. PortB ConSelectCtrl .....	114
6.14.6. PortB PinWCntrl .....	115
6.14.7. PortB UnsolResp .....	115
6.14.8. PortB ChSense .....	116
6.14.9. PortB ConfigDefault .....	117
6.15. PortC Node (NID = 0x0C) .....	117
6.15.1. PortC WCap .....	117
6.15.2. PortC PinCap .....	118
6.15.3. PortC ConLst .....	119
6.15.4. PortC ConLstEntry .....	120
6.15.5. PortC PinWCntrl .....	120
6.15.6. PortC UnsolResp .....	121
6.15.7. PortC ChSense .....	121
6.15.8. PortC ConfigDefault .....	122

6.16. PortD Node (NID = 0x0D) .....	123
6.16.1. PortD WCap .....	123
6.16.2. PortD PinCap .....	124
6.16.3. PortD ConLst .....	124
6.16.4. PortD ConLstEntry .....	125
6.16.5. PortD PinWCntrl .....	125
6.16.6. PortD UnsolResp .....	126
6.16.7. PortD ChSense .....	127
6.16.8. PortD ConfigDefault .....	127
6.17. PortE Node (NID = 0x0E) .....	128
6.17.1. PortE WCap .....	128
6.17.2. PortE PinCap .....	129
6.17.3. PortE ConLst .....	130
6.17.4. PortE ConLstEntry .....	130
6.17.5. PortE PinWCntrl .....	131
6.17.6. PortE UnsolResp .....	131
6.17.7. PortE ChSense .....	132
6.17.8. PortE ConfigDefault .....	132
6.18. PortF Node (NID = 0x0F) .....	133
6.18.1. PortF WCap .....	133
6.18.2. PortF PinCap .....	134
6.18.3. PortF ConLst .....	135
6.18.4. PortF ConLstEntry .....	136
6.18.5. PortF PinWCntrl .....	136
6.18.6. PortF UnsolResp .....	137
6.18.7. PortF ChSense .....	137
6.18.8. PortF ConfigDefault .....	138
6.19. PortG Node (NID = 0x10) .....	139
6.19.1. PortG WCap .....	139
6.19.2. PortG PinCap .....	140
6.19.3. PortG ConLst .....	140
6.19.4. PortG ConLstEntry .....	141
6.19.5. PortG PinWCntrl .....	141
6.19.6. PortG UnsolResp .....	142
6.19.7. PortG ChSense .....	142
6.19.8. PortG ConfigDefault .....	143
6.20. PortH Node (NID = 0x11) .....	144
6.20.1. PortH WCap .....	144
6.20.2. PortH PinCap .....	145
6.20.3. PortH ConLst .....	145
6.20.4. PortH ConLstEntry .....	146
6.20.5. PortH PinWCntrl .....	146
6.20.6. PortH UnsolResp .....	147
6.20.7. PortH ChSense .....	147
6.20.8. PortH ConfigDefault .....	148
6.21. DMic0 Node (NID = 0x13) .....	149
6.21.1. DMic0 WCap .....	149
6.21.2. DMic0 PinCap .....	150
6.21.3. DMic0 PinWCntrl .....	151
6.21.4. DMic0 ConfigDefault .....	151
6.22. DMic1 Node (NID = 0x14) .....	152
6.22.1. DMic1 WCap .....	152
6.22.2. DMic1 PinCap .....	153
6.22.3. DMic1 PinWCntrl .....	154
6.22.4. DMic1 ConfigDefault .....	154

6.23. DigOut0 Node (NID = 0x21) .....	155
6.23.1. DigOut0 WCap .....	155
6.23.2. DigOut0 PinCap .....	156
6.23.3. DigOut0 ConLst .....	157
6.23.4. DigOut0 ConLstEntry0 .....	157
6.23.5. DigOut0 ConLstEntry4 .....	158
6.23.6. DigOut0 ConSelectCtrl .....	158
6.23.7. DigOut0 PinWCntrl .....	158
6.23.8. DigOut0 ConfigDefault .....	159
6.24. DigIn Node (NID = 0x22) .....	160
6.24.1. DigIn WCap .....	160
6.24.2. DigIn PinCap .....	161
6.24.3. DigIn PwrState .....	161
6.24.4. DigIn PinWCntrl .....	162
6.24.5. DigIn UnsolResp .....	162
6.24.6. DigIn ChSense .....	163
6.24.7. DigIn EAPD .....	164
6.24.8. DigIn ConfigDefault .....	164
6.25. InPort0Mux Node (NID = 0x15) .....	165
6.25.1. InPort0Mux WCap .....	165
6.25.2. InPort0Mux ConLst .....	166
6.25.3. InPort0Mux OutAmpCap .....	166
6.25.4. InPort0Mux OutAmpRight .....	167
6.25.5. InPort0Mux OutAmpLeft .....	167
6.25.6. InPort0Mux ConSelectCtrl .....	168
6.25.7. InPort0Mux ConLstEntry0 .....	168
6.25.8. InPort0Mux ConLstEntry4 .....	169
6.25.9. InPort0Mux ConLstEntry8 .....	169
6.26. InPort1Mux Node (NID = 0x16) .....	170
6.26.1. InPort1Mux WCap .....	170
6.26.2. InPort1Mux ConLst .....	171
6.26.3. InPort1Mux OutAmpCap .....	171
6.26.4. InPort1Mux OutAmpRight .....	172
6.26.5. InPort1Mux OutAmpLeft .....	172
6.26.6. InPort1Mux ConSelectCtrl .....	173
6.26.7. InPort1Mux ConLstEntry0 .....	173
6.26.8. InPort1Mux ConLstEntry4 .....	173
6.26.9. InPort1Mux ConLstEntry8 .....	174
6.27. InPort2Mux Node (NID = 0x17) .....	174
6.27.1. InPort2Mux WCap .....	174
6.27.2. InPort2Mux ConLst .....	175
6.27.3. InPort2Mux OutAmpCap .....	176
6.27.4. InPort2Mux OutAmpRight .....	176
6.27.5. InPort2Mux OutAmpLeft .....	177
6.27.6. InPort2Mux ConSelectCtrl .....	177
6.27.7. InPort2Mux ConLstEntry0 .....	178
6.27.8. InPort2Mux ConLstEntry4 .....	178
6.27.9. InPort2Mux ConLstEntry8 .....	179
6.28. PCBEEP Node (NID = 0x23) .....	179
6.28.1. PCBEEP OutAmpLeft .....	179
6.28.2. PCBEEP WCap .....	180
6.28.3. PCBEEP OutAmpCap .....	180
6.28.4. PCBEEP Gen .....	181
6.29. CD Node (NID = 0x12) .....	182
6.29.1. CD WCap .....	182

6.29.2. CD PinCap .....	183
6.29.3. CD PinWCntrl .....	183
6.29.4. CD ConfigDefault .....	184
6.30. ADATOut Node (NID = 0x1F) .....	185
6.30.1. ADATOut Cnvtr .....	185
6.30.2. ADATOut WCap .....	186
6.30.3. ADATOut CnvtrID .....	187
6.30.4. ADATOut DigCnvtr .....	187
6.30.5. ADATOut VCSR0 .....	188
6.31. VolumeKnob Node (NID = 0x24) .....	189
6.31.1. VolumeKnob WCap .....	189
6.31.2. VolumeKnob VolKnobCap .....	190
6.31.3. VolumeKnob ConLst .....	190
6.31.4. VolumeKnob ConLstEntry0 .....	191
6.31.5. VolumeKnob ConLstEntry4 .....	191
6.31.6. VolumeKnob UnsolResp .....	192
6.31.7. VolumeKnob Cntrl .....	192
6.31.8. VolumeKnob VCSR0 .....	193
6.32. InPort0Vol Node (NID = 0x18) .....	193
6.32.1. InPort0Vol WCap .....	193
6.32.2. InPort0Vol ConLst .....	194
6.32.3. InPort0Vol InAmpRight .....	195
6.32.4. InPort0Vol InAmpLeft .....	195
6.32.5. InPort0Vol ConLstEntry .....	196
6.33. InPort1Vol Node (NID = 0x19) .....	196
6.33.1. InPort1Vol WCap .....	196
6.33.2. InPort1Vol ConLst .....	197
6.33.3. InPort1Vol InAmpRight .....	198
6.33.4. InPort1Vol InAmpLeft .....	198
6.33.5. InPort1Vol ConLstEntry .....	198
6.34. InPort2Vol Node (NID = 0x1A) .....	199
6.34.1. InPort2Vol WCap .....	199
6.34.2. InPort2Vol ConLst .....	200
6.34.3. InPort2Vol InAmpRight .....	200
6.34.4. InPort2Vol InAmpLeft .....	201
6.34.5. InPort2Vol ConLstEntry .....	201
6.35. ADC0Mux Node (NID = 0x1B) .....	202
6.35.1. ADC0Mux WCap .....	202
6.35.2. ADC0Mux ConLst .....	203
6.35.3. ADC0Mux ConSelectCtrl .....	203
6.35.4. ADC0Mux ConLstEntry .....	203
6.35.5. ADC0Mux LR .....	204
6.35.6. ADC0Mux OutAmpCap .....	204
6.35.7. ADC0Mux OutAmpRight .....	205
6.35.8. ADC0Mux OutAmpLeft .....	205
6.36. ADC1Mux Node (NID = 0x1C) .....	206
6.36.1. ADC1Mux WCap .....	206
6.36.2. ADC1Mux ConLst .....	207
6.36.3. ADC1Mux ConSelectCtrl .....	207
6.36.4. ADC1Mux ConLstEntry .....	208
6.36.5. ADC1Mux LR .....	208
6.36.6. ADC1Mux OutAmpCap .....	209
6.36.7. ADC1Mux OutAmpRight .....	209
6.36.8. ADC1Mux OutAmpLeft .....	210
6.37. ADC2Mux Node (NID = 0x1D) .....	210

6.37.1. ADC2Mux WCap .....	210
6.37.2. ADC2Mux ConLst .....	211
6.37.3. ADC2Mux ConSelectCtrl .....	212
6.37.4. ADC2Mux ConLstEntry .....	212
6.37.5. ADC2Mux LR .....	213
6.37.6. ADC2Mux OutAmpCap .....	213
6.37.7. ADC2Mux OutAmpRight .....	214
6.37.8. ADC2Mux OutAmpLeft .....	214
<b>7. ORDERING INFORMATION .....</b>	<b>215</b>
7.1. Part Order Numbers .....	215
<b>8. PIN INFORMATION .....</b>	<b>216</b>
8.1. Pin Diagram .....	216
8.2. Pin Table .....	217
<b>9. PACKAGE OUTLINE AND PACKAGE DIMENSIONS .....</b>	<b>219</b>
9.1. 48-Pin LQFP .....	219
<b>10. SOLDER REFLOW PROFILE .....</b>	<b>220</b>
10.1. Standard Reflow Profile Data .....	220
10.2. Pb Free Process - Package Classification Reflow Temperatures .....	221
<b>11. REVISION HISTORY .....</b>	<b>222</b>

## List of Figures

Figure 1. Single Digital Microphone (data is ported to both left and right channels) .....	25
Figure 2. Stereo Digital Microphone Configuration .....	25
Figure 3. Quad Digital Microphone Configuration .....	26
Figure 4. 48-Pin LQFP Pinout .....	216
Figure 5. 48-Pin LQFP Package Outline and Package Dimensions .....	219
Figure 6. Reflow Profile .....	220

## List of Tables

Table 1. Impedance Sense .....	26
Table 3. Valid Digital Microphone Configurations .....	29
Table 4. DMIC_CLK and DMIC_0,1 Operation During Power States .....	29
Table 5. CODEC IDs .....	32
Table 6. Pin Configuration Default Settings .....	36
Table 7. High Definition Audio Widget .....	37
Table 8. Root ID Command Verb Format .....	39
Table 9. Root ID Command Response Format .....	39
Table 10. Root ReVID Command Verb Format .....	39
Table 11. Root ReVID Command Response Format .....	39
Table 12. Root NodeInfo Command Verb Format .....	40
Table 13. Root NodeInfo Command Response Format .....	40
Table 14. AFG Reset Command Verb Format .....	40
Table 15. AFG Reset Command Response Format .....	40
Table 16. AFG NodeInfo Command Verb Format .....	41
Table 17. AFG NodeInfo Command Response Format .....	41
Table 18. AFG Type Command Verb Format .....	41
Table 19. AFG Type Command Response Format .....	41
Table 20. AFG Cap Command Verb Format .....	41

Table 21. AFG Cap Command Response Format .....	42
Table 22. AFG PCMCap Command Verb Format .....	42
Table 23. AFG PCMCap Command Response Format .....	42
Table 24. AFG Stream Command Verb Format .....	43
Table 25. AFG Stream Command Response Format .....	43
Table 26. AFG InAmpCap Command Verb Format .....	44
Table 27. AFG InAmpCap Command Response Format .....	44
Table 28. AFG SupPwrState Command Verb Format .....	44
Table 29. AFG SupPwrState Command Response Format .....	44
Table 30. AFG GPIOCnt Command Verb Format .....	45
Table 31. AFG GPIOCnt Command Response Format .....	45
Table 32. AFG OutAmpCap Command Verb Format .....	46
Table 33. AFG OutAmpCap Command Response Format .....	46
Table 34. AFG PwrState Command Verb Format .....	46
Table 35. AFG PwrState Command Response Format .....	46
Table 36. AFG UnsolResp Command Verb Format .....	47
Table 37. AFG UnsolResp Command Response Format .....	47
Table 38. AFG GPIO Command Verb Format .....	47
Table 39. AFG GPIO Command Response Format .....	48
Table 40. AFG GPIOEn Command Verb Format .....	48
Table 41. AFG GPIOEn Command Response Format .....	49
Table 42. AFG GPIODir Command Verb Format .....	49
Table 43. AFG GPIODir Command Response Format .....	49
Table 44. AFG GPIOWakeEn Command Verb Format .....	50
Table 45. AFG GPIOWakeEn Command Response Format .....	50
Table 46. AFG GPIOUnsol Command Verb Format .....	51
Table 47. AFG GPIOUnsol Command Response Format .....	51
Table 48. AFG GPIOSticky Command Verb Format .....	52
Table 49. AFG GPIOSticky Command Response Format .....	52
Table 50. AFG SubID Command Verb Format .....	53
Table 51. AFG SubID Command Response Format .....	54
Table 52. AFG TCKT Command Verb Format .....	54
Table 53. AFG TCKT Command Response Format .....	54
Table 54. AFG Sply Command Verb Format .....	54
Table 55. AFG Sply Command Response Format .....	55
Table 56. AFG DACMode Command Verb Format .....	55
Table 57. AFG DACMode Command Response Format .....	55
Table 58. AFG GPIOPlrty Command Verb Format .....	56
Table 59. AFG GPIOPlrty Command Response Format .....	56
Table 60. AFG GPIODrive Command Verb Format .....	57
Table 61. AFG GPIODrive Command Response Format .....	57
Table 62. AFG DMic Command Verb Format .....	58
Table 63. AFG DMic Command Response Format .....	58
Table 64. DAC0 Cnvtr Command Verb Format .....	59
Table 65. DAC0 Cnvtr Command Response Format .....	59
Table 66. DAC0 OutAmpRight Command Verb Format .....	60
Table 67. DAC0 OutAmpRight Command Response Format .....	60
Table 68. DAC0 OutAmpLeft Command Verb Format .....	60
Table 69. DAC0 OutAmpLeft Command Response Format .....	61
Table 70. DAC0 WCap Command Verb Format .....	61
Table 71. DAC0 WCap Command Response Format .....	61
Table 72. DAC0 PwrState Command Verb Format .....	62
Table 73. DAC0 PwrState Command Response Format .....	62
Table 74. DAC0 CnvtrID Command Verb Format .....	62
Table 75. DAC0 CnvtrID Command Response Format .....	63

Table 76. DAC0 LR Command Verb Format .....	63
Table 77. DAC0 LR Command Response Format .....	63
Table 78. DAC1 Cnvtr Command Verb Format .....	63
Table 79. DAC1 Cnvtr Command Response Format .....	64
Table 80. DAC1 OutAmpRight Command Verb Format .....	65
Table 81. DAC1 OutAmpRight Command Response Format .....	65
Table 82. DAC1 OutAmpLeft Command Verb Format .....	65
Table 83. DAC1 OutAmpLeft Command Response Format .....	65
Table 84. DAC1 WCap Command Verb Format .....	65
Table 85. DAC1 WCap Command Response Format .....	66
Table 86. DAC1 PwrState Command Verb Format .....	66
Table 87. DAC1 PwrState Command Response Format .....	67
Table 88. DAC1 CnvtrID Command Verb Format .....	67
Table 89. DAC1 CnvtrID Command Response Format .....	67
Table 90. DAC1 LR Command Verb Format .....	68
Table 91. DAC1 LR Command Response Format .....	68
Table 92. DAC2 Cnvtr Command Verb Format .....	68
Table 93. DAC2 Cnvtr Command Response Format .....	68
Table 94. DAC2 OutAmpRight Command Verb Format .....	69
Table 95. DAC2 OutAmpRight Command Response Format .....	70
Table 96. DAC2 OutAmpLeft Command Verb Format .....	70
Table 97. DAC2 OutAmpLeft Command Response Format .....	70
Table 98. DAC2 WCap Command Verb Format .....	70
Table 99. DAC2 WCap Command Response Format .....	70
Table 100. DAC2 PwrState Command Verb Format .....	71
Table 101. DAC2 PwrState Command Response Format .....	71
Table 102. DAC2 CnvtrID Command Verb Format .....	72
Table 103. DAC2 CnvtrID Command Response Format .....	72
Table 104. DAC2 LR Command Verb Format .....	72
Table 105. DAC2 LR Command Response Format .....	73
Table 106. DAC3 Cnvtr Command Verb Format .....	73
Table 107. DAC3 Cnvtr Command Response Format .....	73
Table 108. DAC3 OutAmpRight Command Verb Format .....	74
Table 109. DAC3 OutAmpRight Command Response Format .....	74
Table 110. DAC3 OutAmpLeft Command Verb Format .....	75
Table 111. DAC3 OutAmpLeft Command Response Format .....	75
Table 112. DAC3 WCap Command Verb Format .....	75
Table 113. DAC3 WCap Command Response Format .....	75
Table 114. DAC3 PwrState Command Verb Format .....	76
Table 115. DAC3 PwrState Command Response Format .....	76
Table 116. DAC3 CnvtrID Command Verb Format .....	77
Table 117. DAC3 CnvtrID Command Response Format .....	77
Table 118. DAC3 LR Command Verb Format .....	77
Table 119. DAC3 LR Command Response Format .....	77
Table 120. DAC4 Cnvtr Command Verb Format .....	78
Table 121. DAC4 Cnvtr Command Response Format .....	78
Table 122. DAC4 OutAmpRight Command Verb Format .....	79
Table 123. DAC4 OutAmpRight Command Response Format .....	79
Table 124. DAC4 OutAmpLeft Command Verb Format .....	79
Table 125. DAC4 OutAmpLeft Command Response Format .....	80
Table 126. DAC4 WCap Command Verb Format .....	80
Table 127. DAC4 WCap Command Response Format .....	80
Table 128. DAC4 PwrState Command Verb Format .....	81
Table 129. DAC4 PwrState Command Response Format .....	81
Table 130. DAC4 CnvtrID Command Verb Format .....	81
Table 131. DAC4 CnvtrID Command Response Format .....	82
Table 132. DAC4 LR Command Verb Format .....	82
Table 133. DAC4 LR Command Response Format .....	82

Table 134. ADC0 Cnvtr Command Verb Format .....	82
Table 135. ADC0 Cnvtr Command Response Format .....	83
Table 136. ADC0 WCap Command Verb Format .....	84
Table 137. ADC0 WCap Command Response Format .....	84
Table 138. ADC0 ConLst Command Verb Format .....	85
Table 139. ADC0 ConLst Command Response Format .....	85
Table 140. ADC0 ConLstEntry Command Verb Format .....	85
Table 141. ADC0 ConLstEntry Command Response Format .....	85
Table 142. ADC0 ProcState Command Verb Format .....	85
Table 143. ADC0 ProcState Command Response Format .....	86
Table 144. ADC0 PwrState Command Verb Format .....	86
Table 145. ADC0 PwrState Command Response Format .....	86
Table 146. ADC0 CnvtrID Command Verb Format .....	87
Table 147. ADC0 CnvtrID Command Response Format .....	87
Table 148. ADC1 Cnvtr Command Verb Format .....	87
Table 149. ADC1 Cnvtr Command Response Format .....	87
Table 150. ADC1 WCap Command Verb Format .....	88
Table 151. ADC1 WCap Command Response Format .....	89
Table 152. ADC1 ConLst Command Verb Format .....	89
Table 153. ADC1 ConLst Command Response Format .....	90
Table 154. ADC1 ConLstEntry Command Verb Format .....	90
Table 155. ADC1 ConLstEntry Command Response Format .....	90
Table 156. ADC1 ProcState Command Verb Format .....	90
Table 157. ADC1 ProcState Command Response Format .....	91
Table 158. ADC1 PwrState Command Verb Format .....	91
Table 159. ADC1 PwrState Command Response Format .....	91
Table 160. ADC1 CnvtrID Command Verb Format .....	92
Table 161. ADC1 CnvtrID Command Response Format .....	92
Table 162. ADC2 Cnvtr Command Verb Format .....	92
Table 163. ADC2 Cnvtr Command Response Format .....	92
Table 164. ADC2 WCap Command Verb Format .....	93
Table 165. ADC2 WCap Command Response Format .....	94
Table 166. ADC2 ConLst Command Verb Format .....	94
Table 167. ADC2 ConLst Command Response Format .....	95
Table 168. ADC2 ConLstEntry Command Verb Format .....	95
Table 169. ADC2 ConLstEntry Command Response Format .....	95
Table 170. ADC2 ProcState Command Verb Format .....	95
Table 171. ADC2 ProcState Command Response Format .....	96
Table 172. ADC2 PwrState Command Verb Format .....	96
Table 173. ADC2 PwrState Command Response Format .....	96
Table 174. ADC2 CnvtrID Command Verb Format .....	97
Table 175. ADC2 CnvtrID Command Response Format .....	97
Table 176. SPDIFOut Cnvtr Command Verb Format .....	97
Table 177. SPDIFOut Cnvtr Command Response Format .....	97
Table 178. SPDIFOut WCap Command Verb Format .....	98
Table 179. SPDIFOut WCap Command Response Format .....	99
Table 180. SPDIFOut PCM Command Verb Format .....	99
Table 181. SPDIFOut PCM Command Response Format .....	100
Table 182. SPDIFOut Stream Command Verb Format .....	101
Table 183. SPDIFOut Stream Command Response Format .....	101
Table 184. SPDIFOut CnvtrID Command Verb Format .....	101
Table 185. SPDIFOut CnvtrID Command Response Format .....	101
Table 186. SPDIFOut DigCnvtr Command Verb Format .....	102
Table 187. SPDIFOut DigCnvtr Command Response Format .....	102
Table 188. SPDIFIn Cnvtr Command Verb Format .....	102

Table 189. SPDIFIn Cnvr Command Response Format .....	103
Table 190. SPDIFIn WCap Command Verb Format .....	104
Table 191. SPDIFIn WCap Command Response Format .....	104
Table 192. SPDIFIn PCMCap Command Verb Format .....	105
Table 193. SPDIFIn PCMCap Command Response Format .....	105
Table 194. SPDIFIn Stream Command Verb Format .....	106
Table 195. SPDIFIn Stream Command Response Format .....	106
Table 196. SPDIFIn ConLst Command Verb Format .....	106
Table 197. SPDIFIn ConLst Command Response Format .....	106
Table 198. SPDIFIn ConLstEntry Command Verb Format .....	106
Table 199. SPDIFIn ConLstEntry Command Response Format .....	107
Table 200. SPDIFIn CntrlID Command Verb Format .....	107
Table 201. SPDIFIn CntrlID Command Response Format .....	107
Table 202. SPDIFIn DigCnvr Command Verb Format .....	107
Table 203. SPDIFIn DigCnvr Command Response Format .....	108
Table 204. SPDIFIn VCSR0 Command Verb Format .....	108
Table 205. SPDIFIn VCSR0 Command Response Format .....	108
Table 206. PortA WCap Command Verb Format .....	110
Table 207. PortA WCap Command Response Format .....	111
Table 208. PortA PinCap Command Verb Format .....	111
Table 209. PortA PinCap Command Response Format .....	112
Table 210. PortA ConLst Command Verb Format .....	112
Table 211. PortA ConLst Command Response Format .....	112
Table 212. PortA ConLstEntry Command Verb Format .....	113
Table 213. PortA ConLstEntry Command Response Format .....	113
Table 214. PortA ConSelectCtrl Command Verb Format .....	113
Table 215. PortA ConSelectCtrl Command Response Format .....	113
Table 216. PortA PinWCntrl Command Verb Format .....	114
Table 217. PortA PinWCntrl Command Response Format .....	114
Table 218. PortA UnsolResp Command Verb Format .....	114
Table 219. PortA UnsolResp Command Response Format .....	115
Table 220. PortA ChSense Command Verb Format .....	115
Table 221. PortA ChSense Command Response Format .....	115
Table 222. PortA ConfigDefault Command Verb Format .....	116
Table 223. PortA ConfigDefault Command Response Format .....	116
Table 224. PortB WCap Command Verb Format .....	116
Table 225. PortB WCap Command Response Format .....	117
Table 226. PortB PinCap Command Verb Format .....	117
Table 227. PortB PinCap Command Response Format .....	118
Table 228. PortB ConLst Command Verb Format .....	118
Table 229. PortB ConLst Command Response Format .....	118
Table 230. PortB ConLstEntry Command Verb Format .....	119
Table 231. PortB ConLstEntry Command Response Format .....	119
Table 232. PortB ConSelectCtrl Command Verb Format .....	119
Table 233. PortB ConSelectCtrl Command Response Format .....	119
Table 234. PortB PinWCntrl Command Verb Format .....	120
Table 235. PortB PinWCntrl Command Response Format .....	120
Table 236. PortB UnsolResp Command Verb Format .....	120
Table 237. PortB UnsolResp Command Response Format .....	121
Table 238. PortB ChSense Command Verb Format .....	121
Table 239. PortB ChSense Command Response Format .....	121
Table 240. PortB ConfigDefault Command Verb Format .....	122
Table 241. PortB ConfigDefault Command Response Format .....	122
Table 242. PortC WCap Command Verb Format .....	122
Table 243. PortC WCap Command Response Format .....	123

Table 244. PortC PinCap Command Verb Format .....	123
Table 245. PortC PinCap Command Response Format .....	124
Table 246. PortC ConLst Command Verb Format .....	124
Table 247. PortC ConLst Command Response Format .....	124
Table 248. PortC ConLstEntry Command Verb Format .....	125
Table 249. PortC ConLstEntry Command Response Format .....	125
Table 250. PortC PinWCntrl Command Verb Format .....	125
Table 251. PortC PinWCntrl Command Response Format .....	125
Table 252. PortC UnsolResp Command Verb Format .....	126
Table 253. PortC UnsolResp Command Response Format .....	126
Table 254. PortC ChSense Command Verb Format .....	126
Table 255. PortC ChSense Command Response Format .....	126
Table 256. PortC ConfigDefault Command Verb Format .....	127
Table 257. PortC ConfigDefault Command Response Format .....	127
Table 258. PortD WCap Command Verb Format .....	128
Table 259. PortD WCap Command Response Format .....	128
Table 260. PortD PinCap Command Verb Format .....	129
Table 261. PortD PinCap Command Response Format .....	129
Table 262. PortD ConLst Command Verb Format .....	129
Table 263. PortD ConLst Command Response Format .....	130
Table 264. PortD ConLstEntry Command Verb Format .....	130
Table 265. PortD ConLstEntry Command Response Format .....	130
Table 266. PortD PinWCntrl Command Verb Format .....	130
Table 267. PortD PinWCntrl Command Response Format .....	131
Table 268. PortD UnsolResp Command Verb Format .....	131
Table 269. PortD UnsolResp Command Response Format .....	131
Table 270. PortD ChSense Command Verb Format .....	132
Table 271. PortD ChSense Command Response Format .....	132
Table 272. PortD ConfigDefault Command Verb Format .....	132
Table 273. PortD ConfigDefault Command Response Format .....	133
Table 274. PortE WCap Command Verb Format .....	133
Table 275. PortE WCap Command Response Format .....	133
Table 276. PortE PinCap Command Verb Format .....	134
Table 277. PortE PinCap Command Response Format .....	134
Table 278. PortE ConLst Command Verb Format .....	135
Table 279. PortE ConLst Command Response Format .....	135
Table 280. PortE ConLstEntry Command Verb Format .....	135
Table 281. PortE ConLstEntry Command Response Format .....	135
Table 282. PortE PinWCntrl Command Verb Format .....	136
Table 283. PortE PinWCntrl Command Response Format .....	136
Table 284. PortE UnsolResp Command Verb Format .....	136
Table 285. PortE UnsolResp Command Response Format .....	136
Table 286. PortE ChSense Command Verb Format .....	137
Table 287. PortE ChSense Command Response Format .....	137
Table 288. PortE ConfigDefault Command Verb Format .....	137
Table 289. PortE ConfigDefault Command Response Format .....	138
Table 290. PortF WCap Command Verb Format .....	138
Table 291. PortF WCap Command Response Format .....	138
Table 292. PortF PinCap Command Verb Format .....	139
Table 293. PortF PinCap Command Response Format .....	139
Table 294. PortF ConLst Command Verb Format .....	140
Table 295. PortF ConLst Command Response Format .....	140
Table 296. PortF ConLstEntry Command Verb Format .....	141
Table 297. PortF ConLstEntry Command Response Format .....	141
Table 298. PortF PinWCntrl Command Verb Format .....	141

Table 299. PortF PinWCntrl Command Response Format .....	141
Table 300. PortF UnsolResp Command Verb Format .....	142
Table 301. PortF UnsolResp Command Response Format .....	142
Table 302. PortF ChSense Command Verb Format .....	142
Table 303. PortF ChSense Command Response Format .....	142
Table 304. PortF ConfigDefault Command Verb Format .....	143
Table 305. PortF ConfigDefault Command Response Format .....	143
Table 306. PortG WCap Command Verb Format .....	144
Table 307. PortG WCap Command Response Format .....	144
Table 308. PortG PinCap Command Verb Format .....	145
Table 309. PortG PinCap Command Response Format .....	145
Table 310. PortG ConLst Command Verb Format .....	145
Table 311. PortG ConLst Command Response Format .....	146
Table 312. PortG ConLstEntry Command Verb Format .....	146
Table 313. PortG ConLstEntry Command Response Format .....	146
Table 314. PortG PinWCntrl Command Verb Format .....	146
Table 315. PortG PinWCntrl Command Response Format .....	146
Table 316. PortG UnsolResp Command Verb Format .....	147
Table 317. PortG UnsolResp Command Response Format .....	147
Table 318. PortG ChSense Command Verb Format .....	147
Table 319. PortG ChSense Command Response Format .....	148
Table 320. PortG ConfigDefault Command Verb Format .....	148
Table 321. PortG ConfigDefault Command Response Format .....	148
Table 322. PortH WCap Command Verb Format .....	149
Table 323. PortH WCap Command Response Format .....	149
Table 324. PortH PinCap Command Verb Format .....	150
Table 325. PortH PinCap Command Response Format .....	150
Table 326. PortH ConLst Command Verb Format .....	150
Table 327. PortH ConLst Command Response Format .....	151
Table 328. PortH ConLstEntry Command Verb Format .....	151
Table 329. PortH ConLstEntry Command Response Format .....	151
Table 330. PortH PinWCntrl Command Verb Format .....	151
Table 331. PortH PinWCntrl Command Response Format .....	151
Table 332. PortH UnsolResp Command Verb Format .....	152
Table 333. PortH UnsolResp Command Response Format .....	152
Table 334. PortH ChSense Command Verb Format .....	152
Table 335. PortH ChSense Command Response Format .....	153
Table 336. PortH ConfigDefault Command Verb Format .....	153
Table 337. PortH ConfigDefault Command Response Format .....	153
Table 338. DMic0 WCap Command Verb Format .....	154
Table 339. DMic0 WCap Command Response Format .....	154
Table 340. DMic0 PinCap Command Verb Format .....	155
Table 341. DMic0 PinCap Command Response Format .....	155
Table 342. DMic0 PinWCntrl Command Verb Format .....	156
Table 343. DMic0 PinWCntrl Command Response Format .....	156
Table 344. DMic0 ConfigDefault Command Verb Format .....	156
Table 345. DMic0 ConfigDefault Command Response Format .....	156
Table 346. DMic1 WCap Command Verb Format .....	157
Table 347. DMic1 WCap Command Response Format .....	157
Table 348. DMic1 PinCap Command Verb Format .....	158
Table 349. DMic1 PinCap Command Response Format .....	158
Table 350. DMic1 PinWCntrl Command Verb Format .....	159
Table 351. DMic1 PinWCntrl Command Response Format .....	159
Table 352. DMic1 ConfigDefault Command Verb Format .....	159
Table 353. DMic1 ConfigDefault Command Response Format .....	160

Table 354. DigOut0 WCap Command Verb Format .....	160
Table 355. DigOut0 WCap Command Response Format .....	160
Table 356. DigOut0 PinCap Command Verb Format .....	161
Table 357. DigOut0 PinCap Command Response Format .....	161
Table 358. DigOut0 ConLst Command Verb Format .....	162
Table 359. DigOut0 ConLst Command Response Format .....	162
Table 360. DigOut0 ConLstEntry0 Command Verb Format .....	162
Table 361. DigOut0 ConLstEntry0 Command Response Format .....	162
Table 362. DigOut0 ConLstEntry4 Command Verb Format .....	163
Table 363. DigOut0 ConLstEntry4 Command Response Format .....	163
Table 364. DigOut0 ConSelectCtrl Command Verb Format .....	163
Table 365. DigOut0 ConSelectCtrl Command Response Format .....	163
Table 366. DigOut0 PinWCntrl Command Verb Format .....	163
Table 367. DigOut0 PinWCntrl Command Response Format .....	164
Table 368. DigOut0 ConfigDefault Command Verb Format .....	164
Table 369. DigOut0 ConfigDefault Command Response Format .....	164
Table 370. DigIn WCap Command Verb Format .....	165
Table 371. DigIn WCap Command Response Format .....	165
Table 372. DigIn PinCap Command Verb Format .....	166
Table 373. DigIn PinCap Command Response Format .....	166
Table 374. DigIn PwrState Command Verb Format .....	166
Table 375. DigIn PwrState Command Response Format .....	167
Table 376. DigIn PinWCntrl Command Verb Format .....	167
Table 377. DigIn PinWCntrl Command Response Format .....	167
Table 378. DigIn UnsolResp Command Verb Format .....	167
Table 379. DigIn UnsolResp Command Response Format .....	168
Table 380. DigIn ChSense Command Verb Format .....	168
Table 381. DigIn ChSense Command Response Format .....	168
Table 382. DigIn EAPD Command Verb Format .....	169
Table 383. DigIn EAPD Command Response Format .....	169
Table 384. DigIn ConfigDefault Command Verb Format .....	169
Table 385. DigIn ConfigDefault Command Response Format .....	169
Table 386. InPort0Mux WCap Command Verb Format .....	170
Table 387. InPort0Mux WCap Command Response Format .....	170
Table 388. InPort0Mux ConLst Command Verb Format .....	171
Table 389. InPort0Mux ConLst Command Response Format .....	171
Table 390. InPort0Mux OutAmpCap Command Verb Format .....	171
Table 391. InPort0Mux OutAmpCap Command Response Format .....	171
Table 392. InPort0Mux OutAmpRight Command Verb Format .....	172
Table 393. InPort0Mux OutAmpRight Command Response Format .....	172
Table 394. InPort0Mux OutAmpLeft Command Verb Format .....	172
Table 395. InPort0Mux OutAmpLeft Command Response Format .....	173
Table 396. InPort0Mux ConSelectCtrl Command Verb Format .....	173
Table 397. InPort0Mux ConSelectCtrl Command Response Format .....	173
Table 398. InPort0Mux ConLstEntry0 Command Verb Format .....	173
Table 399. InPort0Mux ConLstEntry0 Command Response Format .....	173
Table 400. InPort0Mux ConLstEntry4 Command Verb Format .....	174
Table 401. InPort0Mux ConLstEntry4 Command Response Format .....	174
Table 402. InPort0Mux ConLstEntry8 Command Verb Format .....	174
Table 403. InPort0Mux ConLstEntry8 Command Response Format .....	174
Table 404. InPort1Mux WCap Command Verb Format .....	175
Table 405. InPort1Mux WCap Command Response Format .....	175
Table 406. InPort1Mux ConLst Command Verb Format .....	176
Table 407. InPort1Mux ConLst Command Response Format .....	176
Table 408. InPort1Mux OutAmpCap Command Verb Format .....	176

Table 409. InPort1Mux OutAmpCap Command Response Format .....	176
Table 410. InPort1Mux OutAmpRight Command Verb Format .....	177
Table 411. InPort1Mux OutAmpRight Command Response Format .....	177
Table 412. InPort1Mux OutAmpLeft Command Verb Format .....	177
Table 413. InPort1Mux OutAmpLeft Command Response Format .....	177
Table 414. InPort1Mux ConSelectCtrl Command Verb Format .....	178
Table 415. InPort1Mux ConSelectCtrl Command Response Format .....	178
Table 416. InPort1Mux ConLstEntry0 Command Verb Format .....	178
Table 417. InPort1Mux ConLstEntry0 Command Response Format .....	178
Table 418. InPort1Mux ConLstEntry4 Command Verb Format .....	178
Table 419. InPort1Mux ConLstEntry4 Command Response Format .....	179
Table 420. InPort1Mux ConLstEntry8 Command Verb Format .....	179
Table 421. InPort1Mux ConLstEntry8 Command Response Format .....	179
Table 422. InPort2Mux WCap Command Verb Format .....	179
Table 423. InPort2Mux WCap Command Response Format .....	180
Table 424. InPort2Mux ConLst Command Verb Format .....	180
Table 425. InPort2Mux ConLst Command Response Format .....	181
Table 426. InPort2Mux OutAmpCap Command Verb Format .....	181
Table 427. InPort2Mux OutAmpCap Command Response Format .....	181
Table 428. InPort2Mux OutAmpRight Command Verb Format .....	181
Table 429. InPort2Mux OutAmpRight Command Response Format .....	182
Table 430. InPort2Mux OutAmpLeft Command Verb Format .....	182
Table 431. InPort2Mux OutAmpLeft Command Response Format .....	182
Table 432. InPort2Mux ConSelectCtrl Command Verb Format .....	182
Table 433. InPort2Mux ConSelectCtrl Command Response Format .....	183
Table 434. InPort2Mux ConLstEntry0 Command Verb Format .....	183
Table 435. InPort2Mux ConLstEntry0 Command Response Format .....	183
Table 436. InPort2Mux ConLstEntry4 Command Verb Format .....	183
Table 437. InPort2Mux ConLstEntry4 Command Response Format .....	183
Table 438. InPort2Mux ConLstEntry8 Command Verb Format .....	184
Table 439. InPort2Mux ConLstEntry8 Command Response Format .....	184
Table 440. PCBEEP OutAmpLeft Command Verb Format .....	184
Table 441. PCBEEP OutAmpLeft Command Response Format .....	184
Table 442. PCBEEP WCap Command Verb Format .....	185
Table 443. PCBEEP WCap Command Response Format .....	185
Table 444. PCBEEP OutAmpCap Command Verb Format .....	185
Table 445. PCBEEP OutAmpCap Command Response Format .....	185
Table 446. PCBEEP Gen Command Verb Format .....	186
Table 447. PCBEEP Gen Command Response Format .....	186
Table 448. CD WCap Command Verb Format .....	187
Table 449. CD WCap Command Response Format .....	187
Table 450. CD PinCap Command Verb Format .....	188
Table 451. CD PinCap Command Response Format .....	188
Table 452. CD PinWCntrl Command Verb Format .....	188
Table 453. CD PinWCntrl Command Response Format .....	189
Table 454. CD ConfigDefault Command Verb Format .....	189
Table 455. CD ConfigDefault Command Response Format .....	189
Table 456. ADATOut Cnvtr Command Verb Format .....	190
Table 457. ADATOut Cnvtr Command Response Format .....	190
Table 458. ADATOut WCap Command Verb Format .....	191
Table 459. ADATOut WCap Command Response Format .....	191
Table 460. ADATOut CnvtrID Command Verb Format .....	192
Table 461. ADATOut CnvtrID Command Response Format .....	192
Table 462. ADATOut DigCnvtr Command Verb Format .....	192
Table 463. ADATOut DigCnvtr Command Response Format .....	193

Table 464. ADATOut VCSR0 Command Verb Format .....	193
Table 465. ADATOut VCSR0 Command Response Format .....	193
Table 466. VolumeKnob WCap Command Verb Format .....	194
Table 467. VolumeKnob WCap Command Response Format .....	195
Table 468. VolumeKnob VolKnobCap Command Verb Format .....	195
Table 469. VolumeKnob VolKnobCap Command Response Format .....	195
Table 470. VolumeKnob ConLst Command Verb Format .....	195
Table 471. VolumeKnob ConLst Command Response Format .....	195
Table 472. VolumeKnob ConLstEntry0 Command Verb Format .....	196
Table 473. VolumeKnob ConLstEntry0 Command Response Format .....	196
Table 474. VolumeKnob ConLstEntry4 Command Verb Format .....	196
Table 475. VolumeKnob ConLstEntry4 Command Response Format .....	196
Table 476. VolumeKnob UnsolResp Command Verb Format .....	197
Table 477. VolumeKnob UnsolResp Command Response Format .....	197
Table 478. VolumeKnob Cntrl Command Verb Format .....	197
Table 479. VolumeKnob Cntrl Command Response Format .....	198
Table 480. VolumeKnob VCSR0 Command Verb Format .....	198
Table 481. VolumeKnob VCSR0 Command Response Format .....	198
Table 482. InPort0Vol WCap Command Verb Format .....	198
Table 483. InPort0Vol WCap Command Response Format .....	199
Table 484. InPort0Vol ConLst Command Verb Format .....	199
Table 485. InPort0Vol ConLst Command Response Format .....	200
Table 486. InPort0Vol InAmpRight Command Verb Format .....	200
Table 487. InPort0Vol InAmpRight Command Response Format .....	200
Table 488. InPort0Vol InAmpLeft Command Verb Format .....	200
Table 489. InPort0Vol InAmpLeft Command Response Format .....	200
Table 490. InPort0Vol ConLstEntry Command Verb Format .....	201
Table 491. InPort0Vol ConLstEntry Command Response Format .....	201
Table 492. InPort1Vol WCap Command Verb Format .....	201
Table 493. InPort1Vol WCap Command Response Format .....	201
Table 494. InPort1Vol ConLst Command Verb Format .....	202
Table 495. InPort1Vol ConLst Command Response Format .....	202
Table 496. InPort1Vol InAmpRight Command Verb Format .....	203
Table 497. InPort1Vol InAmpRight Command Response Format .....	203
Table 498. InPort1Vol InAmpLeft Command Verb Format .....	203
Table 499. InPort1Vol InAmpLeft Command Response Format .....	203
Table 500. InPort1Vol ConLstEntry Command Verb Format .....	203
Table 501. InPort1Vol ConLstEntry Command Response Format .....	204
Table 502. InPort2Vol WCap Command Verb Format .....	204
Table 503. InPort2Vol WCap Command Response Format .....	204
Table 504. InPort2Vol ConLst Command Verb Format .....	205
Table 505. InPort2Vol ConLst Command Response Format .....	205
Table 506. InPort2Vol InAmpRight Command Verb Format .....	205
Table 507. InPort2Vol InAmpRight Command Response Format .....	206
Table 508. InPort2Vol InAmpLeft Command Verb Format .....	206
Table 509. InPort2Vol InAmpLeft Command Response Format .....	206
Table 510. InPort2Vol ConLstEntry Command Verb Format .....	206
Table 511. InPort2Vol ConLstEntry Command Response Format .....	206
Table 512. ADC0Mux WCap Command Verb Format .....	207
Table 513. ADC0Mux WCap Command Response Format .....	207
Table 514. ADC0Mux ConLst Command Verb Format .....	208
Table 515. ADC0Mux ConLst Command Response Format .....	208
Table 516. ADC0Mux ConSelectCtrl Command Verb Format .....	208
Table 517. ADC0Mux ConSelectCtrl Command Response Format .....	208
Table 518. ADC0Mux ConLstEntry Command Verb Format .....	208

Table 519. ADC0Mux ConLstEntry Command Response Format .....	209
Table 520. ADC0Mux LR Command Verb Format .....	209
Table 521. ADC0Mux LR Command Response Format .....	209
Table 522. ADC0Mux OutAmpCap Command Verb Format .....	209
Table 523. ADC0Mux OutAmpCap Command Response Format .....	210
Table 524. ADC0Mux OutAmpRight Command Verb Format .....	210
Table 525. ADC0Mux OutAmpRight Command Response Format .....	210
Table 526. ADC0Mux OutAmpLeft Command Verb Format .....	210
Table 527. ADC0Mux OutAmpLeft Command Response Format .....	211
Table 528. ADC1Mux WCap Command Verb Format .....	211
Table 529. ADC1Mux WCap Command Response Format .....	211
Table 530. ADC1Mux ConLst Command Verb Format .....	212
Table 531. ADC1Mux ConLst Command Response Format .....	212
Table 532. ADC1Mux ConSelectCtrl Command Verb Format .....	212
Table 533. ADC1Mux ConSelectCtrl Command Response Format .....	213
Table 534. ADC1Mux ConLstEntry Command Verb Format .....	213
Table 535. ADC1Mux ConLstEntry Command Response Format .....	213
Table 536. ADC1Mux LR Command Verb Format .....	213
Table 537. ADC1Mux LR Command Response Format .....	213
Table 538. ADC1Mux OutAmpCap Command Verb Format .....	214
Table 539. ADC1Mux OutAmpCap Command Response Format .....	214
Table 540. ADC1Mux OutAmpRight Command Verb Format .....	214
Table 541. ADC1Mux OutAmpRight Command Response Format .....	215
Table 542. ADC1Mux OutAmpLeft Command Verb Format .....	215
Table 543. ADC1Mux OutAmpLeft Command Response Format .....	215
Table 544. ADC2Mux WCap Command Verb Format .....	215
Table 545. ADC2Mux WCap Command Response Format .....	215
Table 546. ADC2Mux ConLst Command Verb Format .....	216
Table 547. ADC2Mux ConLst Command Response Format .....	216
Table 548. ADC2Mux ConSelectCtrl Command Verb Format .....	217
Table 549. ADC2Mux ConSelectCtrl Command Response Format .....	217
Table 550. ADC2Mux ConLstEntry Command Verb Format .....	217
Table 551. ADC2Mux ConLstEntry Command Response Format .....	217
Table 552. ADC2Mux LR Command Verb Format .....	218
Table 553. ADC2Mux LR Command Response Format .....	218
Table 554. ADC2Mux OutAmpCap Command Verb Format .....	218
Table 555. ADC2Mux OutAmpCap Command Response Format .....	218
Table 556. ADC2Mux OutAmpRight Command Verb Format .....	219
Table 557. ADC2Mux OutAmpRight Command Response Format .....	219
Table 558. ADC2Mux OutAmpLeft Command Verb Format .....	219
Table 559. ADC2Mux OutAmpLeft Command Response Format .....	219

## 1. DESCRIPTION

The STAC9271/74 are 10-channel audio CODECs compatible with the Intel High Definition (HD) Audio Interface (formerly known as "Azalia"). The STAC9271/74 CODECs provide high quality, HD Audio capability to notebook and cost sensitive desktop PC applications.

The STAC9271/74 incorporate IDT's proprietary technology to achieve a DAC SNR up to 105dB. The higher performance and quality of IDT's audio solutions brings consumer electronics level performance to the notebook, desktop and media center PC.

The STAC9271/74 provide stereo 24-bit, full duplex resolution, supporting sample rates up to 192 KHz by the DAC and ADC. The SPDIF In/Out support sample rates of 96 KHz, 48 KHz and 44.1 KHz plus SPDIF OUT supports 88.2 KHz. Additional sample rates are supported by the driver software.

The STAC9271/74 support all desired ten channel configurations, including switchable Headphone Out, and Universal Jacks™ functionality for jack detection and re-tasking. The SPDIF interface provides connectivity to Consumer Electronic equipment like Dolby Digital decoders, powered speakers, mini disk drives or a home entertainment systems. All analog I/O pairs support LINE\_IN, LINE\_OUT and MIC.

MIC inputs can be programmed with 0/10/20/30/40dB boost. For more advanced configurations, the STAC9271/74 have up to five General Purpose I/O (GPIO) pins. Also provides a single ended CD input for compatibility with DRM solutions and to support legacy OS issues.

STAC9271/74 integrates a headphone amplifiers on Ports A, B and D. The headphone amplifier is dedicated to these three outputs for increased flexibility, enhanced user experience, and reduced implementation costs.

The Universal Jack™ feature allows the CODECs to detect when audio devices are plugged in, and for the CODECs to be reconfigured to support these devices regardless of which port they are plugged into. SPDIF input sensing is also supported. The fully parametric IDT SoftEQ can be initiated/disabled upon headphone jack insertion/removal for protection of notebook speakers. Note: The Jack Detect circuit and component selection are critical for accurate detection of audio jacks on individual ports. Please see the reference design for circuit implementation details.

The STAC9271/74 can operate with a 3.3 V digital supply and a 5 V analog supply.

The STAC9271/74 are available in a 48-pin LQFP Environmental (ROHS) packages.

## 2. CHARACTERISTICS

### 2.1. Audio Fidelity

DAC SNR:	105dB	A-Weighted	5.0 V +/- 5%
ADC SNR:	90dB	A-Weighted	5.0 V +/- 5%

### 2.2. Electrical Specifications

#### 2.2.1. Absolute Maximum Ratings

Stresses above the ratings listed below can cause permanent damage to the STAC9271/9274. These ratings, which are standard values for IDT commercially rated parts, are stress ratings only. Functional operation of the device at these or any other conditions above those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods can affect product reliability. Electrical parameters are guaranteed only over the recommended operating temperature range.

Item	Pin	Maximum Rating
Analog maximum supply voltage	AVdd	6 Volts
Digital maximum supply voltage	DVdd	5.5 Volts
VREFOUT output current		5 mA
Voltage on any pin relative to ground		Vss - 0.3 V to Vdd + 0.3 V
Operating temperature		0°C to +70°C
Storage temperature		-55 °C to +125 °C
Soldering temperature		260 °C for 10 seconds * Soldering temperature information for all available packages begins on page 225.

#### 2.2.2. Recommended Operation Conditions

Parameter		Min.	Typ.	Max.	Units
Power Supply Voltage	Digital - 3.3 V	3.135	3.3	3.465	V
	Analog - 3.3 V	3.135	3.3	3.465	V
(Note: With Supply Override Enable Bit set to force 5 V operation.)	Analog - 4 V	3.8	4	4.2	V
	Analog - 4.5 V	4.275	4.5	4.725	V
	Analog - 5 V	4.75	5	5.25	V
Ambient Operating Temperature		0		+70	°C
Case Temperature	T <sub>case</sub> (48-LQFP)			+90	°C

**ESD:** The STAC9271/9274 is an ESD (electrostatic discharge) sensitive device. The human body and test equipment can accumulate and discharge electrostatic charges up to 4000 Volts without detection. Even though the STAC9271/9274 implements internal ESD protection circuitry, proper ESD precautions should be followed to avoid damaging the functionality or performance.

### 2.3. STAC9271/74 5 V, 4.5 V, 4.0 V and 3.3 V Analog Performance Characteristics

( $T_{\text{ambient}} = 25^{\circ}\text{C}$ , AVdd = Supply  $\pm 5\%$ , DVdd = 3.3 V  $\pm 5\%$ , AVss=DVss=0 V; 1 kHz input sine wave; Sample Frequency = 48 kHz; 0 dB = 1 VRMS, 10 K $\Omega$ /50 pF load, Testbench Characterization BW: 20 Hz – 20 kHz, 0 dB settings on all gain stages)

Parameter	Conditions	AVdd	Min	Typ	Max	Unit
<b>Digital to Analog Converters</b>						
Resolution		All		24		Bits
SNR - DAC to All Line-Out Ports (Note 4)	Analog Mixer Disabled, PCM data	5 V 4.5 V 4.0 V 3.3 V		105 101 100 98		dB
THD+N - DAC to All Line-Out Ports (Note 3)	Analog Mixer Disabled, -3dB Signal, PCM data	5 V 4.5 V 4.0 V 3.3 V		90 88 86 84		dB
SNR - DAC to All Line-Out Ports (Note 4)	Analog Mixer Enabled, PCM data	5 V 4.5 V 4.0 V 3.3 V		90 88 87 85		dB
THD+N - DAC to All Line-Out Ports (Note 3)	Analog Mixer Enabled, -3dB Signal, PCM data	5 V 4.5 V 4.0 V 3.3 V		80 78 77 75		dB
Dynamic Range: DAC to All Line Out Ports (Note2)	-60dB Signal Level	5 V 4.5 V 4.0 V 3.3 V	-	95 93 92 90	-	dB
SNR - DAC to All Headphone Ports (Note 4)	Analog Mixer Disabled, 10 K $\Omega$ load, PCM data	5 V 4.5 V 4.0 V 3.3 V		105 101 100 98		dB
THD+N - DAC to All Headphone Ports (Note 3)	Analog Mixer Disabled, -3dB Signal, 10 K $\Omega$ load, PCM data	5 V 4.5 V 4.0 V 3.3 V		85 83 82 80		dB
SNR - DAC to All Headphone Ports with 2 Headphone Outputs Operating (Note 4)	Analog Mixer Disabled, 32 $\Omega$ load, PCM data	5 V 4.5 V 4.0 V 3.3 V		100 98 97 95		dB
THD+N - DAC to All Headphone Ports with 2 Headphone Outputs Operating (Note 3)	Analog Mixer Disabled, -3dB Signal, 32 $\Omega$ load, PCM data	5 V 4.5 V 4.0 V 3.3 V		82 80 79 77		dB
SNR - DAC to All Headphone Ports (Note 4)	Analog Mixer Disabled, 32 $\Omega$ load, PCM data	5 V 4.5 V 4.0 V 3.3 V		100 98 97 95		dB

Parameter	Conditions	AVdd	Min	Typ	Max	Unit
THD+N - DAC to All Headphone Ports (Note 3)	Analog Mixer Disabled, -3dB Signal, 32 Ω load, PCM data	5 V 4.5 V 4.0 V 3.3 V		85 83 82 80		dB
SNR - DAC to All Headphone Ports (Note 4)	Analog Mixer Enabled, 10 kΩ load, PCM data	5 V 4.5 V 4.0 V 3.3 V		90 88 87 85		dB
THD+N - DAC to All Headphone Ports (Note 3)	Analog Mixer Enabled, -3dB Signal, 10 kΩ load, PCM data	5 V 4.5 V 4.0 V 3.3 V		79 77 76 74		dB
SNR - DAC to All Headphone Ports (Note 4)	Analog Mixer Enabled, 32 Ω load, PCM data	5 V 4.5 V 4.0 V 3.3 V		87 85 84 82		dB
THD+N - DAC to All Headphone Ports (Note 3)	Analog Mixer Enabled, -3dB Signal, 32 Ω load, PCM data	5 V 4.5 V 4.0 V 3.3 V		74 72 71 69		dB
Any Analog Input to DAC Crosstalk	10 KHz Signal Frequency	All	-	-85	-	dB
Any Analog Input to DAC Crosstalk	1 KHz Signal Frequency	All	-	-80	-	dB
Gain Error	Analog Mixer Disabled	All			0.5	dB
Interchannel Gain Mismatch	Analog Mixer Disabled	All			0.5	dB
D/A Digital Filter Pass Band (Note 5)		All	20	-	19,200	Hz
D/A Digital Filter Transition Band		All	19,200	-	28,800	Hz
D/A Digital Filter Stop Band		All	28,800	-	-	Hz
D/A Digital Filter Stop Band Rejcn (Note 6)		All	-100	-	-	dB
D/A Out-of-Band Rejection (Note 7)		All	-55	-	-	dB
Group Delay (48 KHz sample rate)		All	-	-	1	ms
Attenuation, Gain Step Size DIGITAL		All	-	0.75	-	dB
Gain Drift		All	-	100	-	ppm/°C
DAC Offset Voltage		All	-	100	20	mV
Deviation from Linear Phase		All	-	1	10	deg.
<b>Analog Outputs</b>						
Full Scale All Line-Outs	DAC PCM Data	5 V 4.5 V 4.0 V 3.3 V	1.00 1.00 1.00 0.70	-	-	Vrms
Full Scale All Line-Outs	DAC PCM Data	All	2.83	-	-	Vp-p
All Headphone Capable Outputs	32 Ω load	All	31	50	-	mW peak
<b>Analog inputs</b>						

Parameter	Conditions	AVdd	Min	Typ	Max	Unit
Full Scale Input Voltage	0dB Boost @ 4.75 V	All	1.00	-	-	Vrms
All Analog Inputs with boost	10dB Boost	All	0.31	-	-	Vrms
All Analog Inputs with boost	20dB Boost	All	0.10	-	-	Vrms
All Analog Inputs with boost	30dB Boost	All	0.03	-	-	Vrms
All Analog Inputs with boost	40dB Boost	All	0.01	-	-	Vrms
Input Impedance		All	-	50	-	kΩ
Input Capacitance		All	-	15	-	pF
<b>Analog Mixer</b>						
SNR - CD to Ports A,B, & D Line-Out (Note 4)		All		90		dB
THD+N - CD to Ports A,B, & D Line-Out (Note 3)	-3dB Input	All		70		dB
SNR - All Line-In to A,B, & D Line-Out (Note 4)		All		90		dB
THD+N - All Line-In to A,B, & D Line-Out (Note 3)	-3dB Input	All		70		dB
SNR - Analog PC Beep to Ports A,B, & D Line-Out (Note 4)		All		85		dB
THD+N - Analog PC Beep to Ports A,B, & D Line-Out (Note 3)	-3dB Input	All		70		dB
<b>Analog to Digital Converter</b>						
Resolution		All		24		Bits
Dynamic Range, All Analog Inputs to A/D (Note 1)	High Pass Filer Enabled, 1Vrms Input, No boost	All	88	90		dB
SNR All Analog Inputs to A/D (Note 4)	High Pass Filter enabled	All	88	90		dB
THD+N All Analog Inputs to A/D (Note 3)	High Pass Filter enabled, -3dBV input Level	All		85		dB
Analog Frequency Response (Note 2)		All	10	-	30,000	Hz
A/D Digital Filter Pass Band (Note 5)		All	20	-	19,200	Hz
A/D Digital Filter Transition Band		All	19,200	-	28,800	Hz
A/D Digital Filter Stop Band		All	28,800	-	-	Hz
A/D Digital Filter Stop Band Rejection (Note 6)		All	-100	-	-	dB
Group Delay (48 KHz sample rate)		All	-	-	1	ms
Any Analog Input to ADC Crosstalk	10 KHz Signal Frequency	All	-	-85	-	dB
Any Analog Input to ADC Crosstalk	1 KHz Signal Frequency	All	-	-80	-	dB
Spurious Tone Rejection		All	-	-100	-	dB
Attenuation, Gain Step Size ANALOG		All	-	1.5	-	dB
Interchannel Gain Mismatch ADC		All	-	-	0.5	dB
Noise Floor when 40dB Mic Boost Enabled		All			0.01	mV
40dB Mic Boost Enabled SNR	5 mV Input	All		60		dB

Parameter	Conditions	AVdd	Min	Typ	Max	Unit
40dB Mic Boost Enabled THD+N	5 mV Input	All		55		dB
<b>Power Supply</b>						
Power Supply Rejection Ratio	1 KHz	All	-	-70	-	dB
Power Supply Rejection Ratio	20 KHz	All	-	-40	-	dB
D0 Didd	3.3 V			75	90	mA
D0 Aidd	5.0 V, 4.5 V, & 4.0 V, 3.3 V			85		mA
D1 Didd	3.3 V			75	90	mA
D1 Aidd	5.0 V, 4.5 V, & 4.0 V, 3.3 V			85		mA
D2 Didd	3.3 V			23	30	mA
D2 Aidd	5.0 V, 4.5 V, & 4.0 V, 3.3 V			58		mA
D3 Didd	3.3 V			23	30	mA
D3 Aidd	5.0 V, 4.5 V, & 4.0 V, 3.3 V			37		mA
One Stereo ADC Didd	3.3 V			8	10	mA
One Stereo ADC Aidd	5.0 V, 4.5 V, & 4.0 V, 3.3 V			10		mA
One Stereo DAC Didd	3.3 V			3	5	mA
One Stereo DAC Aidd	5.0 V, 4.5 V, & 4.0 V, 3.3 V			2		mA
<b>CD Input</b>						
CD Common Mode Rejection (CMR)		All	50	55		dB
<b>Voltage Reference Outputs</b>						
VREFout (Note 8)		All	-	0.5 X AVdd	-	V
VREFILT (VAG)		All		0.45X AVdd		V
<b>Phased Locked Loop</b>						
PLL lock time		All		96	200	μsec
PLL (or Azalia Bit CLK) 24 MHz clock jitter		All		150	500	psec

1. Ratio of Full Scale signal to noise output with -60dB signal, measured "A weighted" over a 20 Hz to a 20 KHz bandwidth.
2.  $\pm 3$ dB limits for Line Output and 0dB gain, at -20dBV
3. Amplitude of THD+N, measured with A-weighting filter, over 20 Hz to 20 KHz bandwidth.
4. Ratio of Full Scale signal to idle channel noise output is measured "A weighted" over a 20 Hz to a 20 KHz bandwidth. (AES17-1991 Idle Channel Noise or EIAJ CP-307 Signal-to-noise Ratio.)
5. Peak-to-Peak Ripple over Passband meets  $\pm 0.25$ dB limits, 48 KHz Sample Frequency.
6. Stop Band rejection determines filter requirements. Out-of-Band rejection determines audible noise.
7. The integrated Out-of-Band noise generated by the DAC process, during normal PCM audio playback, over a bandwidth 28.8 KHz to 100 KHz, with respect to a 1 Vrms DAC output.
8. Can be set to 0.5 or 0.8 AVdd.