imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



100 Mbps Plastic Fiber Optic IR LED



11/29/10



APPLICATIONS

- ► Low-Cost Digital Data Links
- ► Optical Sensors
- ► Audio Systems
- ► Medical Instruments
- ► Automotive Electronics
- ► Robotics Communications
- ► Local Area Networks (LANs)
- ► Wavelength Multiplexing
- ► Electronic Games

DESCRIPTION

The IF-E91D is a high-optical-output, high-speed, infrared LED housed in a "connector-less" style plastic fiber optic package. High performance at economical cost is provided by the IF-E91D in a variety of applications. The device package features an internal micro-lens and a precision-molded PBT housing to ensure efficient optical coupling with standard 1000 µm core plastic fiber cable.

APPLICATION HIGHLIGHTS

The high output and fast transition times of the IF-E91D make it suitable for low-cost digital data links. Using standard 1000 µm core plastic fiber, the IF-E91D LED is ideally suited for distances up to 10 meters at data rates of 100 Mbps. The drive circuit design is simpler than required for laser diodes, making the IF-E91D a good low-cost device in a variety of short distance analog and digital applications.

FEATURES

- ◆ High Infrared Optical Power
- ◆ Fast Rise and Fall Times
- Economically Priced
- $\blacklozenge\,$ Mates with Standard 1000 μm Core Jacketed Plastic Fiber Cable
- ◆ Internal Micro-Lens for Maximum Coupling
- ◆ Inexpensive Plastic Connector Housing
- ◆ Connector-Less Fiber Termination
- Light-Tight Housing Provides Interference-Free Transmission

MAXIMUM RATINGS

 $(T_A = 25^{\circ}C)$

Operating and Storage Temperature Range (T _{OP} , T _{STG})40° to 85°C
Junction Temperature (T_J) 85°C
$\begin{array}{l} \mbox{Soldering Temperature} \\ (2 \mbox{ mm from case bottom}) \\ (T_S) \mbox{t} \leq 5 \mbox{s} $
Reverse Voltage (V_R)3 V
Power Dissipation (P_{TOT}) T _A =25°C60 mW
De-rate Above 25°C1.33 mW/°C
Forward Current, DC (I_F) 60 mA
Surge Current (I _{FSM}) t \leq 10 µsec duty cycle <5% 1 A

Characteristics ($T_A=25^{\circ}C$)

Parameter	Symbol	Min.	Тур.	Max.	Unit
Peak Wavelength	λ_{PEAK}	865	870	875	nm
Spectral Bandwidth (50% of I _{MAX})	Δλ	-	30	-	nm
Output Power Coupled into Plastic Fiber (1 mm core diameter). Distance Lens to Fiber ≤0.1 mm, 10 cm SH4001 polished fiber I _F =20 mA	Φ_{\min}	200 7.0	300 -5.2	400 -4.0	μW dBm
Switching Times (10% to 90% and 90% to 10%) (Figure 3)	t _r , t _f	-	3.0	_	ns
Capacitance (F=1 MHz)	C ₀	-	120	-	pF
Forward Voltage (I _F =20 mA)	V _f	-	1.85	2.05	V
Temperature Coefficient, λ_{PEAK}	TC_{λ}		0.3		nm/K

IF-E91D

100 Mbps Plastic Fiber Optic IR LED



FIGURE 1. Normalized power launched versus forward current.



FIGURE 2. Typical spectral output vs. wavelength.





FIBER TERMINATION INSTRUCTIONS

- 1. Cut off the ends of the optical fiber with a singleedge razor blade or sharp knife. Try to obtain a precise 90-degree angle (square).
- 2. Insert the fiber through the locking nut and into the connector until the core tip seats against the internal micro-lens.
- 3. Screw the connector locking nut down to a snug fit, locking the fiber in place.



FIGURE 4. Case outline.