



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# SC2002ALM-HL

## Dual Trip Amplifier



The SC2002ALM-HL trip amplifier can accept a wide range of user configurable inputs including 4-20mA, 0-20mA, 0-5V and 0-10V. The unit can have up to two relay outputs and each can operate as a high or a low trip; alternatively latching operation using both trip points can be configured. The relay outputs are single pole change-over relays with mains voltage rating. Each trip can be configured so that the alarm condition can be above or below setpoint. The relays can be energised or de-energised in the alarm condition, satisfying fail-safe and non-fail-safe applications. In addition the alarm LEDs can be selected to light when the relay is either on or off. All these options are user-configurable using internal DIP switches. This minimises the number of spare units required. The input stage is fully isolated and the high level input current or voltage and range may be configured. Separate products are available for thermocouple and RTD inputs.

- **Wide Range of User Configurable Inputs**
- **2 Setpoints with Configurable Trip Action & Fail-safe mode**
- **Isolated Input Stage**
- **Setpoints Available as 0-10V, (0-100%) on terminals 9 & 12**
- **D.C or A.C. Power Supply Options, See 4002-ALM for Mains Version**

### Inputs

#### SC-2002ALM-HL Standard Ranges

0-20mA, 4-20mA, 0-10mA into 12 $\Omega$ /15 $\Omega$ /24 $\Omega$   
 0-5V, 0-10V into 1M $\Omega$

Min and Max Full Scale Ranges available to order:

DC Current 0 to 1mA 0 to 5A

DC Voltage 0 to 100mV 0 to 300V

Note: For input voltages greater than 60Vdc a Divider unit must be specified.

### Outputs

Mains Rated Relays - 3A resistive at 240V ac

### Technical Specifications

Parameter	Min	Typ	Max	Comments
Supply Voltage		24V		
Supply Current (mA)			45	24Vdc supply, both relays energised
Volt Drop (mA input)		0.3	0.35	At 20mA Input
Input Impedance (Volt)	100k $\Omega$	1M $\Omega$	10M $\Omega$	Dependant on range (typ=10V)
Input Impedance (mA)	0.02 $\Omega$	15 $\Omega$	5k $\Omega$	Dependant on range (typ=4-20mA)
Trip Point Accuracy			0.25%	
Trip Point Drift			$\pm 100$ ppm/ $^{\circ}$ C	
Temp Coefficient			$\pm 100$ ppm/ $^{\circ}$ C	
Hysteresis		1% span		
Time Constant (10-90%)		10ms		
Operating Ambient	0 $^{\circ}$ C		55 $^{\circ}$ C	
Relative Humidity	0%		90%	
Isolation Voltage <sup>see note</sup>	1kV			
Surge Voltage	2.5kV for 50 $\mu$ S		Transient of 10kV/ $\mu$ S	

### Notes

Setpoints are adjusted by 20 turn potentiometers on the front panel.

Setpoints can be checked by measuring the 0-10V (0-100%) voltage on terminals 9 & 12

H/H,H/L, L/H, LL, fail-safe, non-fail safe and LED options are user selectable using internal links.


Hysteresis is set at 1.0% but other values are possible, please specify if required.

### Installation Data

Mounting	DIN Rail TS35
Orientation	Any
Connections	Screw Clamp with pressure plate
Conductor Size	0.5-4.0mm
Insulation Stripping	12mm
Weight	Approx 120g

### Ordering Information

Part No.: SC2002ALM-HL



### Connection Details

10. Power input -ve	
11. Power input +ve	
7. Process Input -ve and Setpoint common	
8. Process input +ve	
9. Setpoint 1 (0-10V = 0-100%)	
12. Setpoint 2 (0-10V = 0-100%)	
1. Relay 1 Common	4. Relay 2 Common
2. Relay 1 N/C	5. Relay 2 N/C
3. Relay 1 N/O	6. Relay 2 N/O

Cynergy3 Components Ltd.  
 7 Cobham Road  
 Ferndown Industrial Estate  
 Wimborne, Dorset BH21 7PE  
 Telephone +44 (0) 1202 897969  
 Email:sales@cynergy3.com

ISO9001CERTIFIED

SC2002ALM-HL 2017

© 2017 Cynergy3 Components, All Rights Reserved. Specifications are subject to change without prior notice. Cynergy3 Components and the Cynergy3 Components logo are trademarks of Cynergy3 Components Limited.

www.cynergy3.com



Made in the UK