



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Gravity: VL53L0X ToF Laser Range Finder

SKU:SEN0245

The VL53L0X range finder is a high-precision distance finder that based on new Time-of-Flight (ToF) principle. VL53L0X provides accurate distance measurement whatever the target reflectance unlike traditional technology. It can measure absolute distances up to 2m.

DFRobot has introduced VL53L0X into Gravity Series. It provides Gravity-I2C interface, plug and play, supports 3.3V~5V power supply, and is compatible with more microcontrollers, and adapt to more application scenarios than others.


The VL53L0X integrates a leading-edge SPAD array (Single Photon Avalanche Diodes) and embeds ST's second generation FlightSense™ patented technology. Its accuracy is $\pm 3\%$, response time is less than 30ms, power consumption is only 20mW in normal operation mode, stand-by power consumption is 5uA.

The VL53L0X's 940nm VCSEL emitter (vertical cavity surface emitting laser) is totally invisible to the human eye, coupled with internal physical infrared filters, it enables longer ranging distance, higher immunity to ambient light and better robustness to cover-glass optical cross-talk.

Specification

- Power supply: 3.3-5V DC
- Operating Voltage: 2.8V
- Infrared emitter: 940nm
- Range: 30-2000mm
- FOV: 25°
- Ranging Accuracy: $\pm 3\%$
- Sampling Time: $\leq 30\text{ms}$
- Operating Temperature: $-20-70\text{ }^{\circ}\text{C}$
- Interface Type: Gravity-I2C
- Product Size: 0.79*0.87 in

Pin Description



Pin Description

Label	Name	Description
1 green line	D	DATA
2 blue line	C	CLK
3 black line	-	GND
4 red line	+	VCC

GPIO1: interrupt output pin to indicate if the data is ready


XSHUT: Close the pin of the sensor, pulled high by default, sensor enters off mode when pin is pulled low

Tutorial

Requirements

- **Hardware**
 - Arduino UNO control board x1.
 - VL53L0X Distance detection Sensor module
-
- **Software**
 - Arduino IDE, [Click to Download Arduino IDE from Arduino®](#)

Connection Diagram



Connection diagram

Sample Code

```
/*!
 * @file DFRobot_VL53L0X.ino
 * @brief DFRobot's Laser rangefinder library
 * @n The example shows the usage of VL53L0X in a simple way.
 *
 * @copyright [DFRobot] (http://www.dfrobot.com), 2016
 * @copyright GNU Lesser General Public License
 *
 * @author [LiXin]
 * @version V1.0
 * @date 2017-8-21
 * @https://github.com/DFRobot/DFRobot_VL53L0X
 timer*/
#include "Arduino.h"
#include "Wire.h"
#include "DFRobot_VL53L0X.h"

/*****Keywords instruction*****/
//Continuous--->Continuous measurement model
//Single----->Single measurement mode
//High----->Accuracy of 0.25 mm
//Low----->Accuracy of 1 mm
/*****Function instruction*****/
//setMode(ModeState mode, PrecisionState precision)
  /*This function is used to set the VL53L0X mode
  /*mode: Set measurement mode      Continuous or Single
  /*precision: Set the precision    High or Low
//void start()
  /*This function is used to enabled VL53L0X
//float getDistance()
  /*This function is used to get the distance
//uint16_t getAmbientCount()
```

```

    /*This function is used to get the ambient count
//uint16_t getSignalCount()
    /*This function is used to get the signal count
//uint8_t getStatus();
    /*This function is used to get the status
//void stop()
    /*This function is used to stop measuring


DFRobotVL53L0X sensor;

void setup() {
    //initialize serial communication at 115200 bits per second:
    Serial.begin(115200);
    //join i2c bus (address optional for master)
    Wire.begin();
    //Set I2C sub-device address
    sensor.begin(0x50);
    //Set to Back-to-back mode and high precision mode
    sensor.setMode(Continuous,High);
    //Laser rangefinder begins to work
    sensor.start();
}

void loop()
{
    //Get the distance
    Serial.print("Distance: ");Serial.println(sensor.getDistance());
    //The delay is added to demonstrate the effect, and if you do not add the d
    elay,
    //it will not affect the measurement accuracy
    delay(500);
}

```

Expected Results



Result

Measured Results

actual distance	measuring distance (erro)	actual distance	measuring distance (erro)	actual distance	measuring distance (erro)	actual distance	measuring distance (erro)
500	490(-10)	300	304.75(+4.75)	138	138.5(+0.5)	100	102(+2)
	491.5(-8.5)		298.75(-1.25)		131.5(-6.5)		109(+9)
	498(-2)		299.5(-0.5)		132.25(-5.75)		105.5(+5.5)
	496.5(-3.5)		302(+2)		131.25(-6.75)		104.75(+4.75)
	499.75(-0.25)		297.5(-2.5)		136(-2)		99.5(-0.5)
	503.75(+3.75)		299.5(-0.5)		138.5(+0.5)		102.5(+2.5)

API List

```
#include <DFRobot_EINK.h>

DFRobotVL53L0X sensor //Create an object

/*
 * @Function: set range mode.
 * @Parameter 1 mode: ranging mode
 *     Single: Single range
 *     Continuous: Continuous range
 * @parameter 2 precision: Measuring precision
 *     High:high precision(0.25mm)
 *     Low:standard accuracy(1mm)
 */
void setMode(uint8_t mode, uint8_t precision);

/*
 * @function: start measuring
 */
void start();

/*
 * @function: stop measuring
 */
void stop();

/*
 * @function: acquire distance
 */
uint16_t getDistance();
```



```

/*
 * @function: acquire environmental variables
 */
uint16_t getAmbientCount();


/*
 * @function: acquire semaphore
 */
uint16_t getSignalCount();

```

Compatibility Test

MCU	Pass the test	Failed the test	No test	Note
FireBeetle-Board328P	√			
FireBeetle-ESP32	√			
FireBeetle-ESP8266	√			
Leonardo	√			

Dimension



More Documents

- [schematic diagram](#)
- [VL53L0X Datasheet](#)