



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





SM-10 Sound Meter

The Amprobe SM-10 Sound Level Meter is designed to meet the measurement requirements of Safety Engineers, Health, Industrial safety offices and Quality Control in various environments. It offers two types of measurements: A and C weighting.

The A weighting is for general noise sound level and the C weighting is for measuring sound level of acoustic material control in various environments (ie 94dB 1 kHz etc...). The SM-10 conforms to the IEC651 Type 2, ANSI S1.4 Type 2, and JISC1502 requirements for Sound Level Meters. Which means the SM-10 uses two different weighting filters required by the IEC 651 and ANSI S1.4 Type 2: the A-Weighting and the C-Weighting audio filtering.

No hassle warranty

No waiting.

No shipping charges.



Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)

- Designed to meet the measurement requirements of Safety Engineers, Health, Industrial safety offices and quality control in various environments.
- A and C weightings for checking compliance with safety regulations as well as acoustic analysis
- Measuring ranges:
A Weighting 30 ~130dB
C Weighting 35~130dB
- Frequency range: 31.5Hz~8KHz
- Display with 0.1dB steps on a 4 digits LCD
- Slow (1 sec) and fast (125ms) response settings to check peak and average noise levels
- MAX/MIN recording
- Data Hold to freeze reading on digital display
- Accessories supplied: Carrying case, windscreen, user manual and 9V Battery
- CE, designed to meet IEC651 Type2, ANSI S1.4 Type2

SM-10 Sound Meter**Specifications****General Specifications**

Display	4 digits LCD
Microphone	1/2 inch Electret condenser microphone
Low Battery Indication	Replace battery when LCD displays "E3"
Power Supply	9V NEDA 1604, IEC 6F22, JIS 006P battery
Power Life	Approx. 50 hrs (alkaline Battery)
Auto Power Off	Approx. 5 min
Environment	Indoor operation, < 2000 m

Temperature / Humidity

Operation	5 °C to 40 °C (41°F to 104°F); < 80% RH
Storage	-10 °C to 60 °C (14°F to 140°F); < 70 %RH
Dimension	200 x 55 x 38 mm (7.8 x 2.2 x 1.5 in)
Weight	233g. (0.5 lb.) Including battery

Electrical (Audio)

Standard applied	IEC 651 Type2, ANSI 1.4 Type 2
Dynamic range	50 dB
Resolution	0.1 dB, Display Update: 0.5 sec.
Time weighting	FAST(125mS), SLOW(1 sec)
Frequency range:	31.5 Hz to 8 kHz
Measuring level range	(Auto Range)
A Weighting:	30 to 130 dB
C Weighting:	35 to 130 dB
Accuracy	± 1.5 dB
Calibration cycle	1 year

CE-EMC

EN61326-1 This product complies with requirements of the following European Community Directives: 89/336/EEC (Electromagnetic Compatibility) and 73/23/EEC (Low Voltage) as amended by 93/68/EEC (CE Marking). However, electrical noise or intense electromagnetic fields in the vicinity of the equipment may disturb the measurement circuit. Measuring instruments will also respond to unwanted signals that may be present within the measurement circuit. Users should exercise care and take appropriate precautions to avoid misleading results when making measurements in the presence of electronic interference.

Amprobe® Test Tools
website: www.Amprobe.com
email: info@amprobe.com
Everett, WA 98203
Tel: 877-AMPROBE

Amprobe® Test Tools Europe
Amprobe Test Tools Europe
Beha-Amprobe GmbH
In den Engematten 14
79286 Glottertal, Germany
Tel.: +49 (0) 7684 8009 - 0

©2008 Amprobe Test Tools. All rights reserved.
7/2008 3358179 Rev A