

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: [info@chipsmall.com](mailto:info@chipsmall.com) Web: [www.chipsmall.com](http://www.chipsmall.com)

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China


# Super323™ SOT323 PNP SILICON POWER (SWITCHING) TRANSISTOR

ZUMT720

ISSUE 1 - SEPTEMBER 1998

## FEATURES

- \* **500mW POWER DISSIPATION**
- \* 1A Peak Pulse Current
- \* Excellent  $H_{FE}$  Characteristics Up To 1A (pulsed)
- \* Low Saturation Voltage
- \* Low Equivalent On Resistance;  $R_{CE(sat)}$



## APPLICATIONS

- \* Boost functions in DC-DC converters
- \* Motor driver functions

DEVICE TYPE	COMPLEMENT	PARTMARKING	$R_{CE(sat)}$
ZUMT720	ZUMT619	T73	240mΩ at 750mA

## ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	$V_{CBO}$	-40	V
Collector-Emitter Voltage	$V_{CEO}$	-40	V
Emitter-Base Voltage	$V_{EBO}$	-5	V
Peak Pulse Current**	$I_{CM}$	-1	A
<b>Continuous Collector Current</b>	$I_C$	<b>-0.75</b>	A
Base Current	$I_B$	-200	mA
<b>Power Dissipation at <math>T_{amb}=25^\circ C</math>*</b>	$P_{tot}$	<b>385 †</b> <b>500 ‡</b>	mW
Operating and Storage Temperature Range	$T_j-T_{stg}$	-55 to +150	°C

† Recommended  $P_{tot}$  calculated using FR4 measuring 10 x 8 x 0.6mm (still air).

‡ Maximum power dissipation is calculated assuming that the device is mounted on FR4 size 25x25x0.6mm and using comparable measurement methods adopted by other suppliers.

# ZUMT720

## ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ C$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-40			V	$I_C = -100\mu A$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-40			V	$I_C = -10mA^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5			V	$I_E = -100\mu A$
Collector Cut-Off Current	$I_{CBO}$			-10	nA	$V_{CB} = -35V$
Emitter Cut-Off Current	$I_{EBO}$			-10	nA	$V_{EB} = -4V$
Collector Emitter Cut-Off Current	$I_{CES}$			-10	nA	$V_{CES} = -35V$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		-50 -90 -140 -180	-65 -120 -200 -250	mV mV mV mV	$I_C = -0.1A, I_B = -10mA^*$ $I_C = -0.25A, I_B = -20mA^*$ $I_C = -0.5A, I_B = -50mA^*$ $I_C = -0.75A, I_B = -100mA^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		-1000	-1100	mV	$I_C = -0.75A, I_B = -100mA^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$		-890	-1100	mV	$I_C = -0.75A, V_{CE} = -2V^*$
Static Forward Current Transfer Ratio	$h_{FE}$	300 300 90 40 20	510 450 190 60 30			$I_C = -10mA, V_{CE} = -2V^*$ $I_C = -0.1A, V_{CE} = -2V^*$ $I_C = -0.5A, V_{CE} = -2V^*$ $I_C = -0.75A, V_{CE} = -2V^*$ $I_C = -1A, V_{CE} = -2V^*$
Transition Frequency	$f_T$		220		MHz	$I_C = -50mA, V_{CE} = -10V$ $f = 100MHz$
Output Capacitance	$C_{obo}$		8		pF	$V_{CB} = -10V, f = 1MHz$
Turn-On Time	$t_{(on)}$		75		ns	$V_{CC} = -10V, I_C = -0.75A$ $I_{B1} = I_{B2} = -100mA$
Turn-Off Time	$t_{(off)}$		315		ns	

\*Measured under pulsed conditions. Pulse width=300μs. Duty cycle ≤ 2%

**ZUMT720**

## TYPICAL CHARACTERISTICS

