



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Gyro-Stat[®] Bench Top Turntable



Figure 1. Desco 07604 Gyro-Stat[®] ESD Bench Top Turntable

Description

The Gyro-Stat[®] Bench Top Turntable allows an operator to rotate (bidirectional) heavy, large, or awkward assemblies on a bench top without manual handling of the product. The Gyro-Stat[®] Bench Top Turntable includes a pre-installed [Statfree T2™](#) dissipative dual layer rubber mat top. Three thumbscrew locks allow the turntable to be locked temporarily to prevent spinning when required.

Specifications

Base Material:	Stainless Steel
Profile:	5/8" High
Diameter:	18 3/4"
Load Rating:	220 pounds
Volume Resistance:	1 x 10 ⁷ to < 1 x 10 ⁹ ohms
Mat Top:	Statfree T2™ Dissipative Dual Layer Rubber
Mat Top Electricals:	Rtg: 1 x 10 ⁶ to < 1 x 10 ⁹ ohms per ANSI/ESD S4.1 and ESD TR53

Operation

1. Unpack the unit and check for any visible damage.
2. Ensure the turntable is sitting flat on the bench* and the bench is solid. Can also be used on floor.
3. During transit the conductive bearings may stick together. Make sure the turntable reaches room temperature and rotate the top disc a few times to separate the ball bearings and conductive grease.

Note: Gyro-Stat[®] is a registered trademark of Vodex Ltd
 *Gyro-Stat[®] turntable is Made in England. Statfree T2™ mats are made in the USA.

4. Place the product on the Gyro-Stat[®] bench top turntable making sure the weight is evenly distributed. The turntable should now be in working order. To ground the turntable, place it on a grounded bench or bench mat (< 1 x 10⁹ ohms Rtg). The path to ground may be verified with a [resistance meter](#).
5. To temporarily stop the spinning, turn one of the 3 lock screws a few turns just enough to stop the rotary movement. Do not over tighten screw(s). See Figure 2.

*The Gyro-Stat[®] Bench Top Turntable may also be used on a floor or other surface. In order to be grounded it must be on a surface that provides a path to ground.



Figure 2. Thumbscrew Locks



Figure 3. Locking the Turntable

Limited Warranty, Warranty Exclusions, Limit of Liability and RMA Request Instructions

See Desco's Warranty - <http://Desco.DescoIndustries.com/Warranty.aspx>