



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Wio LTE EU Version - 4G, Cat.1, GNSS, Espruino Compatible

SKU 102990923

Description

Wio Tracker (Wireless Input Output) is an open source gateway which enable faster IoT GPS solutions. It is Arduino and Grove compatible development boards that helps you track nearly any moving thing on the planet and then upload that data wirelessly. The Wio LTE is the LTE version of Wio Tracker, so now we've got 2 versions of Wio Tracker and the LTE (4G) version will make some differences.

There are three main updates comparing the Wio LTE to the 2G version. Firstly, from its name we know that the Wio LTE supports LTE (4G) communication which is much faster and popular than 2G. Secondly, the Wio LTE supports in total 4 different GNSS – GPS, Beidou, GLONSS and Galileo, the QZSS is also supported as bonus. With more GNSS support, positioning will be more accurate. Thirdly, the Wio LTE's MCU is upgraded to STM32, which is based on Cortex-M4, makes the Wio LTE 5 times faster than the 2G version. What's more, the flash and RAM have also been raised to 1Mbytes and 192+4k bytes.

Apart from the three main updates, the LTE version is almost the same as the 2G version. If your project is using the 2G version, it would be very easy to update to the LTE version because we have prepared transplantable and expansible AT command library. The Arduino and Grove compatibility allows for quicker development through numerous libraries and a supportive community. The GPS library which will be available with the board is not just limited to Arduino – it can function just as well if you chose to develop in C/C++. With the onboard 6 Grove connections, developers can create any combination of our 180+ sensors and actuators to build project and solve any problem. Simplifying the prototyping and development phase is our goal.

The Wio LTE is well suited for outdoor projects where the device can connect to the GPS satellites and provide a real-time location of the item it is attached to. The LTE provides a wide bandwidth which allows much faster interaction between the user and device. If you are going to build projects like a bicycle sharing service, tracking pets or livestock, locating a vehicle, or even keeping track of a child, the Wio LTE is the best solution.

Note:

This is the EU version of Wio LTE, and there are in total 4 different versions. Here is a table to show the main difference between different versions. For more detail information, please refer to this manual.

https://github.com/SeeedDocument/Bazaar_Attachment/raw/master/102990837/Quectel_EC21_Hardware_Design_V1.4.pdf

| Versions | LTE Bands | 3G Bands | GSM | GNSS |
|----------|-------------------------------|--------------------|-------------------|---|
| US | FDD: B2/B4/B12 | WCDMA: B2/B4/B5 | / | GPS/GLONASS/Beidou/Compass/Galileo/GZSS |
| EU | FDD: B1/B3/B5/B7/B8/B20 | WCDMA: B1/B5/B8 | 900/1800 | GPS/GLONASS/Beidou/Compass/Galileo/GZSS |
| AU | FDD: B1/B2/B3/B4/B5/B7/B8/B28 | WCDMA: B1/B2/B5/B8 | 850/900/1800/1900 | GPS/GLONASS/Beidou/Compass/Galileo/GZSS |
| JP | FDD: B1/B3/B8/B18/B19/B26 | / | / | / |

Technical Details

| | |
|---------|---------|
| Weight | G.W 18g |
| Battery | Exclude |

| Sub-System | Function | Detail |
|------------------------------------|--------------------------------------|---|
| Microcontroller | Processor | STM32F405RG, ARM Cortex-M4, CPU running up to 168MHZ |
| | Flash | 1MB |
| | RAM | 192+4KB |
| | Operating Voltage | 3.3V |
| | Low Power | Sleep, Stop, Standby modes |
| | DC Current per I/O Pin | 7 mA |
| LTE | LTE Cat.1 | FDD LTE: B1/B3/B5/B7/B8/B20 WCDMA: B1/B5/B8 GSM: 900/1800 |
| | | AT Command: 3GPP TS27.007 and enhanced AT Commands |
| | Data | LTE-FDD Max 10Mbps(DL) Max 5Mbps (UL) |
| | | Protocol: TCP/UDP/PPP/FTP/HTTP/SSL |
| | SMS | Peer to Peer Message, SMS broadcast, Text and PDU mode |
| Audio | Echo cancellation; Noise elimination | |
| GNSS | System | GPS/GLONASS/BeiDou/Galileo |
| | Precision | <2.5 m CEP |
| Peripheral | Grove | 2 x Grove Digital Port |
| | | 2 x Analog Port |
| | | 1 x UART |
| | | 1 x I2C |
| | Antenna | 2 x LTE Antenna |
| | | 1 x GPS Antenna |
| | Others | USB: Power supply and upload program |
| | | JST 1.0 connector for battery |
| | | 3.5mm Audio Jack |
| | | MCU Reset Button, EC21 Power Button |
| 1 x User RGB LED SK6812 | | |
| Nano SIM and TF card 2 in 1 socket | | |

Part List

| | |
|---|---|
| Wio LTE EU Version - 4G, Cat.1, GNSS, Espruino Compatible | 1 |
| LTE Antenna | 1 |
| GPS Antenna | 1 |

