



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Power Limiter

SKU: 109990003



(images/product/Power Limiter_01.jpg)

Description

The RF Explorer Power Limiter is a custom device designed from scratch to be the perfect protection against strong RF fields.

As you can see on this note (<http://www.rf-explorer.com/care>) all RF Explorer models have some power ranges for input signal beyond which can be damaged. For most models, the limit is on +5dBm, some others are ok up to +10dBm but only WSUB3G (as well as the RF SMA connector on the right side in a 3G Combo) is protected up to +30dBm.

The new RF Explorer Power Limiter will allow any RF Explorer model to be protected with external signals up to +30dBm (1 Watt), so you get the same level of protection as in the WSUB3G. Furthermore, the power limiter includes additional functionality inside that will otherwise require external devices increasing cost and size:

- **Power limiter:** protection up to +30dBm, for any frequency range between DC-3000Mhz
- **DC block:** You can connect any external DC source up to 16V with no risk of damaging your RF Explorer or interfering in your measurement.
- **Attenuator:** Includes an internal 6dB attenuator to help you extend the range of power signal measurements. 6dB attenuation means only $\frac{1}{4}$ of the input power is received by the unit. To compensate for this extra attenuation you should indicate OffsetDB:+006 in the ATTENUATOR MENU of your RF Explorer.

The Power Limiter is assembled in a rugged aluminum case and it is very compact when compared to other market offerings, not to mention it includes internal DC block and attenuator which makes it a really small device for what it offers. It is a recommended add-on to all users who may expose their unit to strong external fields.

Feature

- Robust, small and low weight custom aluminum case
- 3-in-1 device with Power Limiter, DC Block and Attenuator
- Easy to connect and disconnect when required
- Wide broadband frequency application
- Directional 1 Watt rating
- Suitable for all RF Explorer models, not required for WSUB3G.

Specification

- Frequency range: DC ~ 3.0 GHz
- DC block: +16V DC
- Input Power rating: 1 Watt (+30dBm)
- Output power max: +4 dBm.

- Attenuation: 6 dB
- Impedance (Nominal): 50Ω
- V.S.W.R (Max): 1.25 : 1
- Connector type: SMA male – female
- Connector: Brass / Gold plating
- Body: Aluminum

If you encounter any problems when using this product, please contact [rfexplorer\(at\)arocholl.com](mailto:rfexplorer@arocholl.com) (<mailto:rfexplorer@arocholl.com>) for the technical support.

Overview



(<http://www.seeedstudio.com/depot/Maker-Pro-t-1672.html?ref=pinfo>)

Designer: RF Explorer

RF Explorer[®]
Software Compatible

(<http://micro.arocholl.com/>)

Other Products From This Designer

(<http://www.seeedstudio.com/depot/RF-Explorer-m-22.html?ref=pinfo>)

Weight: 17 g



([depot/OPLopen-parts-library-catalog-c-136_138/?ref=side](http://www.seeedstudio.com/depot/OPLopen-parts-library-catalog-c-136_138/?ref=side))