

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com


Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







| TECHNICAL DATA SHEET | Rosenberger |
|----------------------------|--------------|
| Adaptor SMP jack - jack | 19K106-K00L5 |



All dimensions are in mm; tolerances acc. ISO 2768 m-H

| Interface | MIL CTD 240 |
|--------------|-------------|
| According to | MIL-STD-348 |
| Documents | |
| | N/A |

| Material and plating | | |
|----------------------|----------|-----------------------|
| Connector parts | Material | Plating |
| Center contact | CuBe | AuroDur®, gold plated |
| Outer contact | CuBe | AuroDur®, gold plated |
| Dielectric | PTFE | |

email: $\underline{info@rosenberger.de}$

TECHNICAL DATA SHEET

Rosenberger

Adaptor SMP jack - jack

19K106-K00L5

Electrical data

Impedance 50 Ω

Frequency DC to 26.5 GHz Return loss \geq 30 dB, DC to 4 GHz \geq 18 dB, 4 to 12 GHz

 \geq 14 dB, 12 to 18 GHz

Insertion loss $\leq 0.1 \text{ x} \sqrt{f(GHz)}$ dB, DC to 18 GHz

 $\begin{array}{lll} \text{Insulation resistance} & \geq 5 \text{ } G\Omega \\ \text{Center contact resistance} & \leq 6.0 \text{ } m\Omega \\ \text{Outer contact resistance} & \leq 2.0 \text{ } m\Omega \\ \text{Test voltage} & 500 \text{ } V \text{ } rms \\ \text{Working voltage} & 335 \text{ } V \text{ } rms \\ \text{Contact Current} & 1.2 \text{ } D\text{C max}. \end{array}$

Mechanical data

Mating cycles

if mating part is smooth bore ≥ 1000 if mating part is limited detent ≥ 500 if mating part is full detent ≥ 100 Center contact captivation $\geq 7 \text{ N}$

Engagement force

smooth bore
limited detent
full detent
68 N max.

Disengagement force

- smooth bore 2.2 N min.
- limited detent 9 N min.
- full detent 22 N min.

Environmental data

Temperature range -65°C to +155°C

Thermal shock MIL-STD-202, Method 107, Condition B Vibration MIL-STD-202, Method 204, Condition B Shock MIL-STD-202, Method 213, Condition A

Moisture resistance MIL-STD-202, Method 106

RoHS compliant

Tooling

N/A

Suitable cables

N/A

Weight

Weight 0.3 g/pce

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

| Draft | Date | Approved | Date | | Rev. | Engineering change number | Name | Date | |
|--|----------|-----------------|----------------------------------|--------------------|------|---------------------------|-----------|----------|---|
| A. König | 27/09/07 | J_Krautenbacher | 14.07.16 | | c00 | 15-1629 | I_Wallner | 14.07.16 | l |
| Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany | | | Te | el.: +49 8684 18-0 | | Page | | | |
| www.rosenberger.de | | en | nail: <u>info@rosenberger.de</u> | | 2/2 | | | | |