

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China








TECHNICAL DATA SHEET


ROSenberger

SMP STRAIGHT PLUG PCB
LIMITED DETENT

19S101-40ML5







All dimensions are in mm; tolerances acc. ISO 2768 m-H

Interface
According to

MIL-STD-348

**Documents** 

PCB layout

Tape & reel packaging

B 120 VG01.01M00

Material and plating

**Connector parts** 

Center contact Outer contact Dielectric Material

Brass Brass LCP **Plating** 

AuroDur, gold plated AuroDur, gold plated

RF\_35/11.05/3.1

Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de

Tel.: +49 8684 18-0

Page

email: info@rosenberger.de

1/2

### TECHNICAL DATA SHEET

# Rosenberger

**SMP** 

## STRAIGHT PLUG PCB LIMITED DETENT

## 19S101-40ML5

#### Electrical data

Insertion loss

Impedance 50  $\Omega$ 

Frequency DC to 26.5 GHz Return loss  $\geq$  26 dB, DC to 6 GHz  $\geq$  20 dB, 6 to 12 GHz

 $\leq 0.05 \text{ x} \sqrt{f(GHz)} dB$ 

 $\begin{array}{lll} \text{Insulation resistance} & \geq 5 \text{ } G\Omega \\ \text{Center contact resistance} & \leq 6.0 \text{ } m\Omega \\ \text{Outer contact resistance} & \leq 2.0 \text{ } m\Omega \\ \text{Test voltage} & 500 \text{ } V \text{ } rms \\ \text{Working voltage} & 335 \text{ } V \text{ } rms \\ \text{Contact Current} & 1.2 \text{A DC max.} \end{array}$ 

#### Mechanical data

Mating cycles  $\geq 500$  Center contact captivation  $\geq 7 \text{ N}$ 

Engagement force

- limited detent 45 N max.

Disengagement force

- limited detent 9 N min.

#### Environmental data

Temperature range -65°C to +155°C

Thermal shock MIL-STD-202, Method 107, Condition B
Vibration MIL-STD-202, Method 204, Condition B
Shock MIL-STD-202, Method 213, Condition A

Moisture resistance MIL-STD-202, Method 106
Max. soldering temperature IEC 61760-1, +260°C for 10 sec.

RoHS compliant

#### Tooling

N/A

#### Suitable cables

N/A

#### Weight

Weight 0.3 g/pc

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

				_				
Draft	Date	Approved	Date		Rev.	Engineering change number	Name	Date
A. König	10/07/07	J_Krautenbacher	12.07.16		f00	15-1629	I_Wallner	12.07.16
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany						el.: +49 8684 18-0		Page
www.rosenberger.de					en	nail: info@rosenberger.de		2/2

<sup>-</sup> VSWR in application depends decisive on PCB layout -