

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









0.54" Dual Digit Alphanumeric Displays Technical Data Sheet

Model No: KWA-541XHGB

Spec No.: C5243A1/B1 Rev No.: V.2 Date:Apr/01/2006 Page:1 OF 6

Approved: JOJO Checked: Sun Drawn: Liu
Lucky Light Electronics Co., Ltd. http://www.luckylightled.com



Features:

- ⋄ 0.54" (inch) digit height.
- Excellent segment uniformity.
- Sold state reliability.
- ♦ Industrial standard size.
- ♦ Low power consumption.
- ♦ The product itself will remain within RoHS compliant Version.

Descriptions:

- ♦ The KWA-541XXX series is a lager 13.60mm (0.54") high seven segments display designed for viewing distances up to 7 meters.
- ♦ These displays provide excellent reliability in bright ambient light.
- ♦ These devices are made with white segments and black surface.

Applications:

- Audio equipment.
- ♦ Instrument panels.
- Digital read out display.

Device Selection Guide:


Model No.	Chip Material	Source Color	Description
KWA-541AHGB	AlCainD	Super Yellow Green	Common Anode
KWA-541CHGB	AlGaInP	Super Yellow Green	Common Cathode

Spec No.: C5243A1/B1 Rev No.: V.2 Date:Apr/01/2006 Page: 2 OF 6


Approved: JOJO Checked: Sun Drawn: Liu




Package Dimension:



KWA-541AHGB



KWA-541CHGB



Notes:

- 1. All dimensions are in millimeters (inches).
- 2. Tolerance is \pm 0.25 mm (.010") unless otherwise noted.
- 3. Specifications are subject to change without notice.

Spec No.: C5243A1/B1 Rev No.: V.2 Date:Apr/01/2006 Page:3 OF 6 Approved: JOJO Checked: Sun Drawn: Liu



Absolute Maximum Ratings at Ta=25℃

Parameters	Symbol	Max.	Unit
Power Dissipation (Per Segment)	PD	70	mW
Peak Forward Current (Per Segment) (1/10 Duty Cycle, 0.1ms Pulse Width)	IFP	100	mA
Forward Current (Per Segment)	IF	25	mA
Dating Linear From 25℃		0.4	mA/℃
Reverse Voltage	VR	5	V
Operating Temperature Range	Topr	-40°C to +80°C	
Storage Temperature Range	Tstg	-40°C to +85°C	
Soldering Temperature	Tsld	260°C for 5 Seconds	

Electrical Optical Characteristics at Ta=25 $\ensuremath{^{\circ}}$

Parameters	Symbol	Min.	Тур.	Max.	Unit	Test Condition
Luminous Intensity	IV	8.0	15.5		mcd	IF=20mA (Note 1)
Luminous Intensity Matching Ratio (Segment To Segment)	I _{v-m}			2:1		IF=10mA
Peak Emission Wavelength	λр		575		nm	IF=20mA
Dominant Wavelength	λd		572		nm	IF=20mA (Note 2)
Spectral Line Half-Width	Δλ		20		nm	IF=20mA
Forward Voltage	VF		2.2	2.8	V	IF=20mA
Reverse Current	IR			50	μΑ	VR=5V


Notes:


- 1. Luminous intensity is measured with a light sensor and filter combination that approximates the CIE eye-response curve.
- 2. The dominant wavelength (λd) is derived from the CIE chromaticity diagram and represents the single wavelength which defines the color of the device.

Spec No.: C5243A1/B1 Rev No.: V.2 Date:Apr/01/2006 Page:4 OF 6 Approved: JOJO Checked: Sun Drawn: Liu



Typical Electrical / Optical Characteristics Curves (25°C Ambient Temperature Unless Otherwise Noted)





Ambient Temperature

Ambient Temperature

1000

1000

1000


1000

1000


1000

1000

Ambient Temperature Ta (°C)



Forward Current Derating Curve



Spec No.: C5243A1/B1 Rev No.: V.2 Date:Apr/01/2006 Page:5 OF 6 Approved: JOJO Checked: Sun Drawn: Liu



Please read the following notes before using the datasheets:

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

2. Storage

- 2.1 If the package contains a moisture proof bag inside, please don't open the package before using.
- 2.2 Before opening the package, the LEDs should be kept at 30℃ or less and 80%RH or less.
- 2.3 The LEDs should be used within a year.
- 2.4 After opening the package, the LEDs should be kept at 30° C or less and 60° RH or less.

3. Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than 260°C for 5 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

4. Soldering

When soldering, for Lamp without stopper type and must be leave a minimum of 3mm clearance from the base of the lens to the soldering point.

To avoided the Epoxy climb up on lead frame and was impact to non-soldering problem, dipping the lens into the solder must be avoided.

Do not apply any external stress to the lead frame during soldering while the LED is at high temperature.

Recommended soldering conditions:

Soldering Iron		Wave Soldering		
Temperature Soldering Time	300℃ Max. 3 sec. Max. (one time only)	Pre-heat Pre-heat Time Solder Wave Soldering Time	100°C Max. 60 sec. Max. 260°C Max. 5 sec. Max.	

Note: Excessive soldering temperature and / or time might result in deformation of the LED lens or catastrophic failure of the LED.

5. Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used. It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.

Spec No.: C5243A1/B1 Rev No.: V.2 Date:Apr/01/2006 Page:6 OF 6

Approved: JOJO Checked: Sun Drawn: Liu