



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Data Sheet

Analog Insulation & Continuity Meter

Model 307A

This insulation tester 307A is intended primarily for periodic testing of industrial motors, transformers, electrical wiring, and cable insulation for signs of deterioration. Low readings may indicate impending failure allowing for permit replacement of suspect component during routine maintenance rather than risking component failure. It is also useful for safety testing of TV sets and appliances to assure no hazardous leakage current. The voltage and resistance ratings for insulation testing are often specified for the product to be tested.

Features

- Test insulation to 400M Ω
- Selectable 250V, 500V, or 1000V insulation test
- Low ohm resistance test ranges 500ohm & 3ohm
- 200mA Short circuit test
- Extra rugged integral carrying case
- Locking switch for extended testing
- Live circuit indicator warns of safety hazard
- Volt meter to 600Vac
- Battery test feature
- Overload protection
- IEC 1010-1 Cat III 600V / CE

Applications

Why Test is Necessary?

• Insulation

Every electrical apparatus and installation needs to be safe for the user and for the equipment itself.

Electrical conductors of electricity needs to be insulated from each other, so that they do not create electrical hazard or unnecessary consumption.

Poorly insulated circuits can create leakage current which can be dangerous and trip your GFCI, RCCB or ELCB.

Each country regulates levels at which the insulation levels are acceptable. Generally, Insulation resistance measurement should be done between each conductor and the earth, and between each conductors.

• Continuity

Checking the continuity of wires, complete circuits, connections, closure of contacts, circuit breakers, fuses, bounding resistance of connections, etc... are all very important to ensure wire integrity.

