imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Data Sheet

Programmable DDS Function Generator Series

Models 4084, 4085, 4086 & 4087



B&K Precision® models 4084, 4085, 4086 and 4087 are high performance laboratory grade synthesized function generators with a wide frequency range of up to 120 MHz. Direct digital synthesis (DDS) techniques are used to create stable, accurate output signals for all 27 built-in standard and complex (arbitrary) waveforms. The generators produce high purity, low distortion sine waves, square waves up to 40 MHz and provide a stable output of very small signals down to the 1mV - 10mV range. The instrument also provides a built-in 100 MHz universal counter with frequency measurement and totalize function.

The versatility and capabilities of this series make it an ideal tool for many general-purpose test and bench applications or for use in training and education.

Versatile modulation and trigger capabilities

The generators provide extensive modulation capabilities including AM, FM, FSK, PSK, pulse modulation and linear/logarithmic sweep. Internal and external modulation sources, as well as internal, external and gated trigger sources are supported. Modulation parameters can be set precisely and are adjustable over a wide range. For instance burst count is programmable in 1 burst increments up to 10000 bursts and burst phase is adjustable in 0.1° increments.

Convenient user interface and operation

You can adjust parameters via knob or numeric keypad. Enter amplitude values directly in Vpp, mVpp, Vrms, mVrms or dBm and display the correct voltage by entering the actual output configuration used (terminated with 50 Ohm or open circuit). You can enter frequency in terms of frequency or seconds using time values s, ms, Hz, kHz or MHz. Submenus are used for modulation modes and other complex functions. The generators are fully programmable via the standard RS232 interface, using SCPI commands. The instrument also provides 10 memories to store and recall instrument settings. Additionally the current state is saved at power off and can be restored at power up.




Fig.1 Single cycle burst, start phase=0°



Specifications

Models	4084	4085	4086	4087
Frequency Characteristics				
Sine				$I \mu Hz \sim I 20 MHz$
Square	$I\mu$ Hz ~ 20MHz		$I\mu Hz \sim 40 MHz$	IµHz ∼40MHz
All Other waveforms	$I\mu Hz \sim 100 kHz$			
Frequency Stability		±lx	$10^{-6} (22^{\circ}C \pm 5^{\circ}C)$	
Resolution			IµHz	2)
Accuracy			$5 \times 10^{-6} (22^{\circ}C \pm 5^{\circ}C)$	C)
Data entry Units		s, m	s, Hz, kHz, MHz	
Waveform Characteristics Main Waveforms (Sine, Square	1			
Amplitude resolution			12 bits	
Sample Rate		200MSa/s	12 013	300MSa/s
Sine		2001/13//3		5001154/3
Harmonic Distortion		< - 50dB	Sc (frequency ≤ 5)	MHz)
of Sine Wave*			c (frequency ≤ 10	
			$(frequency \le 20)$	
			$(frequency \le 40)$	
			(frequency > 40)	
THD *			(20Hz ~ 100kH	
Square				,
Rise and fall time*			≤ I5ns	
* = Note: Test conditions for	harmonic distortio	n, sine distortion,		
rise/fall time Output Amp	litude 2Vp-p, Envi	ronmental tempera	ature: $25^{\circ}C \pm 5^{\circ}C$	
Others built-in waveforms				
27 build-in standard and	S	ine, Square, Trians	gle, Positive Ramp,	Falling Ramp,
complex waveforms	N	loise, Pulse, Positi	ve Pulse, Negative	Pulse, Positive
	D	C, Negative DC,	Stair wave, Coded	Pulse, Full wave
	rectified, Half-wave rectified, Sine transverse cut, Sine			
		vertical cut, Sine	phase modulation,	Logarithmic,
	E	xponential, Half-ro	ound, Sinx/x, Squar	re root, Tangent,
	C	ardiac, Earthquake	e, Combination	
Waveform Length			4096 dots	
Amplitude Resolution			10 bits	
Pulse				
Duty Cycle			99.9% (below 10k	
			% (10kHz ~ 100	
Rise/Fall Time		≤ 100r	is (Duty Cycle 20	%)
DC signal characteristics				
DC range			- 10V (high imped	
DC Accuracy		$\leq \pm 5\%$ of setti	ng +10mV (high i	mpedance)
Arbitrary			8 waveforms	
Non volatile memory Waveform length		8	~16000 points	
Amplitude resolution		07	10 bits	
Frequency range		1	µHz~100kHz	
Sample rate		1,	200MSa/s	
Amplitude Characteristics			2001/13//3	
Amplitude Range				
For all models	Freo < 40 MHz:	2mV ~ 20Vpp (o	pen circuit) , 1mV	~ 10Vpp (50Ω)
4084, 4085, 4086			pen circuit), 1 mV	
4087	-	0.1 mV ~ 3Vpp (
Resolution			en circuit), $I\mu Vpp$	(50Ω)
Accuracy			(sine wave relative	
Stability			0.5 % /3 hours	,
Flatness				
For amplitude ≤ 2Vpp	±	:3% (freq≤ 5MHz)	, ±10% (5MHz<	freq≤ 40MHz)
For amplitude >2Vpp:	±	:5% (freq≤ 5MHz)	, ±10% (5MHz<	freq≤ 20MHz)
		±20%	(frequency>20MF	łz)
		± I dBm	(frequency>40M	Hz)
			50Ω	
Output Impedance				
Output Impedance Output Units		Vpp, mVp	p, Vrms, mVrms,	dBm
		Vpp, mVp	op, Vrms, mVrms,	dBm
Output Units	Freq≤ 40MH;		pp, Vrms, mVrms, c (Offset ≤ 2 x pk	
Output Units DC Offset Characteristics		z: ±10Vpk ac+d	•	- pk amplitude)
Output Units DC Offset Characteristics		z: ±10Vpk ac+do lz: ±2Vpk ac+do	c (Offset ≤ $2 \times pk$	- pk amplitude) - pk amplitude)
Output Units DC Offset Characteristics Offset Range (open circuit)	Freq > 40MH	z: ±10Vpk ac+do Iz: ±2Vpk ac+do 2μV (ope	c (Offset ≤ 2 x pk c (Offset ≤ 2 x pk	- pk amplitude) - pk amplitude) 0Ω)

AM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Distortion Modulation Depth Modulation Source Internal Modulating Vaveforms Modulation Error Max. Amplitude of ext. input signal FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode <t< th=""><th>Sine or SquareInternal or externalSine, Square, Triangle, Rising/Falling Ramp100μHz ~ 20kHz$\leq 2\%$$1\% ~ 120\%, 1\% ~ 80\%$ (frequency>40MHz, Ampl > 2Vpp into open circuit)$\pm 5\% + 0.2\%$ (100μHz < frequency $\leq 10k$Hz) $\pm 10\% + 2\%$ ($10k$Hz < frequency $\leq 20k$Hz)il $3Vp-p$ ($-1.5V ~ + 1.5V$)Sine or SquareInternal or externalSine, Square, Triangle, Rising/Falling Ramp100μHz ~ 10kHzMax. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency $\geq 5M$Hz) for externa FM, with input signal voltage $3Vp-p$ ($-1.5V ~ + 1.5V$Sine or SquareInternal or external trigger (external: TTL level, low level F1, high level F2)$0.1ms ~ 800s$Sine or SquarePhase1 (P1) and Phase 2 (P2), range: $0.0 ~ 360.0$$0.1^{\circ}$$0.1ms ~ 800s$Internal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareSine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareSine or SquareSine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareI ~ 10000 cycles0.1ms ~ 800s</th></t<>	Sine or SquareInternal or externalSine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 20kHz $\leq 2\%$ $1\% ~ 120\%, 1\% ~ 80\%$ (frequency>40MHz, Ampl > 2Vpp into open circuit) $\pm 5\% + 0.2\%$ (100μ Hz < frequency $\leq 10k$ Hz) $\pm 10\% + 2\%$ ($10k$ Hz < frequency $\leq 20k$ Hz)il $3Vp-p$ ($-1.5V ~ + 1.5V$)Sine or SquareInternal or externalSine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 10kHzMax. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency $\geq 5M$ Hz) for externa FM, with input signal voltage $3Vp-p$ ($-1.5V ~ + 1.5V$ Sine or SquareInternal or external trigger (external: TTL level, low level F1, high level F2) $0.1ms ~ 800s$ Sine or SquarePhase1 (P1) and Phase 2 (P2), range: $0.0 ~ 360.0$ 0.1° $0.1ms ~ 800s$ Internal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareSine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareSine or SquareSine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareI ~ 10000 cycles0.1ms ~ 800s
Modulation Source Internal Modulating Waveform Frequency of modulating signal Distortion Modulation Depth Modulation Error Max. Amplitude of ext. input signal FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation SK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Resolution PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outp	Internal or externalSine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 20kHz $\leq 2\%$ $1\% ~ 120\%$, $1\% ~ 80\%$ (frequency>40MHz, Ampl > 2Vpp into open circuit) $\pm 5\%+0.2\%$ (100μ Hz < frequency $\leq 10k$ Hz) $\pm 10\%+2\%$ ($10k$ Hz < frequency $\leq 20k$ Hz)il $3Vp$ -p (-1.5V~ +1.5V)Sine or SquareInternal or externalSine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 10kHzMax. 50% of carrier frequency ≤ 5 MHz) for external FM, with input signal voltage $3Vp$ -p (-1.5V~+1.5VSine or SquareInternal or external trigger (external: TTL level, low level F1, high level F2)0.1ms ~ 800sSine or SquarePhase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.00.1°0.1ms ~ 800sSine or squareSine restranal trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareSine or SquareSine or SquareInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareSine or SquareSine or SquareSine or SquareSine or SquareSine or Square
Internal Modulating Waveform Frequency of modulating signal Distortion Modulation Depth Modulation Error Max. Amplitude of ext. input signal FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Impedance	Sine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 20kHz $\leq 2\%$ $1\% ~ 120\%, 1\% ~ 80\%$ (frequency>40MHz, Ampl > 2Vpp into open circuit) $\pm 5\% + 0.2\%$ (100 μ Hz < frequency \leq 10kHz) $\pm 10\% + 2\%$ (100 μ Hz < frequency \leq 20kHz) $il 3Vp-p$ (-1.5V~ + 1.5V)Sine or SquareInternal or externalSine, Square, Triangle, Rising/Falling Ramp100 μ Hz ~ 10kHzMax. 50% of carrier frequency \leq 5MHz) for externalFM, with input signal voltage 3Vp-p (-1.5V~+1.5V)Sine or SquareInternal or external trigger (external: TTL level, low level F1, high level F2)0.1ms ~ 800sSine or SquarePhase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.00.1°0.1ms ~ 800sSine or SquareSine or SquarePhase1 (P1), and Phase 2 (P2), range: 0.0 ~ 360.00.1°0.1ms ~ 800sInternal or external trigger (external: TTL level, low level P1, high level P2)Sine or SquareSine or SquareI ~ 10000 cycles
Frequency of modulating signal Distortion Modulation Depth Modulation Error Max. Amplitude of ext. input signal FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform Control Model PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Characteristics Waveform Burst Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Time Sweep Time Sweep resignal frequency D Control Mode Imputs/ Outputs Main Output	$100\mu Hz \sim 20kHz$ $\leq 2\%$ $100\mu Hz \sim 20kHz$ $\leq 2\%$ $1\% \sim 120\%, 1\% \sim 80\% (frequency>40MHz, Ampl > 2Vpp into open circuit)$ $\pm 5\%+0.2\% (100\mu Hz < frequency \le 10kHz)$ $\pm 10\%+2\% (10kHz < frequency \le 20kHz)$ $il 3Vp-p (-1.5V \sim + 1.5V)$ Sine or Square Internal or external Sine, Square, Triangle, Rising/Falling Ramp 100\mu Hz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency 5 MHz) for external FM, with input signal voltage 3Vp-p (-1.5V ~ + 1.5V) Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) $0.1ms \sim 800s$ Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square $1 \sim 10000 \text{ cycles}$
Distortion Modulation Depth Modulation Error Max. Amplitude of ext. input signa FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Resolution PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Impedance	$\leq 2\%$ $ \% \sim 120\%, 1\% \sim 80\% (frequency>40MHz, Ampl > 2Vpp into open circuit)$ $\pm 5\%+0.2\% (100\muHz < frequency \le 10kHz)$ $\pm 10\%+2\% (10kHz < frequency \le 20kHz)$ $il 3Vp-p (-1.5V \sim + 1.5V)$ Sine or Square Internal or external Sine, Square, Triangle, Rising/Falling Ramp 100\muHz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency \ge 5MHz) for external FM, with input signal voltage 3Vp-p (-1.5V ~ + 1.5V) Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2)
Modulation Depth Modulation Error Max. Amplitude of ext. input signal FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Rate PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Impedance	$1\% \sim 120\%$, $1\% \sim 80\%$ (frequency>40MHz, Ampl > 2Vpp into open circuit) $\pm 5\% + 0.2\%$ (100µHz < frequency ≤ 10kHz) $\pm 10\% + 2\%$ (10kHz < frequency ≤ 20kHz)
Modulation Error Max. Amplitude of ext. input signal FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Rate PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Impedance	Ampl > 2Vpp into open circuit) $\pm 5\% + 0.2\%$ (100µHz < frequency ≤ 10kHz)
Max. Amplitude of ext. input signa FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	$ \pm 5\% + 0.2\% (100\mu Hz < frequency ≤ 10kHz) \pm 10\% + 2\% (10kHz < frequency ≤ 20kHz) il 3Vp-p (-1.5V~ + 1.5V) Sine or Square Internal or external Sine, Square, Triangle, Rising/Falling Ramp 100\mu Hz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency ≥ 5MHz) for externa FM, with input signal voltage 3Vp-p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Sine or Square Sine or Square 1 ~ 10000 cycles$
Max. Amplitude of ext. input signa FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform Control Model FSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	$\begin{array}{r llllllllllllllllllllllllllllllllllll$
FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK Resolution PSK Resolution PSK Resolution Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	I $3Vp$ -p (-1.5V~ +1.5V) Sine or Square Internal or external Sine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency≥ 5MHz) for external FM, with input signal voltage $3Vp$ -p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
FM Characteristics Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK Resolution PSK Resolution PSK Resolution Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	Sine or Square Internal or external Sine, Square, Triangle, Rising/Falling Ramp 100µHz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency's SMHz) for external FM, with input signal voltage 3Vp-p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Carrier Waveforms Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Start/ Stop Frequency External trigger signal frequency D Control Mode Impedance	Internal or external Sine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency) \geq 5MHz) for externa FM, with input signal voltage $3Vp$ -p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Iow level P1, high level P2)
Modulation Source Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time	Internal or external Sine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency) \geq 5MHz) for externa FM, with input signal voltage $3Vp$ -p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Iow level P1, high level P2)
Internal Modulating Waveform Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	Sine, Square, Triangle, Rising/Falling Ramp 100μ Hz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency≥ 5MHz) for externa FM, with input signal voltage 3Vp-p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Sine or Square 1 ~ 10000 cycles
Frequency of modulating signal Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	100μ Hz ~ 10kHz Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency≥ 5MHz) for external FM, with input signal voltage 3Vp-p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2)
Deviation FSK Characteristics Carrier Waveform Control Model FSK Rate PSK PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Time Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	Max. 50% of carrier frequency for internal FM Max 100kHz (carrier frequency≥ 5MHz) for external FM, with input signal voltage 3Vp-p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) O. Ins ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 O.1° O.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Phase1 (P1), high level P2) Sine or Square O. 1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Sine or Square I ~ 10000 cycles
FSK Characteristics Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Swee	Max 100kHz (carrier frequency≥ 5MHz) for externa FM, with input signal voltage 3Vp-p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) O. Ins ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Time Sweep Time Start/ Stop Frequency D Control Mode Imputs/ Outputs Main Output Impedance	FM, with input signal voltage 3Vp-p (-1.5V~+1.5V Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Time Sweep Time Start/ Stop Frequency D Control Mode Imputs/ Outputs Main Output Impedance	Sine or Square Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Carrier Waveform Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Time Sweep Time Start/ Stop Frequency D Control Mode Imputs/ Outputs Main Output Impedance	Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase 1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Control Model FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	Internal or external trigger (external: TTL level, low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase 1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
FSK Rate PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output Impedance	low level F1, high level F2) 0.1ms ~ 800s Sine or Square Phase 1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	0.1ms ~ 800s Sine or Square Phase 1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
PSK Characteristics Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	0.1ms ~ 800s Sine or Square Phase 1 (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Carrier Waveform PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Time Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	Phase I (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square I ~ 10000 cycles
PSK Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Top Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	Phase I (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square I ~ 10000 cycles
Resolution PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Time Sweep Time Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output	Phase I (P1) and Phase 2 (P2), range: 0.0 ~ 360.0 0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square I ~ 10000 cycles
PSK rate Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/Outputs Main Output	0.1° 0.1ms ~ 800s Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Control Mode Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/Outputs Main Output	Internal or external trigger (external: TTL level, low level P1, high level P2) Sine or Square 1 ~ 10000 cycles
Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	low level P1, high level P2) Sine or Square I ~ 10000 cycles
Burst Characteristics Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	low level P1, high level P2) Sine or Square I ~ 10000 cycles
Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output	Sine or Square 1 ~ 10000 cycles
Waveform Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output	1 ~ 10000 cycles
Burst Counts Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Imputs/ Outputs Main Output Impedance	1 ~ 10000 cycles
Time interval between bursts Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	2
Control Mode Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	
Frequency Sweep Characteristics Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	
Waveform Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	Internal, single or external gated trigger
Sweep Time Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	
Sweep Mode Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	Sine or Square
Start/ Stop Frequency External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	1ms ~ 800s (linear), 100ms ~ 800s (log)
External trigger signal frequency D Control Mode Inputs/ Outputs Main Output Impedance	Linear or Logarithmic
Control Mode Inputs/ Outputs Main Output Impedance	Same as frequency range of Sine & Square
Inputs/ Outputs Main Output Impedance	
Main Output Impedance	Internal or external trigger
Impedance	
Protection	50Ω
	Short circuit and overload protected
Output MOD OUT	
Frequency	100Hz ~ 20kHz
Waveform	Sine, Square, Triangle, Rising/Falling Ramp
Amplitude	5Vp-p ± 5%
Output Impedance	600Ω
Modulation IN	3Vpp = 100% Modulation
External Input Trig/FSK/Burst	Level - TTL
Universal Counter, Key Specs*	
Frequency Range	
Frequency Measurement	1Hz ~ 100MHz
Totalize mode	50MHz max
	ection, refer to online manual at www.bkprecision.com
General	center, refer to online manual at www.bxprecision.com
AC Input	198~242V or 99~121V, Frequency: 47~ 63Hz
Power Consumption	198~242 V 01 99~121V, Frequency: 47~ 63HZ <35VA
State Storage Memory	~55W1
	fraquancy amplituda unusform DC affecture
Storage Parameters	frequency, amplitude, waveform, DC offset values,
Sharran C	modulation parameters
Storage Capacity	10 user configurable stored states
Dimensions (W x H x D)	10" x 3.93" x 14.56" (255 x 100 x 370) mm
Weight	6.6 lbs (3 kg)
Remote Interface	RS232
Safety designed according to	10232
EMC tested according to	EN61010
	EN61010 EN55022, EN55024, EN61326, EN601000
luded Accessories: BNC to alligator ca	EN61010
power line cord, te	EN61010 EN55022, EN55024, EN61326, EN601000