



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




PmodSWT™ Reference Manual

Revised April 12, 2016

This manual applies to the PmodSWT rev. A

Overview

The PmodSWT provides users with four slide switches for up to 16 different binary logic inputs to for the attached system board.



The PmodSWT.

Features include:

- 4 slide switches
- Add user input to host board or project
- Static binary logic input
- Small PCB size for flexible designs 1.3 in × 0.8 in (3.3 cm × 2.0 cm)
- 6-pin Pmod port with GPIO interface
- Follows Digilent Pmod Interface Specification Type 1

1 Functional Description

The PmodSWT utilizes four slide switches that users can use as a set of on and off switches or as a set of static binary inputs.

2 Interfacing with the Pmod

The Pmod communicates with the host board via the GPIO protocol. When a switch is turned to the “on” position, its respective pin will be at the logic level high voltage and when a switch is off, the pin will be a logic level low voltage.

Pin	Signal	Description
1	SWT1	Switch 1 input
2	SWT2	Switch 2 input
3	SWT3	Switch 3 input
4	SWT4	Switch 4 input
5	GND	Power Supply Ground
6	VCC	Positive Power Supply

Table 1. Pinout description table.

There are no integrated circuits on the PmodSWT, so any voltage range that is usable with your system board can be used on the PmodSWT.

3 Physical Dimensions

The pins on the pin header are spaced 100 mil apart. The PCB is 1.3 inches long on the sides parallel to the pins on the pin header and 0.8 inches long on the sides perpendicular to the pin header.