



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




## Pmod SSR Reference Manual

Revised January  
This manual applies to the Pmod SSR rev. B

---

### Overview

The Digilent Pmod SSR (Revision B) is a solid state relay that features [IXYS' CPC1908J](#). The Pmod SSR uses a switch controlled by a single GPIO pin and is rated to block up to 60 Volts and pass up to 15 Amps.



*The Pmod SSR.*

#### Features:

- Solid State Relay electronic switch
- Open/closed status LED
- 1×6-pin Pmod port with GPIO interface

## 1 Functional Description

The Pmod SSR uses a single GPIO pin to establish a connection between two terminals.

## 2 Specifications

Parameter	Rating	Units
Maximum Blocking Voltage	60	V <sub>P</sub>
Maximum Peak Current	25	A <sub>P</sub>
Maximum Continuous Current	15	A <sub>rms</sub> /A <sub>rms</sub>
On-resistance	0.09-0.3	Ω
Turn-on Switching Speed	20	ms
Turn-off Switching Speed	5	ms

## 3 Interfacing with the Pmod

The Pmod SSR communicates with the host board via a GPIO pin. To open the relay, the ON pin must be driven to a logic high state. To close the relay, the ON pin must be driven to a logic low state.

### 3.1 Pinout Description Table

Pin	Signal	Description
1	ON	Switch Control
2	NC	Not Connected
3	NC	Not Connected
4	NC	Not Connected
5	GND	Power Supply Ground
6	VCC	Power Supply (3.3/5V)

## 4 Physical Dimensions

The pins on the pin header are spaced 100 mil apart. The PCB is 1.7 inches long on the sides parallel to the pins on the pin header and 0.8 inches long on the sides perpendicular to the pin header.

## 5 Additional Information

The schematics of the Pmod SSR are available [here](#).

Example code demonstrating how to use the Pmod SSR can be found at the [Pmod SSR Resource Center](#).

If you have any questions or comments about the Pmod SSR, feel free to post them under the appropriate section (“Add-on Boards”) of the [Digilent Forum](#).