



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



CAN Bus 24 Development Kit

Sku: 53325-892



Development Kit Options

Tools Included	12-24 Bit Compilers	24 Bit Compiler	Just H/W	Only PCB
Compiler for PIC10-PIC18	●			
Compiler for PIC24-dsPIC33	●	●		
Programmer	●	●	●	
Prototyping board	●	●	●	●
Power supply & cables	●	●	●	
Exercise book	●	●	●	
Price				
Buy Now ➔	Add	Add	Add	Add

This kit enables users to begin CAN network development with Microchip's PIC[®] PIC24 and dsPIC[®] DSC families. The development kit includes the powerful PCWHD Integrated Development Environment with compiler support for Microchip's 8-bit and 16-bit PIC[®] MCU families and an ICD-U64 in-circuit programmer/debugger that supports C-aware real time debugging. The prototyping board has four nodes and includes a PIC24HJ56GP610 with two on-chip ECAN controllers, a dsPIC30F4012 connected to an MCP2515 CAN peripheral, and two MCP25050 CAN expanders. CAN drivers and example code are also included.

Node A: A PIC24HJ56GP610 which includes an integrated CAN peripheral. Note: Only the can-PIC24 driver can be used with node A.

Node B: A dsPIC30F4012 connected to an MCP2515 (external CAN peripheral SPI interface).

Node C & D: MCP25050s (stand-alone CAN expanders) pre-programmed by CCS to respond to specific CAN IDs.

Nodes A-C have potentiometer, three LEDs and three pushbuttons connections. Node D is connected to a 7-segmented LED.

An extra CAN transceiver has also been left open to connect the CAN Bus Prototype board with other CAN systems.

CAN Bus 24 Prototyping Board (Size: 3.27" x 4.80") includes:

- PIC24HJ56GP610
- dsPIC30F4012
- 30 I/O (8 Can Be Analog)
- MCP2515
- Two MCP25050
- Three Potentiometers
- Nine LEDs



- 7-Segment LED
- Two RS-232 Ports
- RS-232 Level Converter
- Two ICD Jacks

CAN Bus 24 Development Kit includes:

- CAN Bus Prototyping Board
- In-Circuit Debugger/Programmer
- Exercise Tutorial
- 9V AC Adapter and Cables

