



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us


Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



## Neon Circuit Component Lamps

Configuration	Part Number	Old Ref. Number	Design Current mA	Initial DC Breakdown Voltage	Initial DC Maintaining Voltage
Wire Terminal					
	2AA	NE-99	0.30	60-80	52-62
	2AC		1.50	125 Max.	-
	3AD	NE-98	0.30	65-80	Avg.>50
	3AG		0.40	60-90	Avg.>58
	3AG-B		0.40	65-73	52-62
	3AG-C		0.40	68-76	52-62
	3AG-F		0.40	65-73	64 Max.
	3AH		2.00	75-135	Avg.70
	3AJ		5.00	60-100	Avg.>59
	3AJ-C		5.00	60-100	Avg.>59
	4AD		0.50	105-135	60-80
	4AE		0.50	120-150	60-80
	5AB	NE-23	0.30	60-90	Avg.59
	5AB-A		0.30	60-80	50-65
	5AB-B		0.30	62-72	50-60
	5AB-BT		0.30	62-72	50-60
	5AB-T		0.30	60-90	Avg.59
	5AC	NE-68	0.30	60-90	52-65
	5AG	NE-81	0.10	64-80	50-58
	5AG-A	NE-76	0.40	68-76	50-60
	5AH	NE-83	5.00	60-100	Avg.>59
	5AH-A		5.00	60-85	50-65
	5AH-B		5.00	75-85	55-66
	5AH-D		3.00	60-85	50-70
	5AH-E		5.00	60-100	Avg.>61
	5AJ	NE-86	1.50	55-90	Avg.>57
	5AJ-A		1.50	55-75	45-65
	5AJ-B		1.50	70-90	55-75

Average Life to Indicate Change				Dimensions		
Breakdown Voltage		Maintain Voltage		inches		
Chg.	Hrs.	Chg.	Hrs.	A (Max.)	B (Max.)	C (Min.)
Wire Terminal-Standard Brightness						
-	-	6.0	7,500	.244	.500	1.00
-	25,000	-	-	.244	.500	1.00
5.0	6,000	5.0	6,000	.244	.750	2.00
5.0	2,000	5.0	2,000	.244	.750	2.00
5.0	2,000	5.0	2,000	.244	.750	2.00
5.0	2,000	5.0	2,000	.244	.750	2.00
5.0	2,000	5.0	2,000	.244	.750	1.00
10.0	2,000	10.0	2,000	.244	.750	2.00
5.0	500	5.0	500	.244	.750	1.00
5.0	500	5.0	500	.244	.750	2.00
10.0	3,000	10.0	3,000	.244	.844	1.00
10.0	3,000	10.0	3,000	.244	.844	1.00
5.0	6,000	5.0	6,000	.244	1.000	1.00
5.0	6,000	5.0	6,000	.244	1.000	1.00
5.0	6,000	5.0	6,000	.244	1.000	1.00
5.0	6,000	5.0	6,000	.244	1.000	1.00
5.0	6,000	5.0	6,000	.244	1.000	1.00
-	-	5.0	2,000	.244	1.000	1.00
5.0	2,000	5.0	2,000	.244	1.000	1.00
-	1,000	5.0	2,000	.244	1.000	1.00
5.0	5,000	5.0	5,000	.244	.938	1.00
5.0	5,000	5.0	5,000	.244	.938	1.00
5.0	5,000	5.0	5,000	.244	.938	1.00
5.0	5,000	5.0	5,000	.244	.938	1.00
5.0	5,000	5.0	5,000	.244	.938	2.00
5.0	2,000	5.0	2,000	.244	.938	1.00
5.0	2,000	5.0	2,000	.244	.938	1.00
5.0	2,000	5.0	2,000	.244	.938	1.00