



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us


Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# 3M™ Scotchlok™ Closed End Connector, Nylon Insulated, Copper Insert, 722-N-A



Data Sheet

September 2008

Product Number	L
722-N-A	0.83

## Specifications

Wire Size:	22-16 AWG Copper wire only
Maximum Voltage Rating:	600V Building Wire 1000V Signs, Fixtures (Luminaires)
Maximum Operating Temp:	221°F (105°C)
Maximum Current:	Same as Wire
Insulator Material:	Nylon
Sleeve Material:	Copper

## SOLID / STRANDED AWG WIRE COMBINATIONS:

Copper Wire Only. "CU ONLY"

Wire Combinations
2 to 5 #22
1 to 4 #22 w/ 1 or 2 #20
1 to 3 #22 w/ 1 #18
1 #22 w/ 1 #16
2 or 3 #20

# 3M™ Scotchlok™ Closed End Connector Nylon Insulated, Copper Insert, 722-N-A

## Installation Information

### **WARNING**


Turn power off before installing or removing terminal. All electrical work should be done according to appropriate electrical codes.

For use on solid or stranded copper (AWG) wire only.

#### Instructions:

1. Strip all wires ½ inch.
2. Pre-twist wires before crimping.
3. Insert wires into connector.
4. Insert into proper tool station and crimp.

3M™ Scotchlok™ Crimp Station Tools: TH-440, 22-14 Insul.; TH-450, 26-14 Insul.



 Barrel Crimp (Required)

*Pre-twist wires before crimping.*

## Engineering/ Architectural Specifications

3M™ Scotchlok™ Closed End Connector, Nylon Insulated, Copper Insert 722-N-A shall, electrically and mechanically, connect permanently to the pre-stripped ends of two or more copper wires.

The closed end connector shall be a copper sleeve covered by a molded nylon, skirted insulator of natural color.

## Availability

Please contact your local distributor; available from [3M.com/electrical](http://3M.com/electrical) [Where to Buy] or call 1-800-245-3573.

## Important Notice

All statements, technical information, and recommendations related to 3M's products are based on information believed to be reliable, but the accuracy or completeness is not guaranteed. Before using this product, you must evaluate it and determine if it is suitable for your intended application. You assume all risks and liability associated with such use. Any statements related to the product which are not contained in 3M's current publications, or any contrary statements contained on your purchase order shall have no force or effect unless expressly agreed upon, in writing, by an authorized officer of 3M.

## Warranty; Limited Remedy; Limited Liability:

This product will be free from defects in material and manufacture at the time of purchase. **3M MAKES NO OTHER WARRANTIES INCLUDING, BUT NOT LIMITED TO, ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.** If this product is defective within the warranty period stated above, your exclusive remedy shall be, at 3M's option, to replace or repair the 3M product or refund the purchase price of the 3M product. **Except where prohibited by law, 3M will not be liable for any indirect, special, incidental or consequential loss or damage arising from this 3M product, regardless of the legal theory asserted.**

3M and Scotchlok are trademarks of 3M Company.



### Electrical Markets Division

6801 River Place Blvd.  
Austin, TX 78726-9000  
800 245 3573  
FAX 800 245 0329  
[www.3M.com/electrical](http://www.3M.com/electrical)

Please recycle.  
© 3M 2008 All rights reserved.  
78-8127-6880-8\_A