



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# Concentric Ring Probe Installation, Operation and Maintenance



Made in the  
United Kingdom



Figure 1. SCS [770007](#) Concentric Ring Probe

## Description

The SCS [770007](#) Concentric Ring Probe is an instrument to be used in conjunction with a resistance meter, such as the SCS [701](#) Analog Surface Resistance Megohmmeter, to measure surface resistance per ANSI/ESD STM11.11 the test method listed in Packaging standard ANSI/ESD S541 for surface resistance of planar materials.

The Concentric Ring Probe (Ref: ANSI/ESD STM11.12) can measure the volume resistance of planar materials using a flat conductive metal plate (not included).

The Concentric Ring Probe may be used for the resistance measurements of ESD packaging including static shielding and other bags.

The SCS Concentric Ring Probe is compatible with the following SCS Surface Resistance Meters:

| Item                     | Description                               |
|--------------------------|---|
| <a href="#">701</a>      | Analog Surface Resistance Megohmmeter Kit |
| <a href="#">701-M</a>    | Analog Surface Resistance Megohmmeter     |
| <a href="#">SRMETER2</a> | Surface Resistance Meter                  |

## Resistivity and Resistance

Per ANSI/ESD STM11.11 section 12.0 “CONVERSION TO RESISTIVITY, When it is appropriate to convert a resistance obtained by this test method to an equivalent resistivity in ohms per square, multiply the resistance measurements obtained by this method by ten. The conversion factor of ten is derived from the geometry of the electrode assembly.

NOTE: Conversions to resistivity may not be valid for materials that are laminated, plated or metallized with conductive materials. This fact should be understood when users of this test procedure are required to satisfy specifications given in “ohms/square.”

## Repeatability

Per ANSI/ESD STM11.11 section 4.0 “REPEATABILITY, This test method has been shown to have a repeatability of approximately one half order of magnitude” in controlled environments.

## Packaging

- 1 Concentric Ring Probe
- 1 BNC / Banana Jack Adapter

## Operation

1. Connect the Concentric Ring Probe to a resistance meter using the included BNC / banana jack adapter and the meter’s test leads.
2. Place the material to be tested on an insulative surface.
3. Place the Concentric Ring Probe on top of the material to be tested.
4. Take a resistance measurement using the resistance meter.



Figure 2. Using the Concentric Ring Probe with the SCS [701](#) Analog Surface Resistance Megohmmeter

## Specifications

|   |  |
|---|--|
| Dimensions<br>(with BNC / banana<br>jack adapter) | 2.8" Dia. x 6.5" H<br>(71 mm x 165 mm) |
| Outer Probe Diameter                              | 2.5" (63 mm)                           |
| Inner Probe Diameter                              | 1.2" (30 mm)                           |
| Weight  | 5.8 lbs. (2.6 kg)                      |
| Insulation Resistance<br>Between Probes           | >1 x 10 <sup>12</sup> ohms @ 500V      |
| Probe Resistance of<br>Carbon Pads                | <100 ohms at low test voltage          |
| Country of Origin                                 | United Kingdom                         |

### Limited Warranty, Warranty Exclusions, Limit of Liability and RMA Request Instructions

See the SCS Warranty -

[StaticControl.DescoIndustries.com/Limited-Warranty.aspx](http://StaticControl.DescoIndustries.com/Limited-Warranty.aspx)



Figure 3. Using the Concentric Ring Probe with the SCS [SRMETER2](#) Surface Resistance Meter