



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



→ Wireless Digital Extension for XD10 and XD26

- Wireless RF transmission of up to 8 digital inputs
- Use with Linx Technologies Keyfob transmitters at 418 MHz
- Transmission distances up to 100 feet
- Power supply via the controller
- Built-in antenna



Remote module

Part numbers

Type	Description	Supply	Part No.
XT01	Wireless digital extension	100-240 VAC controllers ---	88970826

General characteristics

Environmental characteristics

Certifications complies with limits for Class A digital device pursuant to Part 15 of the FCC Rules

Operating temperature -20 → +55°C

Storage temperature -40 → +70°C

Protection IP20

Input characteristics

Input type 8 digital

Receiver frequency 418 MHz

Maximum range 1000 feet

Typical range 100 feet

Transmitter parameters

Type Linx type MS Keyfob Transmitter or compatible

Number of buttons 1 to 8

Comments

* See installation instructions for program example and transmitter setup

Dimensions (mm)

