



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Rugged Metal On/Off Switch with White LED Ring – 16mm White On/Off

PRODUCT ID: 917

These chrome-plated metal buttons are rugged and look real good while doing it! Simply drill a 16mm hole into any material up to 1/2" thick and you can fit these in place, there's even a rubber gasket to keep water out of the enclosure. On the front of the button is a flat metal actuator, surrounded by a white plastic LED ring. On the back there are 3 contacts for the button (common, normally-open and normally-closed) and 2 for the white LED ring (+ and -). Connect 3 to 6V to the LED to have it light up nicely, there's a built in resistor! If you want to use this with a higher voltage, say 12V or 24V, simply add a 470 ohm resistor in series with the LED connection to keep the LED current at around 20mA.

This button is an on/off switch button, when you press it the 'normally-open' contact shorts to the common contact and the button stays 'pressed'. When you press it a second time, the button springs open, and the contacts open up again.

The switch and LED are separated, so you could wire it to turn on when pressed or vice versa or whatever you wish! Check the tech details for information!

. TECHNICAL DETAILS

- Drill hole diameter: 16mm
- Switch rating: 3A / 250VDC
- Switch contacts: 1 NO, 1 NC
- Material: Chrome-plated brass
- Contact resistance: < 50 mOhm
- Insulation resistance: > 1000 Mohm
- Temperature: -20 C to +55 C
- Mechanical life: > 500,000
- Electrical life: > 50,000
- Panel thickness: 1-13mm
- Operating pressure: 1.5 - 2.5 N
- Operating stroke: 2mm
- Lamp rated voltage: 6V

