

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







# **AMPROBE®**

**Data Sheet** 

# **ACD-22SW Swivel Clamp Meter**

New patented rotating head clamp design allows easy viewing of the measurements in tight or inconvenient to reach places. Simply rotate the body of meter to get an unobstructed view of the LCD display. Rich set of features and CAT III 600V safety reading for use in electrical and HVAC applications.

- **TRMS Measurement**
- 180 degree rotating head for the perfect display viewing
- Advanced VoltTect non-contact voltage detection
- Slim jaw design with one hand operation
- Measures AC Current up to 400 ACA, AC/DC Voltage up to 600V, Resistance and Capacitance
- Audible continuity
- Auto and manual ranging respectively for quick checks and precise measurements
- Backlight
- Auto power off
- Data hold
- Accommodates conductors up to 1.18" (30mm) in diameter
- Safety CAT III 600 V
- Test leads, battery (installed), Users Manual, Carrying Case and type-K thermocouple are included with the product



# No hassle warranty

No waiting.





(note: \$500 MSLP limit)



# **ACD-22SW Swivel Clamp Meter**

### **Data Sheet**

# **General Specifications**

Display	3¾ digit liquid crystal display (LCD) with a maximum reading of 3999.
Polarity	Automatic, positive implied, negative polarity indication.
Overrange	(OL) or (-OL) is displayed.
Zero	Automatic.
Low battery indication	The "a" is displayed when the battery voltage drops below the operating level.
Auto power off	Approx. 10 minutes.
Measurement rate	2 times per second, nominal.
Operating Environment	0°C to 50°C / 32°F to 122°F at <70% relativehumidity.
Storage Ttemperature	-20°C to 60° / -4°F to 140°F, 0 to 80% R.H. withbattery removed from meter.
Accuracy	Stated accuracy at 74°F ±8°F, <75% relative humidity.
Temperature Coefficient	0.1 × (specified accuracy) per °F, (32°F to 66°F, 82°F to 122°F).
Altitude	6561.7 Feet (2000m).
Jaw opening capability	30mm conductor.
Power	1.5 volt battery x2, R03/SIZE AAA.
Battery life	50 hours typical with carbon-zinc. 100 hours typical with alkaline.
Dimensions	240 × 70 × 41mm (9.5 × 2.8 × 1.6 in).
Weight	Approx. 220g (7.7oz.) including battery.
Safety	Designed to meet IEC 61010-1 (EN61010-1) and IEC 61010-2-032 (EN61010-2-032), CATIII 600V class II and pollution degree 2 indoor use comply with CE , CSA

# **Electrical Specifications**

Ranges	400mV, 4V, 40V, 400V, 600V
Resolution	0.1mV
Accuracy	±(0.5% rdg + 2 dgts)
Input Impedance	$400$ mV:> $100$ M $\Omega$ ; $4$ V: $10$ M $\Omega$ ; $40$ V~ $600$ V: $9.1$ M $\Omega$
Overload Protection	600VDC or AC rms To measure millivolts, use "RANGE " button to manually select 400mV range.

#### AC Volts (50Hz - 500Hz)

Ranges	4V, 40V, 400V, 600V
Resolution	1mV
Accuracy	±(1.2% rdg + 8 dgts)
	±(1.5% rdg + 8 dgts) on 600V range
Crest Factor	≤3
AC coupled true rms specified from 5% to 100% range	
Input Impedance	4V:10ΜΩ;40V~600V:9.1ΜΩ
Overload Protection	600 VDC or AC rms

#### AC Current (50Hz - 60Hz)

Ranges	40A , 400A	
Resolution	0.01A	
Accuracy	±(2.0% rdg + 10 dgts) 50 ~ 60Hz	
Crest Factor	≤3	
AC coupled true rms specified from 5% to 100% range		
Overload Protection	400A AC	



# **ACD-22SW Swivel Clamp Meter**

**Data Sheet** 

Resistance	
Ranges	400Ω, 4kΩ, 40kΩ, 400kΩ, 4ΜΩ, 40ΜΩ
Resolution	0.1Ω
Accuracy	$\pm$ (1.0% rdg + 5 dgts) on 400 $\Omega$ to 400k $\Omega$ ranges
	$\pm$ (1.5% rdg + 5 dgts) on 4M $\Omega$ range
	$\pm$ (3.0% rdg + 5 dgts) on 40M $\Omega$ range
Open Circuit Volts	-0.45V dc typical, (-1.2Vdc on 400 $\Omega$ range)
Overload Protection	600VDC or AC rms
Diode Test	
Test Current	0.8mA (approximate)
Accuracy	±(3.0% rdg + 3 dgts)
Open Circuit Volts	3.0 Vdc typica
Overload Protection	600VDC or AC rms
Continuity	
Range	400Ω
Resolution	1Ω
Audible Indication:	Less than $25\Omega$
Response Time	500ms
Overload Protection	600VDC or AC rms
Non-Contact Voltage Indicator	Sense voltage 70V to 600VAC (50Hz ~ 60Hz) beeper chirps and big bright red LED comes on, works when meter dial is on any ranges.
AUXILIARY FEATURES	
Hold	Freeze the latest reading on the display.
Range	Excute manual range mode.
Disable Auto Power Off	Set the DMM to off position, press (RANGE) button, and hold the (RANGE) button while turning the rotary knob to the desired range position. Release the button when LCD displays normally. Note "APO" annunciator is missing from the LCD. The Auto Power Off mode is activated with an "APO" symbol indicating on LCD.



#### **ACD-22SW Swivel Clamp Meter**

**Data Sheet** 

#### **Included Accessories**

One pair test leads 1.5V battery x2 (installed) Carrying case TPK01 thermocouple Users Manual

#### **Amprobe® Test Tools**

website: www.Amprobe.com email: info@amprobe.com

Everett, WA 98203 Tel: 877-AMPROBE

#### **Amprobe® Test Tools Europe**

In den Engematten 14 79286 Glottertal, Germany Tel.: +49 (0) 7684 8009 - 0

©2010 Amprobe Test Tools. All rights reserved. 08/2010 ACD-22SW\_DS Rev A