



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Phytion™		Device Programmers and Development Tools for Microcontrollers				
Home	Products	E-Shop	Support	Contact	News	Site Map

Quick Links

- [Help Desk](#)
- [Downloads](#)
- [All Programmers](#)
- [Device Search](#)
- [Tools Catalogs](#)

Shopping Cart

Items: 0

Total: \$0.00


[Your Account](#)

Products

- Development Tools
 - ARM
 - 8051
 - Other
- Device programmers
 - All Models
 - Universal
 - In-System
 - Gang
 - Adapters
- Custom made tools
- OEM tools

AE-TS56-16I-2

DIP40/ TSOP56 specialized adapter for FLASH memory.



Description:

DIP40/TSOP56 specialized adapter for FLASH memory. Device package dimensions: 14 x 20 mm, 0.5 mm pitch.

Supported Devices:

Click the device programmer model below to get an appropriate list of the devices supported by this programmer with this adapter:

- [ChipProg-48](#)
- [ChipProg-G4](#)
- [ChipProg-40](#)
- [ChipProg+](#)

[Adapter wiring diagram](#)

Adapter Connection Table:

DIP-40	SSOP-56	74AHC573	C1, 150pF	C2, 0.1uF
1	21, 33			
2	44			
3	43			
4	38			
5	5			
6	45	4		
7		11	1	
8	56			
9	31			
10	47	7		
11	53			
12	55			
13	51	3		
14	39			
15	26			
16	16			
17	18			
18	17			
19	42			
20	4,15,20,37	1, 10	2	1
21	40			
22	19			
23	50	8		
24	35	9		
25	27			
26	24			
27	25			
28	49	6		
29	54			
30	52			

	31	29		
	32	41		
	33	46	5	
	34	32		
	35	48	2	
	36	22		
	37	30		
	38	3		
	39	36		
	40	1.28	20	2
		6	17	
		7	16	
		8	14	
		9	19	
		10	15	
		11	13	
		12	18	
		13	12	

Copyright © 2007-2010 Phyton, Inc.

Phone: 718-259-3191 • E-mails: info@phyton.com, sales@phyton.com, support@phyton.com