



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



## AS3933

### 3D Low Frequency Wakeup Receiver

#### 1 General Description

The AS3933 is a 3-channel low power ASK receiver that is able to generate a wakeup upon detection of a data signal which uses a LF carrier frequency between 15-150 kHz. The integrated correlator can be used for detection of a programmable 16-bit or 32-bit Manchester wakeup pattern. The device can operate using one, two, or three active channels.

The AS3933 provides a digital RSSI value for each active channel, it supports a programmable data rate and Manchester decoding with clock recovery. The AS3933 offers an internal Clock Generator, which is either derived from a crystal oscillator or the internal RC oscillator. The user can decide to use the external clock generator instead.

The programmable features of AS3933 enable to optimize its settings for achieving a longer distance while retaining a reliable wakeup generation. The sensitivity level of AS3933 can be adjusted in presence of a strong field or in noisy environments.

Antenna tuning is greatly simplified, as the automatic tuning feature ensures perfect matching to the desired carrier frequency.

The device is available in 16 pin TSSOP and QFN 4x4 16LD packages.

#### 2 Key Features

- 3-channel ASK wakeup receiver
- Carrier frequency range 15 - 150 kHz
- One, two, or three channel operation
- Reliable 1-, 2- or 3-D wakeup pattern detection
- Programmable wakeup pattern (16-bit or 32-bit) Manchester
- Doubling of wakeup pattern supported (both for 16 and 32 bits)
- Wakeup without pattern detection supported

- Wakeup sensitivity 80  $\mu$ V<sub>RMS</sub> (typ)
- Adjustable sensitivity level
- Highly resistant to false wakeups
- Easy antenna tuning for perfect matching on the wanted carrier frequency
- Self calibration of the internal RC-oscillator
- False wakeup counter
- Periodical forced wakeup supported (1s – 2h)
- Low power listening modes
- Current consumption in 3-channel listening mode 1.7  $\mu$ A (typ)
- Data rate adjustable from 0.5- 4 kbps (Manchester)
- Manchester decoding with clock recovery
- Digital RSSI values available for each channel
- Dynamic range 64dB
- 5 bit RSSI step (2dB per step)
- Clock Generator based on 32kHz XTAL, RC-OSC, or External Clock
- Operating temperature range -40 to +85°C
- Operating supply voltage 2.4 - 3.6V (TA = 25°C)
- Bidirectional serial peripheral interface (SPI)
- Package option: 16 pin TSSOP, QFN 4x4 16LD

#### 3 Applications

The AS3933 is ideal for Active RFID tags, Real-time location systems, Operator identification, Access control, and Wireless sensors.