



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



LMRx Antenna Cables

100Mx series, 195Mx series, 400Mx series

B+B SMARTWORX

Powered by

ADVANTECH

www.advantech-bb.com



N Male
Abbreviation: "NM"



RPSMA Plug
Abbreviation: "SL"



RPSMA Plug, Right Angle
Abbreviation: "SB"



RPSMA, Jack Bulkhead
Abbreviation: "SW"



RPSMA, Jack Bulkhead w/o Ring
Abbreviation: "SW1"



SMA Male
Abbreviation: "SM"



TNC Reverse Polarity Plug
Abbreviation: "TL"

FEATURES / BENEFITS


- + High quality, low loss LMRx
- + Use with high-gain antennas
- + Choice of connectors and cable lengths
- + Standards-based for critical performance
- + Ready to install

TIP: SELECTING THE RIGHT ANTENNA CABLE

The wrong cable, wrong impedance, or wrong length can take system performance down in a hurry. Long cable runs can cause additional signal loss so, it is wise to keep RF coaxial cable runs as short as possible.


Cable Type	Loss at 900 MHz - per 30.48 m (100 ft)	Loss at 2.4 GHz - per 30.48 m (100 ft)	Diameter
LMR100	22.8 dB	38.9 dB	0.110 in.
LMR195	11.5 dB	19.0 dB	1.195 in.
LMR400	3.9 dB	6.8 dB	0.405 in.

195M



50 Ohm, FPE dielectric, AL Tape+95% braid, PE jckt, .195" OD

400M



50 Ohm, FPE dielectric, AL Tape+95% braid, PE jacket, .405" OD

ORDERING INFORMATION

MODEL NUMBER	CONNECTOR 1	CONNECTOR 2	LENGTH	MATERIAL
100M-SBSW1-24	RPSMA Plug, Right Angle	RPSMA Jack Bulkhead, without ring	60.96 cm (2 ft)	LMR100
195M-NMSL-120	N Male	RPSMA Plug	3.05 m (10 ft)	LMR195
195M-NMSL-24	N Male	RPSMA Plug	60.96 cm (2 ft)	LMR195
195M-NMSL-240	N Male	RPSMA Plug	6.09 m (20 ft)	LMR195
195M-NMSL-48	N Male	RPSMA Plug	6.09 m (20 ft)	LMR195
195M-NMSL-9	N Male	RPSMA Plug	22.86 cm (9 in)	LMR195
195M-NMSM-24	N Male	SMA Male	60.96 cm (2 ft)	LMR195
195M-NMSM-240	N Male	SMA Male	6.09 m (20 ft)	LMR195
195M-NMSM-36	N Male	SMA Male	0.91 m (3 ft)	LMR195
195M-NMSM-60	N Male	SMA Male	1.52 m (5 ft)	LMR195
195M-SLSW-12	RPSMA Plug	RPSMA Jack Bulkhead	30.48 cm (1 ft)	LMR195
195M-SLSW-24	RPSMA Plug	RPSMA Jack Bulkhead	60.96 cm (2 ft)	LMR195
400M-NMNM-120	N Male	N Male	3.05 m (10 ft)	LMR400
400M-NMNM-1200	N Male	N Male	30.48 m (100 ft)	LMR400
400M-NMNM-240	N Male	N Male	6.09 m (20 ft)	LMR400
400M-NMNM-480	N Male	N Male	12.19 m (40 ft)	LMR400
400M-NMNM-600	N Male	N Male	15.24 m (50 ft)	LMR400
400M-NMSL-120	N Male	RPSMA Plug	3.05 m (10 ft)	LMR400
400M-NMSL-24	N Male	RPSMA Plug	60.96 cm (2 ft)	LMR400
400M-NMSL-240	N Male	RPSMA Plug	6.09 m (20 ft)	LMR400
400M-NMSL-600	N Male	RPSMA Plug	15.24 m (50 ft)	LMR400
400M-NMTL-24	N Male	TNC Reverse Polarity Plug	60.96 cm (2 ft)	LMR400

All product specifications are subject to change without notice.

100M-195M-400M-AntennaCables_5117ds