

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









CER0366A

1747.5 MHz Monoblock LR Series BPF

Features

- Low Ripple
- High Rejection
- Low Loss

Description

Surface mount, silver (Ag) coated ceramic filter. Developed for use in DCS repeater and base station applications, CTS Monoblock LR Series Filters are designed to minimize ripple and maximize rejection.

Weight: 9.5 grams typical

Material: Filter is composed of a ceramic block coated with Ag and a shield made of nickel silver plated steel.

Filter complies with RoHS standards.

Electrical Specifications



	Frequency	Typical @	Specification	Spec. over
Parameter	(MHz)	25ºC	@ 25ºC	-40°C to +85°C
Passband Insertion Loss	1710 - 1785	1.7 dB	2.2 dB	2.5 dB
Passband Ripple	1710 - 1785	0.6 dB	0.8 dB	1.0 dB
Passband Return Loss	1710 - 1785	15.0 dB	12.0 dB	12.0 dB
Attenuation:	1610 - 1690	34.0 dB	30.0 dB	30.0 dB
	1691 - 1700	12.5 dB	10.0 dB	10.0 dB
	1805 - 1880	28.5 dB	25.0 dB	25.0 dB
	2000 - 2200	33.0 dB	30.0 dB	30.0 dB
	2200 - 3000	23.0 dB	15.0 dB	18.0 dB
Power into any port		2 Watt max.		

Note: Supplier shall test each filter to the critical electrical specifications of the above table. Any subsequent audits may deviate from in value due to measurement repeatability among different test systems. Such deviations shall not exceed the following limits:

Specification Allowance

Insertion Loss 0.1 dB
Return Loss 1.0 dB
Stopbands 1.0 dB

^{*}This product is covered by one or more of the following U.S. and foreign patents including: US 4,692,726;US 4,742,562; US 4,800,348;US 4,829,274;US 5,146,193;EP 0573597;DE 0573597;FR 0573597;JP 508149/92;KR 142171;US 5,162,760;US 5,218,299;US 5,225,916;US 5,225,91

[•]CTS Corporation 2006 reserves all copyrights in the layout, design and configuration of the patterns on this product."




CER0366A

1747.5 MHz Monoblock LR Series BPF


Mechanical Drawing


Rev 3 - Origin Date: March 7, 2006 - Revision Date: August 3, 2007



Dim	Nominal (mm)	Tolerance (mm) +/- or max	
Α	32.5	max	
В	9.1	max	
С	2.03	0.13	
D	1.27	0.13	
E	1.27	0.13	
F	9.75	0.13	
G	9.75	0.13	
Н	8.44	max	
Ī	2.03	0.13	
J	11.3	max	
K	6.50	0.13	

Electrical response





Packaging and Marking



Under Construction