imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



PRODUCT DATASHEET

NiMH Battery Charger (CHUSB)

VERSATI LE

 Charges through the USB & wall outlet



FAST

Charges
2 AAA in 1.6 Hours
(900 mAh)
2 AA in 4.5 Hours
(2500 mAh)



FUN

 3 Fun colors available Green Blue Magenta



Duo Charger



Before Using Your Charger: Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer NiMH batteries.

North American Region Download Instructions and Warranty Information English | Français | Español

Product Detail:



Designation: Duo Charger Color: Black and Green, Blue or Magenta Capabilities: 1 to 2 "AA" NOTE: When charging a single battery, use bay (1) only 1 to 2 "AAA" Charging Current: Quick Charge 1-2 "AA-AAA" 550mA Slow Charge 1-2 "AA-AAA" 125mA Trickle Charge: 20-60mA Shutoff Mechanism: Delta V, Max Voltage and Timer Control Delta V Detection 10mV per cell Max Voltage 1.65V per cell Max Timer Control Quick Charge "AA" 5.5 hours Quick Charge "AAA" 1.5 hours Slow Charge "AA" No Timer Slow Charge "AAA" 10 hours Charger Input: Quick Charge DC 5V 500mA Slow Charge DC 5V 100mA AC Adapter Input: 100-240V AC 50/60Hz 150mA AC Adapter Output: DC 5V, 500mA Weight (charger): 68 grams (2.4 oz.) Dimensions (mm): $33 \times 101 \times 40$ (H x L x W) Safety Features: Delta V Charging Cut Off Max Voltage Shutoff **Reverse Polarity Protection** Primary Battery Detection

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication. © Energizer Holdings, I nc. Contents herein do not constitute a warranty.

