# mail

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



### Surface Mount Basic Pressure Sensors



#### Features

• 5 in H2O Full Sacale to 100 psi Full ScalePressures

sensors

alle

- 0.5 % linearity
- Small LCC Footprint
- ROHS Compliant

#### **Applications**

- Medical Instrumentation
- Environmental Controls
- HVAC

#### **General Description**

The BASIC Serices of pressure sensors use a silicon micromachined (MEMS) pressure sensor in the most basic configuration. The package is a ceramic surface mount configuration to provide the smallest footprint possible. Best temperature compensation is realized when the sensor has a constant current excitation. This series is intended for use with non-corrosive, non-ionic working fluids such as air, dry gases and the like. Specifications are written for constant voltage of 3.0 volts. The output of the device is ratiometric to the supply voltage.



DS-0165 Rev C

Pressure Sensor Characteristics Maximum Ratings		Environmental Specifications		
Supply Voltage VS	6 Vdc	Temperature Ranges		
Lead Temperature (soldering 2-4 sec.)	270°C	Operating	-25 to 85° C	
		Storage	-40 to 125° C	
		Humidity Limits	0 to 95% RH	
			(non condensing)	

#### Standard Pressure Ranges

Ported	Non-ported			Sensitivity (1)		
Part Number	Part Number	Operating Pressure	Nominal	Std Dev.	Units	Proof Pressure
CSM-L05G-LP	CSM-L05G-LF	0 - 5 inH2O	8.40	±1.10	mV/inH2O	3 PSI
CSM-L10G-LP	CSM-L10G-LF	0 - 10 inH2O	1.65	±0.19	mV/inH2O	3 PSI
CSM-001G-LP	CSM-001G-LF	0 - 1 PSI	22.8	±2.60	mV/PSI	5 PSI
CSM-005G-LP	CSM-005G-LF	0 - 5 PSI	12.0	±1.50	mV/PSI	15 PSI
CSM-015G-LP	CSM-015G-LF	0 - 15 PSI	4.40	±0.58	mV/PSI	45 PSI
CSM-015A-LP	CSM-015A-LF	0 - 15 PSIA	4.40	±0.58	mV/PSI	30 PSI
CSM-030G-LP	CSM-030G-LF	0 - 30 PSI	2.30	±0.30	mV/PSI	100 PSI
CSM-100G-LP	CSM-100G-LF	0 - 100 PSI	0.96	±0.13	mV/PSI	200 PSI

#### **Common Performance Characteristic**

Parameter <sup>(1)</sup>	Minimum	Nominal	Maximum	Units	
Offset Voltage		±1.0	±5.0	mv	
Temperature Effect on Offset <sup>(2)</sup>		±3		uV/V/°C	
Temperature Effect on Resistance (2,6)	2300	2600	3300	ppm/°C	
Temperature Effect on Span <sup>(2,6)</sup>	-1700	-2200	-2700	ppm/°C	
Linearity error <sup>(4,6)</sup>		±0.2	±0.5	% FSS	
Hysteresis error <sup>(6)</sup>		±0.01	±0.05	% FSS	
Position Sensitivity (BST-L10G-xx) <sup>(6)</sup>		±0.01	±0.03	% FSS	
Input Resistance <sup>(6)</sup>	2.7	3.3	4.0	kohms	
Output Resistance <sup>(6)</sup>	2.7	3.3	4.0	kohms	
Long term stability of span <sup>(3)</sup>		0.1		% FSS	

#### Specification Notes

NOTE 1: ALL PARAMETERS ARE MEASURED AT 3.0 VOLT EXCITATION, FOR THE NOMINAL FULL SCALE PRESSURE AND ROOM TEMPERATURE UNLESS OTHERWISE SPECIFIED. PRESSURE MEASUREMENTS ARE WITH POSITIVE PRESSURE TO THE SINGLE PORT CONFIGURATION.

NOTE 2: SHIFT IS RELATIVE TO 25°C.

NOTE 3: Shift is within the first year of operation.

NOTE 4: MEASURED AT ONE-HALF FULL SCALE RATED PRESSURE USING BEST STRAIGHT LINE CURVE FIT.

NOTE 5: THE SPAN IS THE ALGEBRAIC DIFFERENCE BETWEEN FULL SCALE OUTPUT VOLTAGE AND THE OFFSET VOLTAGE.

NOTE 6: PARAMETER IS CHARACTERIZED AND NOT 100% TESTED. MINIMUM AND MAXIMUM VALUES INDICATED AS A DESIGN REFERENCE.

All Sensors reserves the right to make changes to any products herein. All Sensors does not assume any liability arising out of the application or use of any product or circuit described herein, neither does it convey any license under its patent rights nor the rights of others.