



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Wireless Audio Processor with Tri-Band Support and Embedded Multi-Channel USB 2.0 Audio Controller

PRODUCT FEATURES

Data Brief

Highlights

- Single, dual and tri-band (2.4/5.2/5.8 GHz)
- 22 Mbps wireless air data rate
- Up to four uncompressed stereo audio channels
- Bi-directional audio support, allowing simultaneous RX and TX on a single device
- 16-24 bit, 44.1-96 kHz stereo audio transmission
- Integrated USB controller and PHY, offering wireless multi-channel audio
- Bi-directional data channel (up to 100 kbps)
- Point-to-point and point-to-multi-point support
- In-room range up to 50 m
- Video data transfer up to 10 Mbps
- Seamless RF band/channel switching
- Configurable, low latency audio, default at 18 ms
- Real-time Wi-Fi[®] sniffer
- Excellent Quality of Service (QoS)
- Low power consumption
- Single 3.3 V operation
- 129-pin, FBGA package

Target Applications

- Wireless subwoofers
- Wireless soundbars
- Fully wireless 5.1 and 7.1 home cinema applications
- Wireless headphones systems and headsets
- Wireless microphones
- Wireless USB audio dongles
- Automotive infotainment systems
- Digital televisions
- Set-top boxes
- Laptops
- Gaming systems
- Wireless home audio networks

Key Benefits

- High quality audio
 - Low latency of less than 20 ms, supporting wireless audio for video and gaming applications
 - Tight inter-speaker synchronization
 - Audio quality up to 24 bit, 96 kHz
 - Low latency compression algorithm, optimized for voice applications and headsets
- Wireless
 - Enhanced robustness against both in and out of band interferers, such as microwave ovens
 - Excellent coexistence with 802.11b/g/n Wi-Fi, cordless phones and Bluetooth[®], even when collocated in the same device
 - Automatic receiver antenna diversity minimizing fading and multi-path effects
 - Link quality monitoring
 - Soft audio muting under poor link circumstances
 - Automatic TX output power control, minimizing RF footprint
- Networking and Connectivity
 - Supports multi-room network topologies
 - Bi-directional audio
 - Simple pairing and association functions
 - Control data communications between devices up to 100 kbps
 - Backwards compatible to all application modes of previous DARR generations including DARR80, 81 and 82
- Interfacing and Integration
 - Quad I²S[™] or stereo S/PDIF input/output
 - Master and Slave I²C[™] bus for external control functions
 - Integrated SRC and MCU
 - Integrated USB2.0 Controller and PHY, offering a bi-directional, multi channel USB audio interface
- Optimized pre-certified modules available¹

1. For more information, refer to www.smSC.com or your local sales contact.



SMSC[®]

Wireless Audio Processor with Tri-Band Support and Embedded Multi-Channel USB 2.0 Audio Controller

Order Number(s):

DARR83 for 129-pin FBGA package, RoHS-compliant package

This product meets the halogen maximum concentration values per IEC61249-2-21

For RoHS compliance and environmental information, please visit www.smSC.com/rohs



SMSC[®]

80 ARKAY DRIVE, HAUPPAUGE, NY 11788 (631) 435-6000, FAX (631) 273-3123

Copyright © 2011 SMSC or its subsidiaries. All rights reserved.

Circuit diagrams and other information relating to SMSC products are included as a means of illustrating typical applications. Consequently, complete information sufficient for construction purposes is not necessarily given. Although the information has been checked and is believed to be accurate, no responsibility is assumed for inaccuracies. SMSC reserves the right to make changes to specifications and product descriptions at any time without notice. Contact your local SMSC sales office to obtain the latest specifications before placing your product order. The provision of this information does not convey to the purchaser of the described semiconductor devices any licenses under any patent rights or other intellectual property rights of SMSC or others. All sales are expressly conditional on your agreement to the terms and conditions of the most recently dated version of SMSC's standard Terms of Sale Agreement dated before the date of your order (the "Terms of Sale Agreement"). The product may contain design defects or errors known as anomalies which may cause the product's functions to deviate from published specifications. Anomaly sheets are available upon request. SMSC products are not designed, intended, authorized or warranted for use in any life support or other application where product failure could cause or contribute to personal injury or severe property damage. Any and all such uses without prior written approval of an Officer of SMSC and further testing and/or modification will be fully at the risk of the customer. Copies of this document or other SMSC literature, as well as the Terms of Sale Agreement, may be obtained by visiting SMSC's website at <http://www.smSC.com>. SMSC is a registered trademark of Standard Microsystems Corporation ("SMSC"). Product names and company names are the trademarks of their respective holders.

SMSC DISCLAIMS AND EXCLUDES ANY AND ALL WARRANTIES, INCLUDING WITHOUT LIMITATION ANY AND ALL IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, TITLE, AND AGAINST INFRINGEMENT AND THE LIKE, AND ANY AND ALL WARRANTIES ARISING FROM ANY COURSE OF DEALING OR USAGE OF TRADE. IN NO EVENT SHALL SMSC BE LIABLE FOR ANY DIRECT, INCIDENTAL, INDIRECT, SPECIAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES; OR FOR LOST DATA, PROFITS, SAVINGS OR REVENUES OF ANY KIND; REGARDLESS OF THE FORM OF ACTION, WHETHER BASED ON CONTRACT; TORT; NEGLIGENCE OF SMSC OR OTHERS; STRICT LIABILITY; BREACH OF WARRANTY; OR OTHERWISE; WHETHER OR NOT ANY REMEDY OF BUYER IS HELD TO HAVE FAILED OF ITS ESSENTIAL PURPOSE, AND WHETHER OR NOT SMSC HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

General Description

SMSC's DARR83 enables a wide range of digital wireless audio applications. It offers a high level of integration resulting in a very low-cost complete wireless system solution, without any sacrifice to the main technology drivers: Audio Quality and Wireless Fidelity.

From a high-level perspective the DARR83 consists of a number of function blocks, each connected through an internal parallel bus, see [Figure 1](#). The core wireless audio functionality of the DARR83 is implemented in the following top function blocks:

- Audio
- Data Link
- PHY

The Audio function block forms the interface between on the left side the audio interfaces, such as S/PDIF and I²S, and on the right side the audio buffers for the Data Link. The Audio function block takes care of all functions related to audio buffering, audio routing, audio integrity, sample clock synchronization, sample rate conversion and volume control.

The Data Link packs the data when transmitting the audio information into a data stream, directly suitable for modulation by the PHY. When receiving the data, the Data Link block performs the unpacking and verification of the wireless packets. The Data Link also takes care of the exact timing of all the wireless activities. Additionally, it performs the control data messaging.

The PHY performs the digital modulation and demodulation and controls the external radio chip. This includes D/A and A/D conversion. The PHY can operate in each of the following three ISM bands: 2.4, 5.2 and 5.8 GHz. Within each of these bands three non-overlapping channels are available. The PHY facilitates seamless switching between each of the channels and bands, dynamically optimizing the RF footprint for the actual wireless environment.

The USB2.0 PHY and controller are directly connected to the Audio function block to ensure the seamless flow of audio and bulk data. The USB controller is directly controlled by the microcontroller.

The microcontroller of the DARR83 integrates an 8052 MCU as well as an 8 kbytes data RAM, 1 kbyte of program ROM and 45 kbytes program RAM. The MCU is used to configure and monitor the wireless audio core processes.

The Control I/O function block is used for serial communication and incorporates a UART as well as an I²C master and slave interface. The I²C master interface is used when the DARR83 is the controlling device in the application. If the DARR83 is controlled by an other host controller, the I²C slave interface is used.

The Peripherals and Clock function block contains the supporting functions for the chip and includes a crystal oscillator, clock generator, power management unit, auxiliary ADC, RC clock oscillator, General Purpose I/O and a voltage regulator.

Block Diagram




Figure 1 Internal Block Diagram

Package Outline




Figure 2 129-FBGA Package Definition

Table 1 129-FBGA Dimensions

SYMBOL	MILLIMETER			INCH		
	MIN	NOM	MAX	MIN	NOM	MAX
A	0.99	1.10	1.21	.039	.043	.048
A1	0.20	0.24	0.28	.008	.009	.011
A2	0.32	0.36	0.40	.013	.014	.016
A3	0.47	0.50	0.53	.019	.020	.021
b	0.25	0.30	0.35	.010	.012	.014
D	6.90	7.00	7.10	.272	.276	.280
D1	6.00 BSC			.236 BSC		
E	6.90	7.00	7.10	.272	.276	.280
E1	6.00 BSC			.236 BSC		
e	0.50 BSC			.197 BSC		
f	0.40	0.50	0.60	.016	.020	.024

Notes:

1. Dimensions and tolerances per ASME Y14.5M-1994
2. Controlling dimensions are in mm.
3. Details of A1 corners are optional and may consist of ink dot, laser mark or metallized marking, but must be located within the zone indicated.
4. Solder balls are normally a tin lead solder or lead free solder.
5. Refer to JEDEC Outline MO-195 for datums. Features and dimensions are not shown.
6. Primary datum C and seating place are defined by the spherical crowns of the solder balls.