



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# Fluke 715 mA Loop Calibrators

## Technical Data

### Fluke 715 Volt/mA Calibrator

#### Volt Milliamp Calibrator to troubleshoot process loops

The Fluke 715 Volt/mA Calibrator delivers outstanding performance, durability and reliability. Offered in the rugged Fluke 80 Series DMM package, the calibrator is compact, lightweight and easy to carry. With a push button interface similar to the multifunction Fluke 740 Series Documenting Process Calibrators, the 715 is easy to use. It is EMI tolerant, dust/splash resistant and features a removable battery door for quick battery changes. It features:

- Measure loop current (0 mA to 20 mA, 4 mA to 20 mA) signals with 0.01 % accuracy and 0.001 mA resolution
- Source precision voltage signals up to 20 V with 0.01 % accuracy
- Measure voltage output process signals from PLCs, transmitters
- Source or simulate 24 mA loop current
- 24 V loop supply with simultaneous current measurement

### Fluke 707 Loop Calibrator

#### The fastest, one-handed tool for loop checks

The Fluke 707 Loop Calibrator is a high performance solution for calibration, repair and maintenance of current loops. The "Quick Click" knob makes it extremely fast and easy to use. It features:

- One handed user interface with "Quick Click" detented knob
- mA sourcing, simulation and measurement
- 0.015 % accuracy and 0.001 mA resolution
- Simultaneous mA and % of span display
- Selectable step or ramp outputs
- 24 V Loop supply with mA measure, including 250 Ω HART resistor
- 0 V dc to 28 V dc measurement to check Loop Voltage
- Removable battery door for quick battery replacement
- Compact case with protective holster
- Three year warranty

### Fluke 705 Loop Calibrator

#### Low cost calibration muscle

The Fluke 705 Loop Calibrator is a cost-effective, integrated solution for calibration, repair and maintenance of current loops. It features:

- mA sourcing, simulation and measurement
- 0.02 % accuracy and 0.001 mA resolution
- Simultaneous mA and % of span display
- Selectable step or ramp outputs
- 24 V Loop supply with mA measure
- 0 V dc to 28 V dc measurement to check Loop Voltage
- Removable battery door for quick battery replacement
- Compact case with protective holster
- Three-year warranty



## General Specifications:

**Maximum voltage:** 30 volts: Non-operating temperature: -4 °C to 60 °C

**Operating temperature:** -10 °C to 55 °C

**Relative humidity:** 95 % (10 °C to 30 °C); 75 % (30 °C to 40 °C); 45 % (40 °C to 50 °C); 35 % (50 °C to 55 °C)

**Operating altitude:** 3,000 m max

**Shock:** 1 m drop test

**Vibration:** Random, 2 g, 5 Hz to 500 Hz

**Safety:** CSA C22.2 No. 1010.1:1992

**EMC:** EN50082-1:1992 and EN55022:1994 Class B

**Power:** 9 V battery ANSI/NEDA 1604A or IEC 6LR619V alkaline; two batteries in 718

**Warranty:** Three-years

Functional Specifications:	Fluke 705 and 707	Fluke 715
<b>Voltage measurement</b>		
Range	0 V to 28 V	0 mV to 200 mV / 0 V to 25 V
Resolution	1 mV	10 µV / 1 mV
Accuracy	705: 0.025 % Rdg + 1 counts 707, 707Ex: 0.015 % Rdg + 2 counts	0.01 % Rdg + 2 counts
<b>Current measurement</b>		
Range	0 mA to 24 mA	0 mA to 24 mA
Resolution	0.001 mA	0.001 mA
Accuracy	705: 0.02 % Rdg + 2 counts 707, 707Ex: 0.015 % Rdg + 2 counts	0.01 % + 2 counts
<b>Current sourcing</b>		
Range	0 mA to 20 mA or 4 mA to 20 mA	0 mA to 20 mA or 4 mA to 20 mA
Accuracy	705: 0.02 % Rdg + 2 counts 707, 707Ex: 0.015 % Rdg + 2 counts	0.01 % Rdg + 2 counts
Drive capability	705: 1000 Ω @ 24 mA 707: 1200 Ω @ 24 mA 707Ex: 700 Ω @ 20 mA	1000 Ω @ 24 mA
Loop power while measuring mA	24 V	24 V
Voltage sourcing	n/a	0 mV to 200 mV or 0 V to 20 V
Display current and % of span	Yes	mA or %
Auto step, auto ramp	Yes	Yes
Span Check	Yes	Yes
Battery life	18 hours typical, at 12 mA	18 hours typical, at 12 mA

**Fluke.** *Keeping your world  
up and running.*

**Fluke Corporation**  
PO Box 9090, Everett, WA USA 98206

Fluke Europe B.V.  
PO Box 1186, 5602 BD  
Eindhoven, The Netherlands

For more information call:  
In the U.S.A. (800) 443-5853 or  
Fax (425) 446-5116  
In Europe/M-East/Africa (31 40) 2 675 200 or  
Fax (31 40) 2 675 222  
In Canada (800) 36-FLUKE or  
Fax (905) 890-6866  
From other countries +1 (425) 446-5500 or  
Fax +1 (425) 446-5116  
Web access: <http://www.fluke.com>