

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China


SOT23 NPN SILICON PLANAR SWITCHING TRANSISTORS

ISSUE 2 – SEPTEMBER 94

FMMT3903 FMMT3904

COMPLIMENTARY TYPES – FMMT3903 - FMMT3905
FMMT3904 - FMMT3906

PARTMARKING DETAIL – FMMT3903 - 1W
FMMT3904 - 1A



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	60	V
CollectorEmitter Voltage	V_{CEO}	40	V
EmitterBase Voltage	V_{EBO}	6	V
Continuous Collector Current	I_C	200	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	FMMT3903		FMMT3904		UNIT	CONDITIONS.
		MIN.	MAX.	MIN.	MAX.		
Collector Base Breakdown Voltage	$V_{(BR)CBO}$	60		60		V	$I_C=10\mu A, I_E=0$
CollectorEmitter Breakdown Voltage	$V_{(BR)CEO}$	40		40		V	$I_C=1mA, I_B=0^*$
EmitterBase Breakdown Voltage	$V_{(BR)EBO}$	6		6		V	$I_E=10\mu A, I_C=0$
CollectorEmitter CutOff Current	I_{CEX}		50		50	nA	$V_{CE}=30V, V_{BE(off)}=3V$
Base CutOff Current	I_{BEX}		50		50	nA	$V_{CE}=30V, V_{EB(off)}=3V$
Static Forward Current Transfer Ratio	h_{FE}	20 35 50 30 15	150	40 70 100 60 30	300		$I_C=0.1mA, V_{CE}=1V^*$ $I_C=1mA, V_{CE}=1V^*$ $I_C=10mA, V_{CE}=1V^*$ $I_C=50mA, V_{CE}=1V^*$ $I_C=100mA, V_{CE}=1V^*$
CollectorEmitter Saturation Voltage	$V_{CE(sat)}$		0.2 0.3		0.2 0.3	V	$I_C=10mA, I_B=1mA^*$ $I_C=50mA, I_B=5mA^*$
BaseEmitter Saturation Voltage	$V_{BE(sat)}$	0.65	0.85 0.95	0.65	0.85 0.95	V	$I_C=10mA, I_B=1mA^*$ $I_C=50mA, I_B=5mA^*$
Transition Frequency	f_T	250		300		MHz	$I_C=10mA, V_{CE}=20V$ $f=100MHz$
Output Capacitance	C_{obo}		4		4	pF	$V_{CB}=5V, I_E=0, f=100KHz$
Input Capacitance	C_{ibo}		8		8	pF	$V_{BE}=0.5V, I_C=0, f=100KHz$



FMMT3903

FMMT3904

SWITCHING CHARACTERISTICS (at $T_{amb} = 25^{\circ}\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	FMMT3903		FMMT3904		UNIT	CONDITIONS.
		MIN.	MAX.	MIN.	MAX.		
Noise Figure	N		6		5	dB	$V_{CE}=5\text{V}$ $I_C=200\mu\text{A}$, $R_g=2\text{K}\Omega$ $f=30\text{Hz}$ to 15KHz at -3dB points
Delay Time	t_d		35		35	ns	$V_{CC}=3\text{V}$, $I_C=10\text{mA}$, $I_{B1}=1\text{mA}$ $V_{BE(off)}=0.5\text{V}$ (See Figure1)
Rise Time	t_r		35		35	ns	
Storage Time	t_s		175		200	ns	$V_{CC}=3\text{V}$, $I_C=10\text{mA}$ $I_{B1}=I_{B2}=1\text{mA}$ (See Figure2)
Fall Time	t_f		50		50	ns	

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$



ZETEX

Zetex plc.
Fields New Road, Chadderton, Oldham, OL9-8NP, United Kingdom.
Telephone: (44)161 622 4422 (Sales), (44)161 622 4444 (General Enquiries)
Fax: (44)161 622 4420

Zetex GmbH
Streitfeldstraße 19
D-81673 München
Germany
Telefon: (49) 89 45 49 49 0
Fax: (49) 89 45 49 49 49

Zetex Inc.
47 Mall Drive, Unit 4
Commack NY 11725
USA
Telephone: (631) 543-7100
Fax: (631) 864-7630

Zetex (Asia) Ltd.
3701-04 Metroplaza, Tower 1
Hing Fong Road,
Kwai Fong, Hong Kong
Telephone: (852) 26100 611
Fax: (852) 24250 494

These are supported by
agents and distributors in
major countries world-wide
© Zetex plc 2000

Internet: <http://www.zetex.com>

This publication is issued to provide outline information only which (unless agreed by the Company in writing) may not be used, applied or reproduced for any purpose or form part of any order or contract or be regarded as a representation relating to the products or services concerned. The Company reserves the right to alter without notice the specification, design, price or conditions of supply of any product or service.