



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




G3VM-□BR□/□ER□

MOS FET Relays DIP 6-pin, High-current and Low-ON-resistance Type

MOS FET Relays in DIP 6-pin packages that achieve the low ON resistance and high switching capacity of a mechanical relay

- Load voltage: 20 V, 40 V, 60 V, or 100 V
- 20-V Relay: Continuous load current of 4 A (8 A) max. *
- 40-V Relay: Continuous load current of 3.5 A (7 A) max. *
- 60-V G3VM-61BR/ER Relay: Continuous load current of 2.5 A max.
- 60-V G3VM-61BR1/ER1 Relay: Continuous load current of 3 A (6 A) max. *
- 100-V Relay: Continuous load current of 2 A (4 A) max. *

* Values in parentheses are for connection C.



Note: The actual product is marked differently from the image shown here.


RoHS Compliant

Application Examples


- Communication equipment
- Security equipment
- Power circuit
- Test & Measurement equipment
- Industrial equipment

Package (Unit : mm, Average)

DIP 6-pin
PCB Terminals



Surface-mounting Terminals



Note: The actual product is marked differently from the image shown here.

Model Number Legend

G3VM-□□□□□
1 2 3 4 5

- Load Voltage**
2 : 20 V
4 : 40 V
6 : 60 V
10 : 100 V
- Contact form**
1 : 1a (SPST-NO)
- Package**
B : DIP 6-pin with PCB terminals
E : DIP 6-pin with surface-mounting terminals
- Additional functions**
R: Low ON resistance
- Other informations**
When specifications overlap, serial code is added in the recorded order.

Ordering Information

Package	Contact form	Load voltage (peak value) *	Continuous load current (peak value) *		Stick packaging			Tape packaging		
			Connection A, B	Connection C	PCB Terminals	Model	Surface-mounting Terminals	Minimum package quantity	Model	Surface-mounting Terminals
DIP6	1a (SPST-NO)	20 V	4 A	8 A	G3VM-21BR	G3VM-21ER	50 pcs.	50 pcs.	G3VM-21ER(TR)	1,500 pcs.
		40 V	3.5 A	7 A	G3VM-41BR	G3VM-41ER			G3VM-41ER(TR)	
		60 V	2.5 A	—	G3VM-61BR	G3VM-61ER			G3VM-61ER(TR)	
			3 A	6 A	G3VM-61BR1	G3VM-61ER1			G3VM-61ER1(TR)	
100 V	2 A	4 A	G3VM-101BR	G3VM-101ER	G3VM-101ER(TR)					

* The AC peak and DC value are given for the load voltage and continuous load current.


Note: To order tape packaging for Relays with surface-mounting terminals, add "(TR)" to the end of the model number.

■ Absolute Maximum Ratings (Ta = 25°C)

Item		Symbol	G3VM-21BR G3VM-21ER	G3VM-41BR G3VM-41ER	G3VM-61BR G3VM-61ER	G3VM-61BR1 G3VM-61ER1	G3VM-101BR G3VM-101ER	Unit	Measurement conditions	
Input	LED forward current	IF	30						mA	
	Repetitive peak LED forward current	IFP	1						A	100 μs pulses, 100 pps
	LED forward current reduction rate	ΔIf/°C	-0.3						mA/°C	Ta ≥ 25°C
	LED reverse voltage	VR	5						V	
	Connection temperature	TJ	125						°C	
Load voltage (AC peak/DC)		V _{OFF}	20	40	60		100	V		
Output	Continuous load current	Connection A	Io	4	3.5	2.5	3	2	A	Connection A: AC peak/DC Connection B and C: DC
		Connection B		8	7	-	6	4		
		Connection C								
	ON current reduction rate	Connection A	ΔIo/°C	-40	-35	-22	-30	-20	mA/°C	Ta ≥ 25°C
		Connection B		-80	-70	-	-60	-40		
Connection C										
Pulse ON current	I _{op}	12	10.5	7.5	9	6	A	t _{on} =100 ms, Duty=1/10		
Connection temperature	TJ	125						°C		
Dielectric strength between I/O (See note 1.)		V _{I-O}	2,500						V _{rms}	AC for 1 min
Ambient operating temperature		Ta	-40 to +85		-20 to +85		-40 to +85		°C	With no icing or condensation
Ambient storage temperature		Tstg	-55 to +125		-40 to +125		-55 to +125		°C	
Soldering temperature		-	260						°C	10 s

Note: 1. The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side.

Connection Diagram




Note: Only connection A can be used for the G3VM-61BR/ER.

Introduction
General purpose
High-side-voltage
Multi-contact pair (2a, 2b, and 1a1)
High-current and Low-ON-resistance
Small and High-dielectric-strength
High-dielectric-current-limiting
Low-ohmic-resistance and low-threshold
Small and High-side-voltage
Certified Models with Standards Certification
DIP
SOP
SSOP
USOP
VSON
G3VM-□BR□/□ER□

■Electrical Characteristics (Ta = 25°C)

Item		Symbol	G3VM-21BR G3VM-21ER	G3VM-41BR G3VM-41ER	G3VM-61BR G3VM-61ER	G3VM-61BR1 G3VM-61ER1	G3VM-101BR G3VM-101ER	Unit	Measurement conditions			
Input	LED forward voltage	V _F	Minimum					1.18	V	I _F =10 mA		
			Typical					1.33				
			Maximum					1.48				
	Reverse current	I _R	Maximum					10			μA	V _R =5 V
Capacitance between terminals	C _T	Typical					70	pF	V=0, f=1 MHz			
Trigger LED forward current	I _{FT}	Typical	0.5		1	0.5		mA	I _O =1 A			
		Maximum	3									
Release LED forward current	I _{FC}	Minimum	0.1					mA	I _{OFF} =10 μA			
Output	Maximum resistance with output ON	R _{ON}	Connection A	Typical		20	30	65	40	100	mΩ	G3VM-21BR/21ER/41BR/41ER/ 61BR1/61ER1/101BR/101ER : I _F =5 mA, R _L =200 Ω, I _O =2 A (Connection A and B), I _O =4 A (Connection C), t<1 s G3VM-61BR/ER : I _F =10 mA, t=10 ms, I _O =2 A
				Maximum		50	60	100	70	200		
				Connection B	Typical		10	15	-			
	Connection C	Typical			5	8	-		10	25		
Current leakage when the relay is open		I _{LEAK}	Typical	-		0.001		-		μA	V _{OFF} =Load voltage ratings	
			Maximum	1		0.01		1				
Capacitance between terminals	C _{OFF}	Typical	1000		400		1000		pF	V=0, f=1 MHz		
Capacitance between I/O terminals	C _{I-O}	Typical	0.8					pF	f=1 MHz, V _S =0 V			
Insulation resistance between I/O terminals	R _{I-O}	Minimum	1000					MΩ	V _{I-O} =500 VDC, R _{oH} ≤60%			
		Typical	10 ⁹									
Turn-ON time	t _{ON}	Typical	2.5	2	1	2		ms	G3VM-21BR/21ER/41BR/41ER/ 61BR1/61ER1/101BR/101ER : I _F =5 mA, R _L =200 Ω, V _{DD} =20 V (See note 2.) G3VM-61BR/ER : I _F =10 mA, R _L =200 Ω, V _{DD} =20 V (See note 2.)			
		Maximum	5		1.5		5					
Turn-OFF time	t _{OFF}	Typical	0.1		0.2		0.1					
		Maximum	1		0.4		1					

Note: 2. Turn-ON and Turn-OFF Times



■Recommended Operating Conditions

For usage with high reliability, Recommended Operation Conditions is a measure that takes into account the derating of Absolute Maximum Ratings and Electrical Characteristics.

Each item on this list is an independent condition, so it is not simultaneously satisfy several conditions.

Item	Symbol	G3VM-21BR G3VM-21ER	G3VM-41BR G3VM-41ER	G3VM-61BR G3VM-61ER	G3VM-61BR1 G3VM-61ER1	G3VM-101BR G3VM-101ER	Unit		
Load voltage (AC peak/DC)	V _{DD}	Maximum		16	32	48	80	V	
Operating LED forward current	I _F	Minimum		5		10		5	
		Typical		10		-		10	
		Maximum		25		20		25	
Continuous load current (AC peak/DC)	I _O	Maximum		4	3.5	2.5	3	2	A
		Minimum		-					-20
Ambient operating temperature	T _a	Minimum		-					-20
		Maximum		65		60		65	


■Spacing and Insulation

Item	Minimum	Unit
Creepage distances	7.0	mm
Clearance distances	7.0	
Internal isolation thickness	0.4	


Engineering Data

LED forward current vs. Ambient temperature


G3VM-21BR/21ER/41BR/41ER/
61BR1/61ER1/101BR/101ER



G3VM-61BR/61ER




LED forward current vs. LED forward voltage




Continuous load current vs. Ambient temperature


G3VM-21BR/21ER/41BR/41ER




G3VM-61BR1/61ER1/101BR/101ER




G3VM-61BR/61ER




Continuous load current vs. On-state voltage



On-state resistance vs. Ambient temperature



Trigger LED forward current vs. Ambient temperature




Introduction
 General purpose
 High-load-voltage
 Multi-contact pair
 Low-V_{ON} resistance
 High-current and
 High-dielectric
 Small and high-
 High-dielectric-
 High-dielectric-
 Current-limiting
 Low-on-state-resistance
 Small and High-
 Certified Models with
 SOP
 SSOP
 USOP
 VSON
 G3VM-□BR□/□ER□


Engineering Data

● Turn ON, Turn OFF time vs. LED forward current

G3VM-21BR/21ER/41BR/41ER




G3VM-61BR/61ER/61BR1/61ER1/101BR/101ER




● Turn ON, Turn OFF time vs. Ambient temperature


G3VM-21BR/21ER/41BR/41ER



G3VM-61BR/61ER/61BR1/61ER1/101BR/101ER



● Current leakage vs. Ambient temperature




Appearance / Terminal Arrangement / Internal Connections

● Appearance

DIP (Dual Inline Package)


DIP 6-pin

G3VM-21BR/ER, -41BR/ER, -61BR1/ER1, -101BR/ER




Special DIP 6-pin *

G3VM-61BR/ER




● Terminal Arrangement/Internal Connections (Top View)

G3VM-21BR/ER, -41BR/ER, -61BR1/ER1, -101BR/ER



G3VM-61BR/ER



Note: 1. The actual product is marked differently from the image shown here.

Note: 2. "G3VM" does not appear in the model number on the Relay.

Note: 3. The indentation in the corner diagonally opposite from the pin 1 mark is from a pin on the mold.

* The external dimensions of the standard DIP 6-pin are the same, but the number of terminals is different.



■Dimensions (Unit: mm)

G3VM-21BR/41BR/61BR1/101BR



PCB Terminals

Weight: 0.4 g





G3VM-21ER/41ER/61ER1/101ER




Surface-mounting Terminals


Weight: 0.4 g



PCB Dimensions (BOTTOM VIEW)



Actual Mounting Pad Dimensions (Recommended Value, Top View)





Note: The actual product is marked differently from the image shown here.

G3VM-61BR



PCB Terminals

Weight: 0.4 g





G3VM-61ER




Surface-mounting Terminals


Weight: 0.4 g



PCB Dimensions (BOTTOM VIEW)



Actual Mounting Pad Dimensions (Recommended Value, Top View)



Note: The actual product is marked differently from the image shown here.

■Approved Standards

UL recognized

Approved Standards	Contact form	File No.
UL (recognized)	1a (SPST-NO)	E80555

■Safety Precautions

- Refer to the *Common Precautions for All MOS FET Relays* for precautions that apply to all MOS FET Relays.

Introduction
General-purpose
High-head-voltage
Multi-contact pair
High-current and
Low-ON-resistance
Small and high-
dielectric-strength
High-dielectric-
strength
Current-limiting
Low-ON-resistance
and ON-voltage
Small and High-
dielectric-strength
Certified models with
UL certification
DIP
SOP
SSOP
USOP
VSON
G3VM-□BR□/□ER□