



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China


IR2181(4)(S) & (PbF)

HIGH AND LOW SIDE DRIVER

Features

- Floating channel designed for bootstrap operation
Fully operational to +600V
Tolerant to negative transient voltage
 dV/dt immune
 - Gate drive supply range from 10 to 20V
 - Undervoltage lockout for both channels
 - 3.3V and 5V input logic compatible
 - Matched propagation delay for both channels
 - Logic and power ground +/- 5V offset.
 - Lower di/dt gate driver for better noise immunity
 - Output source/sink current capability 1.4A/1.8A
 - Also available LEAD-FREE (PbF)

Packages




IR2181/IR2183/IR2184 Feature Comparison

Description

Part	logic	prevention logic	Dead-time	Ground Pins	I _{on} /I _{off}
2181	HIN/LIN	no	none	COM	180/220 ns
21814				VSS/COM	
2183	HIN/LIN	yes	Internal 500ns	COM	180/220 ns
21834			Program 0.4 ~ 5 us	VSS/COM	
2184	IN/S ^D	yes	Internal 500ns	COM	680/270 ns
21844			Program 0.4 ~ 5 us	VSS/COM	

Part	Input logic	Cross-conduction prevention logic	Dead-Time	Ground Pins	Ton/Toff
2181	HIN/LIN	no	none	COM	180/220 ns
21814				VSS/COM	
2183	HIN/ <u>LIN</u>	yes	Internal 500ns	COM	180/220 ns
21834			Program 0.4 ~ 5 us	VSS/COM	
2184	IN/ <u>SD</u>	yes	Internal 500ns	COM	680/270 ns
21844			Program 0.4 ~ 5 us	VSS/COM	

Typical Connection



IR2181(4) (S) & (PbF)

International
IR Rectifier

Absolute Maximum Ratings

Absolute maximum ratings indicate sustained limits beyond which damage to the device may occur. All voltage parameters are absolute voltages referenced to COM. The thermal resistance and power dissipation ratings are measured under board mounted and still air conditions.

Symbol	Definition	Min.	Max.	Units
V_B	High side floating absolute voltage	-0.3	625	V
V_S	High side floating supply offset voltage	$V_B - 25$	$V_B + 0.3$	
V_{HO}	High side floating output voltage	$V_S - 0.3$	$V_B + 0.3$	
V_{CC}	Low side and logic fixed supply voltage	-0.3	25	
V_{LO}	Low side output voltage	-0.3	$V_{CC} + 0.3$	
V_{IN}	Logic input voltage (HIN & LIN - IR2181/IR21814)	$V_{SS} - 0.3$	$V_{SS} + 10$	
V_{SS}	Logic ground (IR21814 only)	$V_{CC} - 25$	$V_{CC} + 0.3$	
dV_S/dt	Allowable offset supply voltage transient	—	50	V/ns
P_D	Package power dissipation @ $T_A \leq +25^\circ\text{C}$	(8-lead PDIP)	—	1.0
		(8-lead SOIC)	—	0.625
		(14-lead PDIP)	—	1.6
		(14-lead SOIC)	—	1.0
R_{thJA}	Thermal resistance, junction to ambient	(8-lead PDIP)	—	125
		(8-lead SOIC)	—	200
		(14-lead PDIP)	—	75
		(14-lead SOIC)	—	120
T_J	Junction temperature	—	150	$^\circ\text{C}$
T_S	Storage temperature	-50	150	
T_L	Lead temperature (soldering, 10 seconds)	—	300	

Recommended Operating Conditions

The Input/Output logic timing diagram is shown in figure 1. For proper operation the device should be used within the recommended conditions. The V_S and V_{SS} offset rating are tested with all supplies biased at 15V differential.

Symbol	Definition	Min.	Max.	Units
V_B	High side floating supply absolute voltage	$V_S + 10$	$V_S + 20$	V
V_S	High side floating supply offset voltage	Note 1	600	
V_{HO}	High side floating output voltage	V_S	V_B	
V_{CC}	Low side and logic fixed supply voltage	10	20	
V_{LO}	Low side output voltage	0	V_{CC}	
V_{IN}	Logic input voltage (HIN & LIN - IR2181/IR21814)	V_{SS}	$V_{SS} + 5$	
V_{SS}	Logic ground (IR21814/IR21824 only)	-5	5	
T_A	Ambient temperature	-40	125	$^\circ\text{C}$

Note 1: Logic operational for V_S of -5 to +600V. Logic state held for V_S of -5V to $-V_{BS}$. (Please refer to the Design Tip DT97-3 for more details).

Note 2: HIN and LIN pins are internally clamped with a 5.2V zener diode.

Dynamic Electrical Characteristics



V_{BIAS} (V_{CC} , V_{BS}) = 15V, V_{SS} = COM, C_L = 1000 pF, T_A = 25°C.

Symbol	Definition	Min.	Typ.	Max.	Units	Test Conditions
t_{on}	Turn-on propagation delay	—	180	270	nsec	V_S = 0V
t_{off}	Turn-off propagation delay	—	220	330		V_S = 0V or 600V
MT	Delay matching, HS & LS turn-on/off	—	0	35		
t_r	Turn-on rise time	—	40	60		V_S = 0V
t_f	Turn-off fall time	—	20	35		V_S = 0V

Static Electrical Characteristics

V_{BIAS} (V_{CC} , V_{BS}) = 15V, V_{SS} = COM and T_A = 25°C unless otherwise specified. The V_{IH} , V_{IL} and I_{IN} parameters are referenced to V_{SS} /COM and are applicable to the respective input leads HIN and LIN. The V_O , I_O and R_{on} parameters are referenced to COM and are applicable to the respective output leads: HO and LO.


Symbol	Definition	Min.	Typ.	Max.	Units	Test Conditions
V_{IH}	Logic "1" input voltage (IR2181/IR21814)	2.7	—	—	V	V_{CC} = 10V to 20V
V_{IL}	Logic "0" input voltage (IR2181/IR21814)	—	—	0.8		V_{CC} = 10V to 20V
V_{OH}	High level output voltage, V_{BIAS} - V_O	—	—	1.2		I_O = 0A
V_{OL}	Low level output voltage, V_O	—	—	0.1		I_O = 0A
I_{LK}	Offset supply leakage current	—	—	50		V_B = V_S = 600V
I_{QBS}	Quiescent V_{BS} supply current	20	60	150	μA	V_{IN} = 0V or 5V
I_{QCC}	Quiescent V_{CC} supply current	50	120	240		V_{IN} = 0V or 5V
I_{IN+}	Logic "1" input bias current	—	25	60		V_{IN} = 5V
I_{IN-}	Logic "0" input bias current	—	—	1.0		V_{IN} = 0V
V_{CCUV+} V_{BSUV+}	V_{CC} and V_{BS} supply undervoltage positive going threshold	8.0	8.9	9.8	V	
V_{CCUV-} V_{BSUV-}	V_{CC} and V_{BS} supply undervoltage negative going threshold	7.4	8.2	9.0		
V_{CCUVH} V_{BSUVH}	Hysteresis	0.3	0.7	—		
I_{O+}	Output high short circuit pulsed current	1.4	1.9	—	A	V_O = 0V, $PW \leq 10 \mu s$
I_{O-}	Output low short circuit pulsed current	1.8	2.3	—		V_O = 15V, $PW \leq 10 \mu s$



Functional Block Diagrams

Lead Definitions

Symbol	Description
HIN	Logic input for high side gate driver output (HO), in phase (IR2181/IR21814)
LIN	Logic input for low side gate driver output (LO), in phase (IR2181/IR21814)
VSS	Logic Ground (IR21814 only)
V _B	High side floating supply
HO	High side gate drive output
V _S	High side floating supply return
V _{CC}	Low side and logic fixed supply
LO	Low side gate drive output
COM	Low side return

Lead Assignments

 8-Lead PDIP	 8-Lead SOIC
IR2181	IR2181S

 14-Lead PDIP	 14-Lead SOIC
IR21814	IR21814S

IR2181(4) (S) & (PbF)

International
IR Rectifier




Figure 1. Input/Output Timing Diagram




Figure 2. Switching Time Waveform Definitions




Figure 3. Delay Matching Waveform Definitions




Figure 4A. Turn-on Propagation Delay vs. Temperature




Figure 4B. Turn-on Propagation Delay vs. Supply Voltage




Figure 5A. Turn-off Propagation Delay vs. Temperature




Figure 5B. Turn-off Propagation Delay vs. Supply Voltage

IR2181(4) (S) & (PbF)

International
IR Rectifier




Figure 6A. Turn-on Rise Time vs. Temperature




Figure 6B. Turn-on Rise Time vs. Supply Voltage




Figure 7A. Turn-off Fall Time vs. Temperature




Figure 7B. Turn-off Fall Time vs. Supply Voltage

IR2181(4) (S) & (PbF)




Figure 8A. Logic "1" Input Voltage vs. Temperature




Figure 8B. Logic "1" Input Voltage vs. Supply Voltage




Figure 9A. Logic "0" Input Voltage vs. Temperature




Figure 9B. Logic "0" Input Voltage vs. Supply Voltage

IR2181(4) (S) & (PbF)

International
IR Rectifier




Figure 10A. High Level Output vs. Temperature




Figure 10B. High Level Output vs. Supply Voltage




Figure 11A. Low Level Output vs. Temperature




Figure 11B. Low Level Output vs. Supply Voltage




Figure 12A. Offset Supply Leakage Current vs. Temperature




Figure 12B. Offset Supply Leakage Current vs. V_B Boost Voltage




Figure 13A. V_{BS} Supply Current vs. Temperature




Figure 13B. V_{BS} Supply Current vs. V_{BS} Floating Supply Voltage

IR2181(4) (S) & (PbF)

International
IR Rectifier




Figure 14A. V_{CC} Supply Current
vs. V_{CC} Temperature




Figure 14B. V_{CC} Supply Current
vs. V_{CC} Supply Voltage




Figure 15A. Logic "1" Input Bias Current
vs. Temperature




Figure 15B. Logic "1" Input Bias Current
vs. Supply Voltage




Figure 16A. Logic "0" Input Bias Current vs. Temperature




Figure 16B. Logic "0" Input Bias Current vs. Supply Voltage




Figure 17. V_{CC} and V_{BS} Undervoltage Threshold (+) vs. Temperature




Figure 18. V_{CC} and V_{BS} Undervoltage Threshold (-) vs. Temperature

IR2181(4) (S) & (PbF)

International
IR Rectifier




Figure 19A. Output Source Current vs. Temperature




Figure 19B. Output Source Current vs. Supply Voltage




Figure 20A. Output Sink Current vs. Temperature






Figure 20B. Output Sink Current vs. Supply Voltage


IR2181(4) (S) & (PbF)




**Figure 21. IR2181 vs. Frequency (IRFBC20),
 $R_{gate} = 33\Omega$, $V_{cc} = 15V$**



**Figure 22. IR2181 vs. Frequency (IRFBC 30),
 $R_{gate} = 22\Omega$, $V_{cc} = 15V$**



**Figure 23. IR2181 vs. Frequency (IRFBC 40),
 $R_{gate} = 15\Omega$, $V_{cc} = 15V$**



**Figure 24. IR2181 vs. Frequency (IRFPE50),
 $R_{gate} = 10\Omega$, $V_{cc} = 15V$**

IR2181(4) (S) & (PbF)

International
IR Rectifier




Figure 25. IR21814 vs .Frequency (IRFBC 20),
 $R_{gate} = 33\Omega$, $V_{cc} = 15V$




Figure 26. IR21814 vs .Frequency (IRFBC 30),
 $R_{gate} = 22\Omega$, $V_{cc} = 15V$




Figure 27. IR21814 vs .Frequency (IRFBC 40),
 $R_{gate} = 15\Omega$, $V_{cc} = 15V$




Figure 28. IR21814 vs .Frequency (IRFPE50),
 $R_{gate} = 10\Omega$, $V_{cc} = 15V$

IR2181(4) (S) & (PbF)




Figure 29. IR2181s vs. Frequency (RFBC 20),
 $R_{gate} = 33\Omega$, $V_{cc} = 15V$




Figure 30. IR2181s vs. Frequency (RFBC 30),
 $R_{gate} = 22\Omega$, $V_{cc} = 15V$




Figure 31. IR2181s vs. Frequency (RFBC 40),
 $R_{gate} = 15\Omega$, $V_{cc} = 15V$




Figure 32. IR2181s vs. Frequency (RFPE50),
 $R_{gate} = 10\Omega$, $V_{cc} = 15V$

IR2181(4) (S) & (PbF)

International
IR Rectifier




Figure 33. IR21814s vs .Frequency (IRFBC 20),
 $R_{gate} = 33\Omega$, $V_{cc} = 15V$




Figure 34. IR21814s vs .Frequency (IRFBC 30),
 $R_{gate} = 22\Omega$, $V_{cc} = 15V$




Figure 35. IR21814s vs .Frequency (IRFBC 40),
 $R_{gate} = 15\Omega$, $V_{cc} = 15V$








Figure 36. IR21814s vs .Frequency (IRFPE50),
 $R_{gate} = 10\Omega$, $V_{cc} = 15V$

Case outlines




IR2181(4) (S) & (PbF)

International
IR Rectifier



LEADFREE PART MARKING INFORMATION



ORDER INFORMATION

Basic Part (Non-Lead Free)

8-Lead PDIP IR2181 order IR2181
 8-Lead SOIC IR2181S order IR2181S
 14-Lead PDIP IR21814 order IR21814
 14-Lead SOIC IR21814 order IR21814S

Leadfree Part

8-Lead PDIP IR2181 order IR2181PbF
 8-Lead SOIC IR2181S order IR2181SPbF
 14-Lead PDIP IR21814 order IR21814PbF
 14-Lead SOIC IR21814 order IR21814SPbF