

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









## **PolySwitch® PTC Devices**

**Overcurrent Protection Device** 

PRODUCT: LVR025S-1

DOCUMENT: SCD25109

REV LETTER: K

**REV DATE: JULY 26,2016** 

PAGE NO.: 1 OF 3

### **Specification Status: Released**

## Rated Operating Voltage at 20 °C (AC/DC):

Maximum Interrupt Voltage / Current at 20 °C (AC/DC):

265 V, 3.5 A 135 V, 20.0 A


#### **Insulating Material:**


Cured, Flame Retardant Epoxy Polymer

#### **Lead Material:**

22 AWG Sn-Plated Copper (0.64 mm [0.025"] nominal diameter)

#### Marking:





#### **TABLE I. DIMENSIONS:**

	Α		В		С		D		E	
	MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX
mm:		9.6	-	17.4	4.3	5.8	25.4			3.8
in:*		(0.38)		(0.69)	(0.17)	(0.23)	(1.00)			(0.15)

<sup>\*</sup>Rounded off approximation

#### TABLE II. PERFORMANCE RATINGS @ 20 °C:

HOLD CURRENT (A)	TRIP RESIST. CURRENT (Ω (A)		STANCE (Ω)	TIME TO TRIP(SEC) @ 1.25A	POST-TRIP RESISTANCE (Ω)	TRIPPED-STATE POWER DISSIPATION @ 265 V (W)
		R MIN	R MAX	MAX	MAX	TYP
0.25	0.56	1.3	2.1	18.5	3.8	1.5

<sup>\*</sup>Post Trip Resistance measured after one hour.

UL (File #E74889), CSA (File #78165), TUV, CQC Agency Recognitions:

Reference Documents: PS300

Precedence: This specification takes precedence over documents referenced herein.

Reference documents shall be the issue in effect on the date of invitation for bid. Effectivity:

Refer to Page 2 of this document for application limitations Warning:

#### **Materials Information**

**ROHS Compliant ELV Compliant Pb-Free** 

Directive 2002/95/EC Compliant

Directive 2000/53/EC Compliant





# PolySwitch® PTC Devices

**Overcurrent Protection Device** 

PRODUCT: LVR025S-1

DOCUMENT: SCD25109 REV LETTER: K

REV DATE: JULY 26,2016

PAGE NO.: 2 OF 3



### Warning: Application Limitations for the LVR Product Line

- 1. Users should independently evaluate the suitability of and test each product selected for their own application.
- 2. This product should not be used in an application where the maximum interrupt voltage or maximum interrupt current can be exceeded in a fault condition. Operation beyond the maximum ratings or improper use may result in device damage and possible electrical arcing and flame.
- 3. A PPTC device is not a fuse it is a nonlinear thermistor that limits current. Under a fault condition all PPTC devices go into a high resistance state but do not open circuit, so hazardous voltage may be present at PPTC locations.
- The devices are intended for protection against occasional overcurrent or overtemperature fault conditions and should not be used when repeated fault conditions or prolonged trip events are anticipated.
- 5. In most applications, power must be removed and the fault condition cleared in order to reset a PPTC device; however, under certain unusual conditions, a PPTC device may automatically reset. PPTC devices should not be used in an application where an automatic reset could create a safety hazard, such as garbage disposals and blenders. Appropriate qualification testing should be performed.
- 6. It is the responsibility of the user to determine the need for back up or fail safe protection to prevent damage that may occur in the event of abnormal function or failure of the PTC device.
- 7. Operation in circuits with a large inductance can generate a circuit voltage (Ldi/dt) above the rated voltage of a PPTC device. This product should not be used in an application where
  - the maximum interrupt voltage or maximum interrupt current can be exceeded by inductive spikes.
- 8. Devices are not recommended for reflow soldering.
- 9. Device performance can be impacted negatively if devices are handled in a manner inconsistent with recommended electronic, thermal, or mechanical procedures for electronic components.
- 10. PTC devices are not recommended to be installed in applications where the device is constrained such that its PTC properties are inhibited, for example in rigid potting materials
  - or in rigid housings, which lack adequate clearance to accommodate device expansion.
- 11. Contamination of the PTC material with certain silicone-based oils or some aggressive solvents can adversely impact the performance of the devices.



# PolySwitch® PTC Devices

**Overcurrent Protection Device** 

PRODUCT: LVR025S-1

DOCUMENT: SCD25109 REV LETTER: K

**REV DATE: JULY 26,2016** 

PAGE NO.: 3 OF 3

Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and shall not be used for, any purpose (including, without limitation, military, aerospace, medical, lifesaving, life-sustaining or nuclear facility applications, devices intended for surgical implant into the body, or any other application in which the failure or lack of desired operation of the product may result in personal injury, death, or property damage) other than those expressly set forth in applicable Littelfuse product documentation. Warranties granted by Littelfuse shall be deemed void for products used for any purpose not expressly set forth in applicable Littelfuse documentation. Littelfuse shall not be liable for any claims or damages arising out of products used in applications not expressly intended by Littelfuse as set forth in applicable Littelfuse documentation. The sale and use of Littelfuse products is subject to Littelfuse Terms and Conditions of Sale, unless otherwise agreed by Littelfuse.