



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Single LVDS/Anything-to-LVPECL Translator

MAX9375

General Description

The MAX9375 is a fully differential, high-speed, anything-to-LVPECL translator designed for signal rates up to 2GHz. The MAX9375's extremely low propagation delay and high speed make it ideal for various high-speed network routing and backplane applications.

The MAX9375 accepts any differential input signal within the supply rails and with minimum amplitude of 100mV. Inputs are fully compatible with the LVDS, LVPECL, HSTL, and CML differential signaling standards. Outputs are LVPECL and have sufficient current to drive 50Ω transmission lines.

The MAX9375 is available in an 8-pin μ MAX package and operates from a single +3.3V supply over the -40°C to +85°C temperature range.

Features

- ◆ Guaranteed 2GHz Switching Frequency
- ◆ Accepts LVDS/LVPECL/Anything Inputs
- ◆ 421ps (typ) Propagation Delays
- ◆ 30ps (max) Pulse Skew
- ◆ 2ps_{RMS} (max) Random Jitter
- ◆ Minimum 100mV Differential Input to Guarantee AC Specifications
- ◆ Temperature-Compensated LVPECL Output
- ◆ +3.0V to +3.6V Power-Supply Operating Range
- ◆ >2kV ESD Protection (Human Body Model)


Applications

Backplane Logic Standard Translation
 LAN
 WAN
 DSLAM
 DLC


Ordering Information

| PART | TEMP RANGE | PIN-PACKAGE |
|------------|----------------|-------------|
| MAX9375EUA | -40°C to +85°C | 8 μ MAX |

Functional Diagram



Pin Configuration



Single LVDS/Anything-to-LVPECL Translator

ABSOLUTE MAXIMUM RATINGS

| | | | |
|---|-----------------------------------|---|-----------------|
| V _{CC} to GND | -0.3V to +4.1V | Junction Temperature | +150°C |
| Inputs (IN, $\overline{\text{IN}}$) | -0.3V to (V _{CC} + 0.3V) | Storage Temperature Range | -65°C to +150°C |
| IN to $\overline{\text{IN}}$ | ±3.0V | ESD Protection | |
| Continuous Output Current | 50mA | Human Body Model (IN, $\overline{\text{IN}}$, OUT, $\overline{\text{OUT}}$) | ≥ 2kV |
| Surge Output Current | 100mA | Soldering Temperature (10s) | +300°C |
| Continuous Power Dissipation (T _A = +70°C) | | | |
| 8-Pin μ MAX (derate 5.9mW/°C above +70°C) | 470.6mW | | |
| θ_{JA} in Still Air | +170°C/W | | |

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

DC ELECTRICAL CHARACTERISTICS

(V_{CC} = +3.0V to +3.6V, differential input voltage |V_{ID1}| = 0.1V to 3.0V, input voltage (V_{IN}, V $\overline{\text{IN}}$) = 0 to V_{CC}, input common-mode voltage V_{CM} = 0.05V to (V_{CC} - 0.05V), LVPECL outputs terminated with 50 Ω ±1% to V_{CC} - 2.0V, T_A = -40°C to +85°C. Typical values are at V_{CC} = +3.3V, |V_{ID1}| = 0.2V, input common-mode voltage V_{CM} = 1.2V, T_A = +25°C, unless otherwise noted.) (Notes 1, 2, 3)

| PARAMETER | SYMBOL | CONDITIONS | -40°C | | | +25°C | | | +85°C | | | UNITS |
|--|--|--|-------------------------|-------------------------|-------------------------|-------------------------|-------------------------|-------------------------|-------------------------|-------------------------|-------------------------|---------|
| | | | MIN | TYP | MAX | MIN | TYP | MAX | MIN | TYP | MAX | |
| DIFFERENTIAL INPUTS (IN, $\overline{\text{IN}}$) | | | | | | | | | | | | |
| Differential Input Threshold | V _{THD} | | -100 | | +100 | -100 | | +100 | -100 | | +100 | mV |
| Input Current | I _{IN} , I $\overline{\text{IN}}$ | V _{IN} , V $\overline{\text{IN}}$ = V _{CC} or 0V | -20 | | +20 | -20 | | +20 | -20 | | +20 | μ A |
| Input Common-Mode Voltage | V _{CM} | Figure 1 | 0.05 | | V _{CC} - 0.05 | 0.05 | | V _{CC} - 0.05 | 0.05 | | V _{CC} - 0.05 | V |
| LVPECL OUTPUTS (OUT, $\overline{\text{OUT}}$) | | | | | | | | | | | | |
| Single-Ended Output High Voltage | V _{OH} | | V _{CC} - 1.085 | V _{CC} - 1.017 | V _{CC} - 0.880 | V _{CC} - 1.025 | V _{CC} - 0.983 | V _{CC} - 0.880 | V _{CC} - 1.025 | V _{CC} - 0.966 | V _{CC} - 0.880 | V |
| Single-Ended Output Low Voltage | V _{OL} | | V _{CC} - 1.830 | V _{CC} - 1.753 | V _{CC} - 1.620 | V _{CC} - 1.810 | V _{CC} - 1.710 | V _{CC} - 1.620 | V _{CC} - 1.810 | V _{CC} - 1.692 | V _{CC} - 1.620 | V |
| Differential Output Voltage | V _{OH} - V _{OL} | | 595 | 725 | | 595 | 725 | | 595 | 725 | | mV |
| POWER SUPPLY | | | | | | | | | | | | |
| Supply Current | I _{CC} | All pins open except V _{CC} , GND | | 10 | 18 | | 12 | 18 | | 14 | 18 | mA |

Single LVDS/Anything-to-LVPECL Translator

MAX9375

AC ELECTRICAL CHARACTERISTICS

($V_{CC} = +3.0V$ to $+3.6V$, differential input voltage $|V_{ID}| = 0.1V$ to $1.2V$, input frequency $\leq 1.34GHz$, differential input transition time = $125ps$ (20% to 80%), input voltage ($V_{IN}, \overline{V_{IN}}$) = 0 to V_{CC} , input common-mode voltage $V_{CM} = 0.05V$ to $(V_{CC} - 0.05V)$, outputs terminated with $50\Omega \pm 1\%$ to $V_{CC} - 2.0V$, $T_A = -40^\circ C$ to $+85^\circ C$. Typical values are at $V_{CC} = +3.3V$, $|V_{ID}| = 0.2V$, input common-mode voltage $V_{CM} = 1.2V$, $T_A = +25^\circ C$, unless otherwise noted.) (Note 4)

| PARAMETER | SYMBOL | CONDITIONS | MIN | TYP | MAX | UNITS |
|---|------------|------------------------------|-----|-----|-----|---------|
| Switching Frequency | f_{MAX} | $V_{OH} - V_{OL} \geq 250mV$ | 2.0 | 2.5 | | GHz |
| Propagation Delay Low to High | t_{PLH} | Figure 2 | 250 | 421 | 600 | ps |
| Propagation Delay High to Low | t_{PHL} | Figure 2 | 250 | 421 | 600 | ps |
| Pulse Skew $ t_{PLH} - t_{PHL} $ | t_{SKEW} | Figure 2 (Note 5) | | 6 | 30 | ps |
| Output Low-to-High Transition Time (20% to 80%) | t_R | Figure 2 | | 116 | 220 | ps |
| Output High-to-Low Transition Time (20% to 80%) | t_F | Figure 2 | | 116 | 220 | ps |
| Added Random Jitter | t_{RJ} | $f_{IN} = 1.34GHz$ (Note 6) | | 0.7 | 2 | ps(RMS) |

Note 1: Measurements are made with the device in thermal equilibrium. All voltages are referenced to ground except V_{THD} and V_{ID} .

Note 2: Current into a pin is defined as positive. Current out of a pin is defined as negative.

Note 3: DC parameters production tested at $T_A = +25^\circ C$ and guaranteed by design and characterization over the full operating temperature range.



Note 4: Guaranteed by design and characterization, not production tested. Limits are set at ± 6 sigma.

Note 5: t_{SKEW} is the magnitude difference of differential propagation delays for the same output under the same conditions; $t_{SKEW} = |t_{PHL} - t_{PLH}|$.

Note 6: Device jitter added to the input signal.

Typical Operating Characteristics



($V_{CC} = +3.3V$, differential input voltage $|V_{ID}| = 0.2V$, $V_{CM} = 1.2V$, input frequency = $500MHz$, outputs terminated with $50\Omega \pm 1\%$ to $V_{CC} - 2.0V$, $T_A = +25^\circ C$, unless otherwise noted.)



Single LVDS/Anything-to-LVPECL Translator

Typical Operating Characteristics (continued)

($V_{CC} = +3.3V$, differential input voltage $|V_{ID}| = 0.2V$, $V_{CM} = 1.2V$, input frequency = 500MHz, outputs terminated with $50\Omega \pm 1\%$ to $V_{CC} - 2.0V$, $T_A = +25^\circ C$, unless otherwise noted.)



Detailed Description

The MAX9375 is a fully differential, high-speed, anything-to-LVPECL translator designed for signal rates up to 2GHz. The MAX9375's extremely low propagation delay and high speed make it ideal for various high-speed network routing and backplane applications.

The MAX9375 accepts any differential input signals within the supply rails and with a minimum amplitude of 100mV. Inputs are fully compatible with the LVDS, LVPECL, HSTL, and CML differential signaling standards. Outputs are LVPECL and have sufficient current to drive 50Ω transmission lines.

Inputs

Inputs have a wide common-mode range of 0.05V to ($V_{CC} - 0.05V$), which accommodates any differential signals within rails, and requires a minimum of 100mV to switch the outputs. This allows the MAX9375 inputs to support virtually any differential signaling standard.

LVPECL Outputs

The MAX9375 outputs are emitter followers that require external resistive paths to a voltage source ($V_T = V_{CC} - 2.0V$ typ) more negative than worst-case V_{OL} for proper

Pin Description

| PIN | NAME | FUNCTION |
|------|------------------|--|
| 1, 8 | V_{CC} | Positive Supply. Bypass from V_{CC} to GND with 0.1 μF and 0.01 μF ceramic capacitors. Place the capacitors as close to the device as possible with the smaller value capacitor closest to the device. |
| 2 | IN | LVDS/Anything Noninverting Input |
| 3 | \overline{IN} | LVDS/Anything Inverting Input |
| 4, 5 | GND | Power Supply Ground Connection |
| 6 | \overline{OUT} | Differential LVPECL Inverting Output. Terminate with $50\Omega \pm 1\%$ to $V_{CC} - 2V$. |
| 7 | OUT | Differential LVPECL Noninverting Output. Terminate with $50\Omega \pm 1\%$ to $V_{CC} - 2V$. |

static and dynamic operation. When properly terminated, the outputs generate steady-state voltage levels, V_{OL} or V_{OH} with fast transition edges between state levels. Output current always flows into the termination during proper operation.

Single LVDS/Anything-to-LVPECL Translator

MAX9375

Applications Information

Output Termination

Terminate the outputs with 50Ω to $(V_{CC} - 2V)$ or use equivalent Thevenin terminations. Terminate $\overline{\text{OUT}}$ and OUT with identical termination on each for low-output distortion. When a single-ended signal is taken from the differential output, terminate both OUT and $\overline{\text{OUT}}$. Ensure that output currents do not exceed the current limits as specified in the *Absolute Maximum Ratings*. Under all operating conditions, the device's total thermal limits should be observed.

Supply Bypassing

Bypass V_{CC} to ground with high-frequency surface-mount ceramic $0.1\mu\text{F}$ and $0.01\mu\text{F}$ capacitors. Place the capacitors as close to the device as possible with the $0.01\mu\text{F}$ capacitor closest to the device pins.

Traces

Circuit board trace layout is very important to maintain the signal integrity of high-speed differential signals. Maintaining integrity is accomplished in part by reducing signal reflections and skew, and increasing common-mode noise immunity.

Signal reflections are caused by discontinuities in the 50Ω characteristic impedance of the traces. Avoid discontinuities by maintaining the distance between differential traces, not using sharp corners or using vias. Maintaining distance between the traces also increases common-mode noise immunity. Reducing signal skew is accomplished by matching the electrical length of the differential traces.




Figure 1. Input Definitions




Figure 2. Differential Input-to-Output Propagation Delay Timing Diagram

Chip Information


TRANSISTOR COUNT: 614

PROCESS: Bipolar

Single LVDS/Anything-to-LVPECL Translator

Package Information

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to www.maxim-ic.com/packages.)



8LUMAXDEFS

DALLAS SEMICONDUCTOR **MAXIM**
 PROPRIETARY INFORMATION
 TITLE: PACKAGE OUTLINE, 8L uMAX/uSOP
 APPROVAL: DOCUMENT CONTROL NO. 21-0036 REV. J 1/1

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

6 Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600